Colour Television

Chassis

ES1E

AA

Service
Service
Service



F_15040_000.eps
040405

Service Manual

Published by WS 0571 TV Service | Printed in the Netherlands | Subject to modification | EN 3122 785 15041

PHILIPS

1. Technical Specifications, Connections, and Chassis Overview

Index of this chapter:

Note: Data below can deviate slightly from the actual situation, due to the different set executions.

1.1 Technical Specifications

1.1.1 Vision

Display type	:	CRT, DV, RF
Screen size	:	28” (70 cm), 4:3
	:	28” (70 cm), 16:9
	:	29” (72 cm), 4:3
	:	32” (82 cm), 16:9
Tuning system	:	PLL
TV Colour systems	:	PAL B/G, D/K, I
	:	SECAM B/G, D/K, L/L’
Video playback	:	NTSC M/N 3.58, 4.43
	:	PAL B/G
	:	SECAM L/L’
Presets/channels	:	100/125 presets
Tuner bands	:	VHF
	:	UHF
	:	S-band
	:	Hyper-band

1.1.2 Sound

Sound systems	:	FM-mono
	:	AM-mono
	:	FM-stereo B/G
	:	NICAM B/G, D/K, I, L
	:	AV Stereo
Maximum power (W_{RMS})	:	2 x 10

1.1.3 Miscellaneous

Power supply:		
- Mains voltage (V_{AC})	:	230
- Mains frequency (Hz)	:	50 / 60
Ambient conditions:		
- Temperature range (°C)	:	-5 to +40
- Maximum humidity	:	95% R.H.
Power consumption		
- Normal operation (W)	:	≈ 160
- Stand-by (W)	:	< 1
Dimensions (WxHxD cm)	:	?x?x?
Weight (kg)	:	?

1.2 Connection Overview

Note: The following connector colour abbreviations are used (acc. to DIN/IEC 757): Bk= Black, Bu= Blue, Gn= Green, Gy= Grey, Rd= Red, Wh= White, and Ye= Yellow.

1.2.1 Front / Side Connections



Figure 1-1 Front and top control, side I/O connections

Cinch: Video CVBS - In, Audio - In

Ye	- Video CVBS	1 V_{PP} / 75 ohm
Wh	- Audio L	0.5 V_{RMS} / 10 kohm
Rd	- Audio R	0.5 V_{RMS} / 10 kohm

SVHS (Hosiden): Video Y/C - In

1	- Ground Y	Gnd
2	- Ground C	Gnd
3	- Video Y	1 V_{PP} / 75 ohm
4	- Video C	0.3 V_{PP}P / 75 ohm

Mini Jack: Audio Headphone - Out

Bk	- Head phone	32 - 600 ohm / 10 mW

1.2.2 Rear Connections



Figure 1-2 Rear connections

Aerial - In

-	- IEC-type (EU)	Coax, 75 ohm

Cinch: Video CVBS - Out, Audio - Out

Ye	- Video CVBS	1 V_{PP} / 75 ohm
Wh	- Audio L	0.5 V_{RMS} /10 kohm
Rd	- Audio R	0.5 V_{RMS} / 10 kohm

Service Connector (ComPair)

1	- SDA-S	I^2C Data (0 - 5 V)
2	- SCL-S	I^2C Clock (0 - 5 V)
3	- Ground	Gnd

EXT1: Video RGB - In, CVBS - In/Out, Audio - In/Out



Figure 1-3 SCART connector

1	- Audio R	0.5 V_{RMS} / 1 kohm	⊖→
2	- Audio R	0.5 V_{RMS} / 10 kohm	→⊖
3	- Audio L	0.5 V_{RMS} / 1 kohm	⊖→
4	- Ground Audio	Gnd	⏚
5	- Ground Blue	Gnd	⏚
6	- Audio L	0.5 V_{RMS} / 10 kohm	→⊖
7	- Video Blue/U	0.7 V_{PP} / 75 ohm	→⊖
8	- Function Select	0 - 2 V: INT	
		4.5 - 7 V: EXT 16:9	
		9.5 - 12 V: EXT 4:3	→⊖
9	- Ground Green	Gnd	⏚
10	- n.c.		
11	- Video Green/Y	0.7 V_{PP} / 75 ohm	→⊖
12	- n.c.		
13	- Ground Red	Gnd	⏚
14	- Ground FBL	Gnd	⏚
15	- Video Red/V	0.7 V_{PP} / 75 ohm	→⊖
16	- Status/FBL	0 - 0.4 V: INT	
		1 - 3 V: EXT / 75 ohm	→⊖
17	- Ground Video	Gnd	⏚
18	- Ground Video	Gnd	⏚
19	- Video CVBS	1 V_{PP} / 75 ohm	⊖→
20	- Video CVBS	1 V_{PP} / 75 ohm	→⊖
21	- Shield	Gnd	⏚

EXT2: Video YC - In, CVBS - In/Out, Audio - In/Out



Figure 1-4 SCART connector

1	- Audio R	0.5 V_{RMS} / 1 kohm	⊖→
2	- Audio R	0.5 V_{RMS} / 10 kohm	→⊖
3	- Audio L	0.5 V_{RMS} / 1 kohm	⊖→
4	- Ground Audio	Gnd	⏚
5	- Ground Blue	Gnd	⏚
6	- Audio L	0.5 V_{RMS} / 10 kohm	→⊖
7	- C-FRONT	0.7 V_{PP} / 75 ohm	→⊖
8	- Function Select	0 - 2 V: INT	
		4.5 - 7 V: EXT 16:9	
		9.5 - 12 V: EXT 4:3	→⊖
9	- Ground Green	Gnd	⏚
10	- Easylink P50	0 - 5 V / 4.7 kohm	⊖→⊖→
11	- n.c.		
12	- n.c.		
13	- Ground Red	Gnd	⏚
14	- Ground Data	Gnd	⏚
15	- C	0.7 V_{PP} / 75 ohm	→⊖
16	- n.c.		
17	- Ground Video	Gnd	⏚
18	- Ground FBL	Gnd	⏚
19	- Video CVBS	1 V_{PP} / 75 ohm	⊖→
20	- Video CVBS/Y	1 V_{PP} / 75 ohm	→⊖
21	- Shield	Gnd	⏚

1.3 Chassis Overview



Figure 1-5 PWB location

2. Safety Instructions, Warnings, and Notes

Index of this chapter:

2.1 Safety Instructions

Safety regulations require the following **during** a repair:

- Connect the set to the Mains (AC Power) via an isolation transformer (> 800 VA).
- Replace safety components, indicated by the symbol ⚠, only by components identical to the original ones. Any other component substitution (other than original type) may increase risk of fire or electrical shock hazard.
- Wear safety goggles when you replace the CRT.

Safety regulations require that **after** a repair, the set must be returned in its original condition. Pay in particular attention to the following points:

- General repair instruction: as a strict precaution, we advise you to re-solder the solder connections through which the horizontal deflection current flows. In particular this is valid for the:
  1. Pins of the line output transformer (LOT).
  2. Fly-back capacitor(s).
  3. S-correction capacitor(s).
  4. Line output transistor.
  5. Pins of the connector with wires to the deflection coil.
  6. Other components through which the deflection current flows.

Note: This re-soldering is advised to prevent bad connections due to metal fatigue in solder connections, and is therefore only necessary for television sets more than two years old.

- Route the wire trees and EHT cable correctly and secure them with the mounted cable clamps.
- Check the insulation of the Mains (AC Power) lead for external damage.
- Check the strain relief of the mains (AC Power) cord for proper function, to prevent the cord from touching the CRT, hot components, or heat sinks.
- Check the electrical DC resistance between the Mains (AC Power) plug and the secondary side (only for sets that have a Mains (AC Power) isolated power supply):
  1. Unplug the Mains (AC Power) cord and connect a wire between the two pins of the Mains (AC Power) plug.
  2. Set the Mains (AC Power) switch to the "on" position (keep the Mains (AC Power) cord unplugged!).
  3. Measure the resistance value between the pins of the Mains (AC Power) plug and the metal shielding of the tuner or the aerial connection on the set. The reading should be between 4.5 Mohm and 12 Mohm.
  4. Switch "off" the set, and remove the wire between the two pins of the Mains (AC Power) plug.
- Check the cabinet for defects, to prevent touching of any inner parts by the customer.

2.2 Maintenance Instructions

We recommend a maintenance inspection carried out by qualified service personnel. The interval depends on the usage conditions:

- When a customer uses the set under normal circumstances, for example in a living room, the recommended interval is three to five years.
- When a customer uses the set in an environment with higher dust, grease, or moisture levels, for example in a kitchen, the recommended interval is one year.
- The maintenance inspection includes the following actions:
  1. Perform the “general repair instruction” noted above.
  2. Clean the power supply and deflection circuitry on the chassis.
  3. Clean the picture tube panel and the neck of the picture tube.

2.3 Warnings

- In order to prevent damage to ICs and transistors, avoid all high voltage flashovers. In order to prevent damage to the picture tube, use the method shown in figure “Discharge picture tube”, to discharge the picture tube. Use a high voltage probe and a multi-meter (position V_{DC}). Discharge until the meter reading is 0 V (after approx. 30 s).



Figure 2-1 Discharge picture tube

- All ICs and many other semiconductors are susceptible to electrostatic discharges (ESD). Careless handling during repair can reduce life drastically. Make sure that, during repair, you are connected with the same potential as the mass of the set by a wristband with resistance. Keep components and tools also at this same potential. Available ESD protection equipment:
  – Complete kit ESD3 (small tablemat, wristband, connection box, extension cable and earth cable) 4822 310 10671.
  – Wristband tester 4822 344 13999.
- Be careful during measurements in the high voltage section.
- Never replace modules or other components while the unit is switched "on".
- When you align the set, use plastic rather than metal tools. This will prevent any short circuits and prevents circuits from becoming unstable.

2.4 Notes

2.4.1 General

- Measure the voltages and waveforms with regard to the chassis (= tuner) ground (⏚), or hot ground (⏚), depending on the tested area of circuitry. The voltages and waveforms shown in the diagrams are indicative. Measure them in the Service Default Mode (see chapter 5) with a colour bar signal and stereo sound (L: 3 kHz, R: 1 kHz unless stated otherwise) and picture carrier at 475.25 MHz for PAL, or 61.25 MHz for NTSC (channel 3).
- Where necessary, measure the waveforms and voltages with (⊓) and without (⊼) aerial signal. Measure the voltages in the power supply section both in normal operation (⏻) and in stand-by (⏻). These values are indicated by means of the appropriate symbols.
- The semiconductors indicated in the circuit diagram and in the parts lists, are interchangeable per position with the semiconductors in the unit, irrespective of the type indication on these semiconductors.

- Manufactured under license from Dolby Laboratories. “Dolby”, “Pro Logic” and the “double-D symbol”, are trademarks of Dolby Laboratories.

2.4.2 Schematic Notes

- All resistor values are in ohms, and the value multiplier is often used to indicate the decimal point location (e.g. 2K2 indicates 2.2 kohm).
- Resistor values with no multiplier may be indicated with either an "E" or an "R" (e.g. 220E or 220R indicates 220 ohm).
- All capacitor values are given in micro-farads (μ= x10^{-6}), nano-farads (n= x10^{-9}), or pico-farads (p= x10^{-12}).
- Capacitor values may also use the value multiplier as the decimal point indication (e.g. 2p2 indicates 2.2 pF).
- An "asterisk" (*) indicates component usage varies. Refer to the diversity tables for the correct values.
- The correct component values are listed in the Spare Parts List. Therefore, always check this list when there is any doubt.

2.4.3 Rework on BGA (Ball Grid Array) ICs

General
Although (LF)BGA assembly yields are very high, there may still be a requirement for component rework. By rework, we mean the process of removing the component from the PWB and replacing it with a new component. If an (LF)BGA is removed from a PWB, the solder balls of the component are deformed drastically so the removed (LF)BGA has to be discarded.

Device Removal
As is the case with any component that is being removed, it is essential when removing an (LF)BGA, that the board, tracks, solder lands, or surrounding components are not damaged. To remove an (LF)BGA, the board must be uniformly heated to a temperature close to the reflow soldering temperature. A uniform temperature reduces the risk of warping the PWB. To do this, we recommend that the board is heated until it is certain that all the joints are molten. Then carefully pull the component off the board with a vacuum nozzle. For the appropriate temperature profiles, see the IC data sheet.

Area Preparation
When the component has been removed, the vacant IC area must be cleaned before replacing the (LF)BGA.
Removing an IC often leaves varying amounts of solder on the mounting lands. This excessive solder can be removed with either a solder sucker or solder wick. The remaining flux can be removed with a brush and cleaning agent.
After the board is properly cleaned and inspected, apply flux on the solder lands and on the connection balls of the (LF)BGA.
Note: Do not apply solder paste, as this has been shown to result in problems during re-soldering.

Device Replacement
The last step in the repair process is to solder the new component on the board. Ideally, the (LF)BGA should be aligned under a microscope or magnifying glass. If this is not possible, try to align the (LF)BGA with any board markers. So as not to damage neighbouring components, it may be necessary to reduce some temperatures and times.

More Information
For more information on how to handle BGA devices, visit this URL: *www.atyourservice.ce.philips.com* (needs subscription, not available for all regions). After login, select “Magazine”, then go to “Repair Downloads”. Here you will find Information on how to deal with BGA-ICs.

2.4.4 Lead-free Solder

Philips CE is producing lead-free sets (PBF) from 1.1.2005 onwards.

Identification: The bottom line of a type plate gives a 14-digit serial number. Digits 5 and 6 refer to the production year, digits 7 and 8 refer to production week (in example below it is 1991 week 18).



E_06532_024.eps
230205

Figure 2-2 Serial number example

Regardless of the special lead-free logo (which is not always indicated), one must treat all sets from this date onwards according to the rules as described below.

Figure 2-3 Lead-free logo

Due to lead-free technology some rules have to be respected by the workshop during a repair:

- Use only lead-free soldering tin Philips SAC305 with order code 0622 149 00106. If lead-free solder paste is required, please contact the manufacturer of your soldering equipment. In general, use of solder paste within workshops should be avoided because paste is not easy to store and to handle.
- Use only adequate solder tools applicable for lead-free soldering tin. The solder tool must be able:
  - To reach a solder-tip temperature of at least 400°C.
  - To stabilise the adjusted temperature at the solder-tip.
  - To exchange solder-tips for different applications.
- Adjust your solder tool so that a temperature of around 360°C - 380°C is reached and stabilised at the solder joint. Heating time of the solder-joint should not exceed ~ 4 sec. Avoid temperatures above 400°C, otherwise wear-out of tips will increase drastically and flux-fluid will be destroyed. To avoid wear-out of tips, switch “off” unused equipment or reduce heat.
- Mix of lead-free soldering tin/parts with leaded soldering tin/parts is possible but PHILIPS recommends strongly **to avoid** mixed regimes. If this cannot be avoided, carefully clean the solder-joint from old tin and re-solder with new tin.
- Use only original spare-parts listed in the Service-Manuals. Not listed standard material (commodities) has to be purchased at external companies.
- Special information for lead-free BGA ICs: these ICs will be delivered in so-called "dry-packaging" to protect the IC against moisture. This packaging may only be opened shortly before it is used (soldered). Otherwise the body of the IC gets "wet" inside and during the heating time the structure of the IC will be destroyed due to high (steam-) pressure inside the body. If the packaging was opened before usage, the IC has to be heated up for some hours (around 90°C) for drying (think of ESD-protection!).
  Do not re-use BGAs at all!

- For sets produced before 1.1.2005, containing leaded soldering tin and components, all needed spare parts will be available till the end of the service period. For the repair of such sets nothing changes.

In case of doubt whether the board is lead-free or not (or with mixed technologies), you can use the following method:

- Always use the highest temperature to solder, when using SAC305 (see also instructions below).
- De-solder thoroughly (clean solder joints to avoid the mixing of two alloys).

Caution: For BGA-ICs, you **must** use the correct temperature-profile, which is coupled to the 12NC. For an overview of these profiles, visit the website *www.atyourservice.ce.philips.com* (needs subscription, but is not available for all regions).
You will find this and more technical information within the "Magazine", chapter "Repair Downloads".
For additional questions please contact your local repair help desk.

2.4.5 Practical Service Precautions

- **It makes sense to avoid exposure to electrical shock.** While some sources are expected to have a possible dangerous impact, others of quite high potential are of limited current and are sometimes held in less regard.
- **Always respect voltages**. While some may not be dangerous in themselves, they can cause unexpected reactions that are best avoided. Before reaching into a powered TV set, it is best to test the high voltage insulation. It is easy to do, and is a good service precaution.

3. Directions for Use

You can download this information from the following websites:
http://www.philips.com/support
http://www.p4c.philips.com

4. Mechanical Instructions

Index of this chapter:

Note: Figures below can deviate slightly from the actual situation, due to the different set executions.

4.1 Service Connector (for ComPair)

For service diagnostics with ComPair, it is not necessary to disassemble the set. You only have to connect the ComPair interface box, via the appropriate cable, to the service connector (on the rear of the set, see figure 1-2), and start the program (see also chapter 5 "Service Modes, Error Codes, and Fault Finding ").

4.2 Set Disassembly

Follow the disassemble instructions in described order.

4.2.1 Rear Cover Removal

Warning: disconnect the mains power cord before you remove the rear cover.

1. Remove all the fixation screws of the rear cover.
2. Now the rear cover can be removed.

4.3 Service Positions

This chassis has several predefined service positions, for better accessibility. They are explained below in more detail.

4.3.1 Large Signal Panel (LSP)

Component Side LSP

For better accessibility of the LSP, do the following (see Figure “Service position 1”):

1. Simultanuously do the following: a) pull the two plastic locking handles at the mid left and mid right side of the bracket gently backwards to unlock the bracket, and b) loosen the bracket from the bottom tray, by pulling it backwards. N.B.: You do not need to pull the other two locking handles backwards.
2. Remove the LSP-bracket from the bottom tray by lifting it upwards.
3. Hook the bracket in the first row of fixation holes of the bottom tray. In other words, reposition the bracket from [1] to [2].



Figure 4-1 Service position 1

Solder Side LSP

To get access to the bottom side (solder side) of the LSP, do the following (see figure 4-1):

1. Remove the connector of the mains cable (coming from the mains switch-module) from the LSP.
2. Remove the cable (connector) from the side I/O panel.
3. Release some wiring from their fixation clamps, in order to get room for repositioning the LSP.
4. Flip the LSP 90 degrees clockwise [2], and place it in the fixation hole at the left side of the bottom tray [3].
5. Push the LSP forward to fix it. (Alternatively, the LSP may also be placed on your work bench without being positioned in its fixation hole, or it may even be removed from the bracket for better accessibility, see “Assy / Board Removal: Large Signal Panel (LSP)” on the next pages.)



Figure 4-2 Service position 2

4.3.2 Small Signal Board (SSB)

In fact, there is no predefined service position for the SSB. Most test points are located on the A-side (side that is facing the tuner). If you have to replace ICs, you must take the complete SSB module out of the SIMM-connector.

Notes:

- For better access to the SSB, it is possible to order an “extension tool” with cables. You can use this service extension tool to connect a Small Signal Board (SSB) of an ES1E, A02, A10, or EMG (EMx) chassis, via two “IDE” cables to the SIMM connector in the set. In this way, you can service the SSB more easily outside the TV set. You can order this tool under 12nc: 9965 000 14526.
- If necessary for the measurement, you can put the LSP in “service position 2” (as described above).

4.4 Assy / Board Removal

Sometimes, it can be necessary to swap a complete assy or Printed Wiring Board (PWB). How that can be done is explained below.

4.4.1 Top Control Assy/Panel



Figure 4-3 Top control panel

1. Remove the two fixation screws that hold the panel.
2. Pull the board backwards (i.e., release it from the front hinge).
3. The board can be lifted out of the bracket after releasing the two fixation clamps at the connector side.

4.4.2 Side I/O Assy and Panel



Figure 4-4 Side-I/O panel

1. The complete side I/O-assembly can be removed by unscrewing the two fixation screws.
2. The board can be lifted out of the bracket after releasing the two fixation clamps.

4.4.3 Mains Switch Assy/Panel

4.4.4 Accessing the Mains Switch/LED panel



Figure 4-5 Mains Switch/LED panel

1. Release the two fixation clamps (1) by pushing them upward.
2. At the same time, the complete assy must be pulled backward (2).
3. If the board has to be removed, release the two clamps at the sides of the bracket and lift the panel out (3).

4.4.5 Small Signal Board (SSB)



Figure 4-6 SSB removal

1. Push the top of the SSB towards the LOT [1].
2. Due to the pressure, the two metal clamps at both sides of the SIMM-connector will release [2].
3. Take the complete SSB out [3].

4.4.6 Large Signal Panel (LSP)

1. Remove the SSB (see paragraph “Small Signal Board (SSB)” above).
2. Remove the two fixation screws from the large plastic bracket on the right hand side of the LSP (above the EHT shield), and remove the bracket, after releasing the EHT cable and the CRT cables from the fixation clamps on this bracket.
3. Disconnect the other cables (loudspeaker, mains, etc.) from the LSP, and release some cables from their fixation clamps.
4. Press the fixation clamp on the left front side of the LSP-bracket (close to the white arrow/loudspeaker connector) to unlock the LSP, and tilt it upwards (the board hinges at the right side).
5. Remove the board from the bracket by unhooking it from its fixation clamps on the right side.

4.5 Set Re-assembly

To re-assemble the whole set, do all processes in reverse order.
Be sure that, before the rear cover is mounted:

- The mains cord is postioned correctly in its guiding brackets (make sure that the strain relief will function correctly!).
- All wires/cables are returned in their original positions. This is very important, in view of the “hot” and “EHT” areas of the set.

5. Service Modes, Error Codes, and Fault Finding

Index of this chapter:

5.1 Test Points

See chapter 6 " Block Diagrams, Testpoint Overview, and Waveforms".

Perform measurements under the following conditions:
- Service Default Mode.
- Video: colour bar signal.
- Audio: 3 kHz left, 1 kHz right.

5.2 Service Modes

Service Default Mode (SDM) and Service Alignment Mode (SAM) offer several features for the service technician, while the Customer Service Mode (CSM) is used for communication between a Philips Customer Care Centre (P3C) and a customer.

There is also the option of using ComPair, a hardware interface between a computer (see requirements below) and the TV chassis. It offers the ability of structured troubleshooting, test pattern generation, error code reading, software version readout, and software upgrading.
Minimum requirements: a Pentium processor, Windows 95/ 98, and a CD-ROM drive (see also paragraph “ComPair”).

5.2.1 Service Default Mode (SDM)

Purpose
- To create a pre-defined setting for measurement purposes.
- To override SW protections (only when SDM is activated via shorting the SDM pins on the SSB).
- To start the blinking LED procedure.
- Inspection of error buffer, life timer, and software version.

Specifications
- Tuning frequency: 475.25 MHz for PAL/SECAM.
- Colour system: SECAM L for France or PAL B/G for the rest of Europe.
- All picture settings at 50 % (brightness, colour, contrast).
- All sound settings at 50 %, except volume at 25 %.
- All service-unfriendly modes (if present) are disabled, like:
  - (Sleep) timer.
  - Child/parental lock.
  - Blue mute.
  - Automatic volume limiter (AVL).
  - Auto switch-off (when no video signal was received for 10 minutes).
  - Skip/blank of non-favourite pre-sets.
  - Hotel or hospital mode.
  - Local keyboard block.
  - Smart modes.
  - Auto store of personal presets.
  - Auto user menu time-out.

How to Activate SDM
Use one of the following methods:
- Use the standard RC-transmitter and key in the code “**062596**”, directly followed by the “MENU” button.
  Note: It is possible that, together with the SDM, the main menu will appear. To switch it "off", push the “MENU” button again.
- Short circuit, during switch "on" of the set, the two solder pads on the SSB with the indication “FOR SERVICE”. These solder pads are located at the "tuner" side of the SSB (just above the large BGA IC).
  Caution: If the SDM is activated via these pins, all the software-controlled protections are de-activated for 15 s. When these 15 s are expired, the set will shutdown to protection mode.
- Use the DST-emulation feature of ComPair.

After activating this mode:
- “SDM” will appear in the upper right corner of the screen.
- Also, the error buffer, operating hours, and software version are displayed (can be toggled "on/off" with the "STATUS / OSD / [i+]" button).
- Blinking LED procedure will be started.
- All software-controlled protections are overridden for 15 s. When these 15 s are expired, the set will shutdown to protection mode.

Contents of SDM:
- **HRS.** Displays the accumulated total of operation hours (not the standby hours) in hexadecimal value.
- **SW.** Displays the date of the software and the software version of the ROM;
  example: A2EU04-5.10 = AAABBC-X.YY.
  - **AAA**= chassis name.
  - **BB**= region and/or function name: E= Europe, A= Asia Pacific, U= NAFTA, L= LATAM, B= Basic, T= Top, P= PAL, N= NTSC, S= Stereo, M= Mono.
  - **C**= the language cluster number.
  - **X.Y**= the software version, where X is the main version number (different numbers are not compatible with one another) and Y is the sub version number (a higher number is always compatible with a lower number).
- **ERR** (followed by maximal 8 errors). The most recent error is displayed at the upper left (for an error explanation see paragraph “Error Codes”).

How to Navigate
- When you press the “MENU” button on the RC transmitter, the set will toggle between the SDM and the normal user menu (with the SDM mode still active in the background).
- When you press the “STATUS / OSD / [i+]” button on the RC transmitter, the set will toggle between the full SDM screen or a screen with only the text "SDM" displayed on it. This mode is useful when performing measurements, then the OSD info will not generate interference.

How to Exit SDM
Use one of the following methods:
- Switch the set to STANDBY via a standard customer RC-transmitter (the error buffer is erased).
- Via a standard customer RC-transmitter: key in “00”-sequence (the error buffer is **not** erased).

5.2.2 Service Alignment Mode (SAM)

Purpose
- To perform alignments.
- To change option settings.
- To easily identify the used software version.
- To view operation hours.
- To display / clear the error code buffer.

Specifications
- Operating hours counter.
- Software version.

- Option settings.
- Error buffer reading and erasing.
- Software alignments.
- Disable service unfriendly modes.

How to Activate SAM

Use one of the following methods:

- Via a standard RC transmitter: key in the code "**062596**" directly followed by the "STATUS / OSD / [i+]" button.
- Use the DST-emulation feature of ComPair.

After activating this mode, "SAM" will appear in the upper right corner of the screen.

Contents of SAM:

- **HRS.** Displays the accumulated total of operation hours (not the standby hours) in hexadecimal value
  Note: every time the set is switched "on" by the mains switch or the RC, the timer is increased by 0.5.
- **SW ID.** Displays the software version of the ROM
  example: A2EU04-5.10 = AAABBC-X.YY.
  - **AAA**= chassis name.
  - **BB**= region and/or function name: E= Europe, A= Asia Pacific, U= NAFTA, L= LATAM, B= Basic, T= Top, P= PAL, N= NTSC, S= Stereo, M= Mono.
  - **C**= the language cluster number.
  - **X.Y**= the software version, where X is the main version number (different numbers are not compatible with one another) and Y is the sub version number (a higher number is always compatible with a lower number).
- **ERR** (followed by maximal 8 errors). The most recent error is displayed at the upper left (for an error explanation see paragraph "Error Codes").
- **OPTIONS.** Extra features for Service.
- **CLEAR ERRORS.** When you press the "OK" button, the error buffer is reset.
- **AKB.** Disable (off) or enable (on) the "black current loop" (AKB= Auto Kine Bias). For Vg2 alignment.
- **TUNER.** This will activate the "TUNER" alignments sub-menu.
- **WHITE TONE.** This will activate the "WHITE TONE" alignments sub-menu.
- **GEOMETRY.** This will activate the "GEOMETRY" alignments sub-menu.
- **SOUND.** This will activate the "SOUND" alignments sub-menu.
- **SMART SETTINGS.** This will activate the "SMART SETTINGS" alignments sub-menu.
- **STORE.** This will save the new settings/alignments.
- **EEPROM TEST.** This will report if the SW checksum is OK. Convenient after SW upgrading.
- **VID RAM TEST.** This will check the continuity of the address bus and data bus of the Video RAM.
- **VG2.** This feature is not implemented yet. **Do not use.**

Note: Alignments are described in chapter 8 "Alignments".

How to Navigate

- In SAM, you can select the menu items with the "CURSOR UP/DOWN" key on the RC-transmitter. The selected item will be highlighted. When not all menu items fit on the screen, move the "CURSOR UP/DOWN" key to display the next/previous menu items.
- With the "CURSOR LEFT/RIGHT" keys, it is possible to:
  - (De) activate the selected menu item.
  - Change the value of the selected menu item.
  - Activate the selected submenu.
- When you press the "MENU" button on the RC transmitter, the set will toggle between the SAM and the normal user menu (with the SAM mode still active in the background).

How to Exit SAM

Use one of the following methods:

- Switch the set to STANDBY via the RC-transmitter (the error buffer is erased).
- Via a standard customer RC-transmitter: key in "00"-sequence (the error buffer is **not** erased).

5.2.3 Customer Service Mode (CSM)

Purpose

When a customer is having problems with his TV-set, he can call his dealer or the Philips helpdesk (P3C). The service technician can than ask the customer to activate the CSM, in order to identify the status of the set. Now, the service technician can judge the severity of the complaint. In many cases, he can advise the customer how to solve the problem, or he can decide if it is necessary to visit the customer.
The CSM is a **read only** mode; therefore, modifications in this mode are not possible.

How to Activate CSM

Use one of the following methods:

- Press the "MUTE" button on the RC-transmitter **simultaneously** with any key on the TV for at least 4 seconds.
- Key in the code "**123654**" via the standard RC transmitter.

Notes:

- Activation of the CSM is only possible if there is no (user) menu on the screen!
- During CSM, sound volume is set to 25% of the scale, "Smart Sound" is set to "Theatre" mode, and "Smart Picture" is set to "Rich/Movies" mode temporarily to ensure a good picture and sound of the working set. After leaving CSM, the original settings are restored.

How to Navigate

By means of the "CURSOR-DOWN/UP" knob on the RC-transmitter, you can navigate through the menus.

Contents of CSM

The following information is displayed on screen:

- Text "CSM" on the first line.
- Line number for every line (to make CSM language independent).
- Option code information.
- Configuration information.
- Service-unfriendly modes.

1. **SET TYPE.** Type/model number (if present) according to the Philips standard (example: 28PW8720/12).
2. **SOFTWARE.** Software version AAABBC-X.YY.
3. **HOURS ON.** Operating hours (in hexadecimal code).
4. **CODE1.** Shows the contents of the error buffer (the word "error" may not be used on this screen, instead "code1" and "code2" is used).
5. **CODE2.** Idem.
6. **OPTION1.** Option code information.
7. **OPTION2.** Idem.
8. **OPTION3.** Idem.
9. **OPTION4.** Idem.
10. **SIGNAL.** "Ident" signal present or not present (VID status bit in MPIF) on selected source.
11. **TIMER.** Timer is activated (in "FEATURE" menu) or deactivated.
12. **CHANNEL.** Child Lock (if present) is activated or deactivated (i.e. when local keyboard is locked).
13. **PRESET.** (If present). Current channel is defined as skipped or non-preferred.
14. **HOTELMODE.** Shows if the HOTEL mode is activated or deactivated (only for Europe and AP).
15. **SOURCE.** Selected source before entry of CSM; XXX (channel no.), external source name (i.e. AV1, CVI, EXT1, etc...).

16. **SOUND.** Selected SOUND mode; "XX"= MONO, NICAM, STEREO, L1 (Language 1), L2 (Language 2), SAP, VIRTUAL, or DIGITAL prior entry to CSM.
17. **VOLUME.** Volume level before entry of CSM (typ. 00..100).
18. **BALANCE.** Balance level before entry of CSM (typ. -50..50).
19. **BRIGHTNESS.** Brightness level before entry of CSM (typ. 00..100).
20. **COLOUR.** Colour level before entry of CSM (typ. 00..100).
21. **CONTRAST.** Contrast level before entry of CSM (typ. 00..100).
22. **HUE** (if present)**.** Hue level before entry of CSM (typ. -50..100).

How to exit CSM

Use one of the following methods:

- After you press a key on the RC-transmitter (with exception of the “CHANNEL”, “VOLUME” and digit (0-9) keys), or
- After you switch the TV-set “OFF” with the mains switch.
- After 15 min. no RC or local keyboard actions.

5.3 Problems and Solving Tips (related to CSM)

Note: The problems described below are all related to the TV settings. The procedures to change the value (or status) of the different settings are described above. New value(s) are automatically stored.

5.3.1 Picture Problems

Picture too Dark

1. Press SMART PICTURE on the RC. In case the picture improves, increase the “Brightness” or the “Contrast” value. The new value(s) are automatically stored (in “personal” pre-set) for all TV channels.
2. Check in CSM lines BRIGHTNESS and/or CONTRAST. If the value of line BRIGHTNESS is low (< 10) or the value of line CONTRAST is low (< 10), increase them.

Picture too Bright

1. Press SMART PICTURE on the RC. In case the picture improves, decrease the “Brightness” or the “Contrast” value. The new value(s) are automatically stored (in “personal” pre-set) for all TV channels.
2. Check in CSM lines BRIGHTNESS and/or CONTRAST. If the value of line BRIGHTNESS is high (> 50) or the value of line CONTRAST is high (> 50), decrease the “Brightness” or the “Contrast” value.

White Line Around Picture Elements and Text

1. Press SMART PICTURE on the RC. In case the picture improves, decrease the “Sharpness” value. The new value is automatically stored (in “personal” pre-set) for all TV channels.
2. Check in CSM line SHARPNESS. Decrease the “Sharpness” value. The new value is automatically stored for all TV channels.

No Picture

Check in CSM line 10 (**SIGNAL**). In case this line shows NO SIGNAL, check the aerial cable/aerial system.

Blue Picture

No proper signal is received. Check the aerial cable/aerial system.

Blue Picture and/or Unstable Picture

A scrambled or coded signal is received.

Black and White Picture

Check in CSM line COLOR. In case the value is low (< 10), increase the “Color” value. The new value is automatically stored for all TV channels.

No Colours/colour Lines around Picture Elements or Colours not Correct or Unstable Picture

1. Check in CSM line SYSTEM. If a “strange” system pops up, something has gone wrong during installation. Re-install the channel.
2. In case line SYSTEM is “FRANCE”, the installed system for this pre-set is SECAM, while PAL is required. Install the required program again: open the installation menu and perform manual installation. Select system “West Europe”.

Menu Text not Sharp Enough

1. Press “SMART PICTURE”. In case picture improves, decrease the "Contrast" value. The new value(s) are automatically stored for all TV channels.
2. Check in CSM line CONTRAST. If the value of this line is high (> 50), decrease the "Contrast" value.

5.3.2 Sound Problems

No Sound from Left and Right Speaker

Check in CSM line VOLUME. If the value is high, increase the value of “Volume”. The new value(s) are automatically stored (in “personal” pre-set) for all TV channels.

Sound too Loud for Left and Right Speaker

Check in CSM line VOLUME. If the value is low, decrease the value of “Volume”. The new value(s) are automatically stored (in “personal” pre-set) for all TV channels.

5.4 ComPair

5.4.1 Introduction

ComPair (Computer Aided Repair) is a service tool for Philips Consumer Electronics products. ComPair is a further development on the European DST (service remote control), which allows faster and more accurate diagnostics. ComPair has three big advantages:

- ComPair helps you to quickly get an understanding on how to repair the chassis in a short time by guiding you systematically through the repair procedures.
- ComPair allows very detailed diagnostics (on I^2C level) and is therefore capable of accurately indicating problem areas. You do not have to know anything about I^2C commands yourself because ComPair takes care of this.
- ComPair speeds up the repair time since it can automatically communicate with the chassis (when the microprocessor is working) and all repair information is directly available. When ComPair is installed together with the SearchMan electronic manual of the defective chassis, schematics and PWBs are only a mouse click away.

5.4.2 Specifications

ComPair consists of a Windows based faultfinding program and an interface box between PC and the (defective) product. The ComPair interface box is connected to the PC via a serial or RS232 cable.
For this chassis, the ComPair interface box and the TV communicate via a bi-directional service cable via the service connector.

The ComPair faultfinding program is able to determine the problem of the defective television. ComPair can gather diagnostic information in two ways:

- **Automatically** (by communicating with the television set): ComPair can automatically read out the contents of the

entire error buffer. Diagnosis is done on I²C level. ComPair can access the I²C bus of the television. ComPair can send and receive I²C commands to and from the micro controller of the television set. In this way, it is possible for ComPair to communicate (read and write) to devices on the I²C busses of the TV-set.

- **Manually** (by asking questions to you): This option is helpful, because automatic diagnosis is only possible if the micro controller of the television is working correctly (also, the diagnostic possibilities of automatic diagnosis are more limited). When you choose manual diagnosis, ComPair will guide you through the faultfinding tree by asking you questions (e.g. Does the screen give a picture? Click on the correct answer: YES / NO) and by showing you examples (e.g. Measure test-point I7 and click on the correct oscillogram you see on the oscilloscope). You can answer by clicking on a link (e.g. a piece of text or a waveform picture) that will bring you to the next step in the faultfinding process.

By a combination of automatic diagnostics and an interactive question / answer procedure, ComPair will enable you to find most problems in a fast and effective way.

Besides fault finding, ComPair provides some **additional features** like:

- Up- or downloading of pre-sets.
- Managing of pre-set lists.
- Emulation of the Dealer Service Tool (DST).
- If both ComPair and SearchMan (Electronic Service Manual) are installed, all the schematics and the PWBs of the set are available by clicking on the appropriate hyperlink.
  Example: *Measure the DC-voltage on capacitor C2568 (Schematic/Panel) at the Mono-carrier*.
  – Click on the “Panel” hyperlink to automatically show the PWB with a highlighted capacitor C2568.
  – Click on the “Schematic” hyperlink to automatically show the position of the highlighted capacitor.
- SW upgrading

5.4.3 How To Order

ComPair order codes:

- Starter kit ComPair32/SearchMan32 software and ComPair interface (excl. transformer): 3122 785 90450.
- ComPair interface (excluding transformer): 4822 727 21631.
- Starter kit ComPair32 software (registration version): 3122 785 60040.
- Starter kit SearchMan32 software: 3122 785 60050.
- ComPair32 CD (2003 update): 3122 785 60110.
- SearchMan32 CD (2003 update): 3122 785 60120.
- ComPair interface cable: 3122 785 90004.
- ComPair firmware upgrade IC: 3122 785 90510.
- Transformer Europe: 4822 727 21632.
- Transformer UK: 4822 727 21633.

5.5 Error Codes

5.5.1 Introduction

The error code buffer contains all detected errors since the last time the buffer was erased. The buffer is written from left to right, new errors are logged at the left side, and all other errors shift one position to the right.
When an error has occurred, the error is added to the list of errors, provided the list is not full or the error is a protection error.
When an error occurs and the error buffer is full, then the new error is not added, and the error buffer stays intact (history is maintained), except when the error is a protection error.
To prevent that an occasional error stays in the list forever, the error is removed from the list after 50+ operation hours.
When multiple errors occur (errors occurred within a short time span), there is a high probability that there is some relation between them.

5.5.2 How to Read the Error Buffer

Use one of the following methods:

- On screen via the SAM (only if you have a picture). Examples:
  – **0 0 0 0**: No errors detected
  – **6 0 0 0**: Error code 6 is the last and only detected error
  – **9 6 0 0**: Error code 6 was first detected and error code 9 is the last detected error
- Via the blinking LED procedure (when you have no picture). See next paragraph.
- Via ComPair.

5.5.3 How to Clear the Error Buffer

Use **one** of the following methods:

- By activation of the “CLEAR ERRORS” command in the SAM menu.
- With a normal RC, key in sequence “MUTE” followed by “**062599**” and “OK”.
- When you transmit the commands “DIAGNOSE” - “99” - “OK” with ComPair (or with a DST).
- If the content of the error buffer has not changed for 50+ hours, it resets automatically.

5.5.4 Error Codes

The function of error codes is to indicate failures in the TV set. In principle a unique error code is available for every:

- I²C device error.
- I²C bus error (for every bus containing two or more I²C devices).
- Protection error (e.g. +8V protection or Horizontal protection).
- Error not related to an I²C device, but of importance (e.g. BC-loop, RAM error).

Table 5-1 Error Table

Error	Description
0	No error
1	Horizontal Protection (via NOHFB bit in ADOC)
3	+8V error (missing/protection active by checking MPIF ASUP bit))
4	X-ray/High beam current protection signal (via XPROT bit in ADOC)
5	Highbeam protection
7	Under-voltage protection
11	MPIF I^2C communication failure / MPIF test failed
12	BC-loop not stabilised within the time limit (i.e. after timer is expired)
13	NVM I^2C communication failure
14	Main tuner 1232 I^2C failure UV13xx
17	3D Y/C 7823 Combfilter I^2C communication failure
18	PIP Tuner I^2C failure
19	2fH component input I^2C failure (PCF8574)
21	PIP IF demodulator IC TDA988x communication failed (only for PIP/DW sets)
22	Flash over protection error (to register CRT flash-overs, via FPR status bit in ADOC)

Service Tips:
- In case of non-intermittent faults, clear the error buffer before you begin the repair. This to ensure that old error codes are no longer present. Before clearing the buffer, write down the content, as this history can give you significant information.
- If possible, check the entire contents of the error buffer. In some situations, an error code is only the result of another error code and not the actual cause (e.g., a fault in the protection detection circuitry can also lead to a protection).

5.6 The Blinking LED Procedure

5.6.1 Introduction

Via this procedure, you can make the contents of the error buffer visible via the front LED. This is especially useful for fault finding, when there is no picture.

When the SDM is activated, the front LED will show (by blinking) the contents of the error-buffer. Error-codes > 10 are shown as follows:
1. A long blink of 750 ms (which is an indication of the decimal digit),
2. A pause of 1500 ms,
3. “n” short blinks (where “n” = 1 - 9),
4. When all the error-codes are displayed, the sequence finishes with a LED blink of 3000 ms,
5. The sequence starts again.

Example: Error 12 9 6 0 0.
After activation of the SDM, the front LED will show:
1. 1 long blink of 750 ms (which is an indication of the decimal digit) followed by a pause of 1500 ms,
2. 2 short blinks of 250 ms, followed by a pause of 3000 ms,
3. 9 short blinks of 250 ms, followed by a pause of 3000 ms,
4. 6 short blinks of 250 ms, followed by a pause of 3000 ms,
5. 1 long blink of 3000 ms to finish the sequence,
6. The sequence starts again.

5.6.2 How to Activate

Use one of the following methods:
- Activate the SDM (only via soldering pads marked “FOR SERVICE” on the SSB). The blinking front LED will show the entire contents of the error buffer (this works in “normal operation” mode and in “protection” mode). In order to avoid confusion with RC5 signal reception blinking, this LED blinking procedure is terminated when an RC5 command is received.
- Transmit the commands “MUTE”, “**06250x**”, and “OK” with a normal RC (where “x” is the position in the error buffer that has to be displayed). With x= 1, the last detected error is shown, x= 2 the second last error, etc.... When x= 0, all errors are shown.
- “DIAGNOSE X” with the DST (where “x” is the position in the error buffer that has to be displayed). With x= 1, the last detected error is shown, x= 2 the second last error, etc.... When x= 0, all errors are shown.

Note: It can take some seconds before the blinking LED starts.

5.7 Software Downloading

In this chassis, you can **upgrade** the software via ComPair. You can find more information on how this procedure works in the ComPair file. It is possible that not all sets are equipped with the hardware, needed to make software upgrading possible. To speed up the programming process the firmware of the ComPair interface can be upgraded. See paragraph “How To Order” for the order numbers.

6. Block Diagrams, Testpoint Overviews, and Waveforms

Wiring Diagram



F_15040_054.eps
250405

Block Diagram LSP Supply and Deflection



Testpoint Overview LSP

F232 A8 F233 A8 F234 A9 F235 A10 F241 A10 F242 A10 F243 A10 F246 B8 F247 A8 F248 A8 F249 A7 F250 A6 F401 D6 F402 E7 F404 F8 F416 G6 F418 G7 F419 G8 F451 F9 F452 G10 F453 C7 F455 C7 F456 G10 F457 G10 F458 D8 F459 G7 F462 F9 F464 F6 F465 F6 F466 D9 F469 D9 F472 C8 F475 C8 F476 D8 F478 D9 F481 E9 F482 C8 F483 D8 F500 D1 F501 F2 F502 E2 F503 C7 F504 F1 F506 G1 F507 G1 F508 F3 F509 G4 F535 C5 F537 C5 F541 D3 F542 D4 F552 E5 F561 D4 F562 D5 F563 D6 F573 C4 F574 D4 F575 F5 F576 C4 F578 C4 F580 D6 F581 C4 F582 C3 F583 E5 F620 C8 F627 A5 F628 A5 F629 B8 F630 B8 F631 B8 F632 B8 F672 A6 F673 B8 F674 C6 F675 B6 F676 B6 F677 B9 F678 C6 F679 C7 F701 D9 F702 D10 F703 D10 F704 D10 F705 C9 F706 C10 F708 C10 F710 C10 F711 B10 F712 C10 F713 C9 F714 B10 F715 B9 F716 B10 F717 C10 F718 B9 F720 B10 F721 B9 F722 B10 F723 B10 F724 B10 F901 B4 F903 B4 F904 B3 F905 B3 F910 B3 F911 B4 F912 B4 F913 B2 F950 A5 F951 B5 F952 A5 F955 B4 F956 C3 F957 B4 F958 A5 F959 A5 F960 A4 F961 A4 F962 A4 F963 A4 F965 A4 F966 A4 F967 A4 I232 A9 I234 A9 I239 A9 I240 A9 I241 A6 I242 A6 I247 A6 I248 B8 I249 A7 I253 A7 I254 A7 I255 A7 I256 B6 I259 A7 I260 A9 I261 A9 I402 G9 I410 F10 I412 B8 I413 D6 I414 C7 I415 D7 I418 G6 I419 G6 I420 E6 I423 D7 I428 F7 I432 E8 I435 D8 I436 D8 I437 D6 I438 D9 I439 E8 I440 E8 I442 E10 I443 F9 I445 D7 I446 D7 I447 F8 I448 D6 I449 D6 I450 F6 I453 G9 I455 F9 I457 F8 I459 F9 I460 D8 I462 G7 I463 G10 I464 F10 I466 E8 I468 E8 I469 E9 I470 D8 I473 E7 I475 F9 I476 D9 I480 D9 I481 D9 I482 G10 I487 D7 I488 G6 I489 G7 I490 D7 I491 D7 I492 E9 I493 G10 I494 E8 I495 D9 I496 E7 I497 F6 I499 D7 I500 F3 I501 G3 I502 G2 I503 G1 I504 G1 I506 F3 I507 E2 I509 F4 I510 E3 I511 G5 I512 E4 I513 F5 I514 F5 I515 F5 I516 G5 I517 G5 I518 F5 I519 G5 I520 F6 I521 G5 I522 D6 I523 F6 I525 E3 I526 F3 I527 G6 I528 E4 I529 D4 I530 F3 I531 E3 I532 E3 I533 E4 I534 F2 I536 E3 I537 E3 I538 D4 I539 D3 I540 D3 I541 B9 I542 D2 I543 C3 I544 E4 I545 C3 I546 F5 I547 C4 I548 F5 I550 E3 I551 E5 I552 E5 I553 F3 I554 F3 I555 E4 I557 E2 I558 D4 I559 G2 I560 F4 I561 E4 I562 E4 I563 E2 I564 F6 I565 D4 I566 D4 I568 D3 I569 D5 I570 D5 I571 E6 I572 F1 I573 D5 I574 D6 I575 E6 I577 C4 I578 E6 I579 E5 I580 D5 I581 D4 I582 G5 I583 F1 I586 E5 I587 D4 I588 C4 I589 D5 I590 D4 I591 D4 I592 D4 I593 D4 I596 D6 I597 D5 I599 D5 I602 A9 I603 C6 I604 B7 I605 C7 I606 C6 I608 C6 I609 C9 I610 B9 I611 C9 I612 A7 I616 B8 I621 A6 I622 A6 I623 A5 I624 A5 I625 A5 I626 A5 I627 C6 I628 C6 I629 C6 I630 B6 I631 C6 I632 A8 I633 B8 I634 C7 I635 A7 I636 B8 I637 B8 I638 C8 I639 C8 I640 B7 I650 C7 I672 B8 I674 A7 I677 B7 I678 B9 I680 B7 I685 B6 I686 B6 I687 B6 I688 B7 I689 B7 I690 B7 I691 A5 I693 C7 I694 C7 I695 B7 I696 A6 I701 D9 I702 D10 I703 C9 I704 D10 I705 C9 I706 C9 I707 C10 I708 C10 I709 C9 I710 C9 I711 B9



Block Diagram 1 Audio & Video



Block Diagram 2 Audio & Video



F_15040_056.eps
250405

Block Diagram 3 Audio & Video



Testpoint Overview SSB

1009 A2	F064 B1	F134 B2	F351 C4	F390 C3	F512 B3	F527 C2	F551 B3	F794 C5	F910 D2	F929 D3	F947 C5	F962 D5	F976 D7	I009 B2	I108 B2	I308 D4	I381 C3	I442 A4
F014 A3	F074 A2	F135 B2	F354 C3	F391 C3	F513 B3	F532 B3	F570 A5	F795 C5	F911 D2	F931 D3	F948 D5	F963 D6	F977 D6	I010 A2	I151 B1	I309 C4	I382 C3	I443 A5
F015 A3	F075 A2	F137 C2	F355 C5	F437 B4	F514 B3	F533 B4	F582 B6	F797 C6	F913 C2	F932 D3	F949 D5	F964 D6	F978 D7	I061 C2	I152 B1	I310 D4	I431 A4	I444 A5
F016 A4	F076 A1	F138 C2	F357 D5	F438 B3	F515 A7	F534 B4	F584 A7	F798 C6	F915 D2	F933 D4	F950 D5	F965 D6	F979 D7	I062 B1	I153 B2	I341 B5	I432 A4	I445 A5
F017 A4	F077 B1	F139 B2	F358 C5	F439 B4	F516 B4	F537 C4	F601 B5	F799 C6	F918 D2	F935 D3	F951 D5	F966 D6	F980 D7	I063 C1	I154 B2	I342 C5	I433 A3	I446 A5
F020 C1	F078 A1	F150 A1	F381 C3	F448 B4	F517 B4	F538 B4	F650 C6	F901 D1	F919 D3	F936 D3	F952 D5	F967 D6	I001 C1	I064 B1	I281 C2	I343 C5	I434 A3	I447 A6
F021 A2	F080 B1	F152 C1	F382 C4	F449 B4	F518 B4	F539 B4	F651 B6	F902 D1	F920 D3	F937 D3	F953 D5	F968 D6	I002 A2	I101 C2	I301 C4	I344 C5	I435 A4	I448 A6
F041 A1	F088 A2	F159 A2	F383 C3	F480 A5	F519 B3	F540 B4	F652 C6	F903 D1	F921 D3	F938 C4	F955 D5	F969 D6	I003 A2	I102 B2	I302 C4	I345 C6	I436 A4	I501 C4
F042 A1	F089 A2	F281 B4	F384 C3	F481 A5	F520 B4	F541 B4	F730 B5	F904 D2	F923 D3	F939 D2	F956 D5	F970 D6	I004 B2	I103 B2	I303 C4	I346 C5	I437 A4	I502 C6
F045 A1	F114 C2	F282 A4	F385 C3	F508 B4	F521 B3	F542 B4	F790 C5	F905 D2	F924 D3	F940 D4	F958 D5	F972 D7	I005 B1	I104 C2	I304 C4	I347 C5	I438 A4	I601 B5
F046 B1	F115 D2	F341 C4	F386 C4	F509 B4	F522 B3	F543 B4	F791 B5	F906 D2	F925 D3	F941 D4	F959 D5	F973 D6	I006 A2	I105 B2	I305 C4	I348 C5	I439 A3	I651 C7
F047 B1	F116 C1	F346 C4	F387 C3	F510 A3	F523 B3	F544 B4	F792 B5	F907 C2	F926 D3	F943 D4	F960 D5	F974 D6	I007 A2	I106 B3	I306 C4	I349 C5	I440 A4	
F060 C2	F132 C1	F348 A1	F389 C3	F511 B3	F524 C4	F550 B3	F793 C5	F909 D2	F928 D3	F944 D4	F961 D6	F975 D7	I008 A2	I107 B2	I307 C4	I350 C5	I441 A4	









CL 36532058_008.eps
211103

I2C Overview

I²C Overview



F_15040_057.eps
250405

Supply Lines Overview

SUPPLY LINES OVERVIEW



F_15040_058.eps
290405

7. Circuit Diagrams and PWB Layouts

LSP: Power Supply



1500 B2	3542 H8	9503 C3	I593 H9	
1501 B2	3543 H9	9504 C4	I596 G12	
1502 B2	3544 H10	9506 B6	I597 I10	
1503 A7	3545 G10	9507 F10	I599 I12	
1504 A2	3546 F10	9511 B5		
1505 C1	3547 G13	9512 G10		
1506 A13	3548 H8	9513 A12		
1532 E7	3549 C6	9532 B10		
1538 E12	3550 C6	9533 C10		
1542 B8	3551 D11	9553 A12		
1543 B8	3552 D12	F500 A2		
1544 B8	3553 H10	F501 A2		
1550 F6	3554 G12	F502 A5		
1551 F8	3563 E8	F503 C2		
1552 F9	3565 E10	F504 C2		
2500 C3	3566 G10	F506 B3		
2501 A3	3567 F5	F507 C3		
2502 C5	3568 F4	F508 B7		
2503 B6	3571 C8	F509 B7		
2504 B6	3573 D9	F535 F10		
2505 B6	3574 E9	F537 G11		
2506 B5	3575 D9	F541 A8		
2507 B7	3576 E10	F542 B8		
2508 C5	3579 D9	F552 B9		
2509 H2	3580 G1	F561 C10		
2510 G2	3581 I12	F562 C9		
2511 D2	3583 H10	F563 B10		
2512 F2	3584 I10	F573 D10		
2513 E5	3585 H12	F574 B7		
2514 D6	3586 H11	F575 C7		
2515 D7	3587 H8	F576 D9		
2516 E5	3588 H5	F578 F10		
2517 E2	3589 E11	F580 I11		
2521 I3	3590 H11	F581 I11		
2522 G7	3591 H11	F582 F10		
2523 G6	3592 F7	F583 B9		
2524 F11	3593 I3	I500 I1		
2526 E6	3594 I3	I501 A6		
2528 D1	3595 I4	I502 C6		
2535 F9	3596 I4	I503 B2		
2536 F10	3597 H5	I504 C2		
2537 G9	3598 D2	I506 A5		
2538 F9	4550 E11	I507 C5		
2539 F9	5500 C4	I509 G2		
2540 G9	5501 C3	I510 G2		
2541 B8	5502 A6	I511 D2		
2542 B7	5504 F7	I512 I2		
2543 H9	5505 F10	I513 D5		
2544 F7	5506 C4	I514 C6		
2551 B9	5511 D6	I515 D7		
2552 B9	5512 C7	I516 D6		
2553 A11	5532 F7	I517 D5		
2561 C9	5561 C8	I518 D6		
2562 C9	5562 B8	I519 E5		
2563 B9	5564 F10	I520 E5		
2564 E9	5565 A12	I521 D6		
2565 B9	5566 B10	I522 I12		
2570 D7	5567 C10	I523 E7		
2571 D9	6500 B6	I526 G5		
2572 D11	6509 H2	I527 F2		
2575 I9	6511 E2	I528 I5		
2576 H11	6512 E10	I529 I7		
2577 I12	6514 D6	I530 H5		
2578 H9	6532 H6	I531 G6		
2579 I10	6533 H6	I532 G6		
2580 F7	6535 F9	I533 G7		
2582 H1	6536 F9	I534 B4		
2583 I4	6537 G9	I536 F7		
2584 F10	6538 D1	I538 F9		
2585 H1	6539 G1	I539 G8		
2586 H1	6541 A8	I540 F8		
2587 D9	6548 F9	I542 A7		
2588 G7	6549 B9	I543 A8		
2589 G10	6550 C9	I544 H3		
2590 I12	6551 A9	I545 G10		
2591 H12	6562 C9	I546 G2		
3501 C4	6563 B9	I547 G10		
3502 B4	6564 E9	I548 E9		
3503 B4	6565 E9	I550 H6		
3504 C2	6567 F4	I551 B8		
3505 C3	6574 I11	I552 B9		
3507 A4	6575 E6	I553 C1		
3508 B6	6576 H11	I554 D1		
3509 A4	6578 H5	I555 H5		
3510 B5	6581 H1	I557 F7		
3511 E6	6582 F6	I558 F8		
3512 F2	7510 G2	I559 A5		
3513 C6	7511 D2	I560 I4		
3514 D5	7512 D5	I561 D8		
3515 D6	7513 E5	I562 C8		
3516 E6	7516 H7	I563 A4		
3517 E5	7517 C5	I564 E1		
3518 F3	7525 G5	I565 H1		
3519 E1	7532 H2	I566 E11		
3520 E6	7535 G10	I568 F6		
3521 I2	7541 A8	I569 D12		
3522 D5	7542 H8	I570 G11		
3523 A4	7545 F11	I571 E8		
3524 I4	7547 G12	I572 B4		
3525 H5	7548 H13	I573 H11		
3526 G5	7549-1 I3	I574 D10		
3527 G2	7549-2 I4	I575 E8		
3528 D1	7561 E11	I577 E10		
3529 C1	7562 E11	I578 D10		
3530 G5	7567 F4	I579 B8		
3531 G6	7571 D8	I580 I11		
3532 H6	7573 D10	I581 I9		
3533 H6	7575 I9	I582 C6		
3534 G6	7576-1 I11	I583 C4		
3535 E7	7576-2 I10	I586 B8		
3536 F5	7583-1 I11	I587 E9		
3537 G10	7583-2 I12	I588 E9		
3538 H6	7584 I12	I589 I10		
3540 F11	9500 C2	I590 H9		
3541 A8	9501 B3	I591 H9		
	9502 B4	I592 H8		

LSP: Deflection

A2 DEFLECTION



1401 A1	3443 D10	F418 D3
1402 B1	3450 D8	F419 D3
1403 B7	3451 E4	F451 G6
1404 B4	3452 F8	F452 C2
1405 B7	3453 B8	F453 B1
1406 B7	3455 E6	F455 B1
1452 E9	3456 C4	F456 E6
2402 B2	3458 C2	F457 E8
2403 B2	3459 E9	F458 F10
2404 A4	3460 D9	F459 A3
2405 B1	3461 F6	F462 B10
2406 B2	3462 C9	F464 B4
2407 C4	3463 F6	F465 C5
2409 E2	3465 D9	F466 E8
2410 E4	3466 F8	F469 F9
2411 D3	3467 F8	F472 C10
2412 D4	3468 F8	F475 D1
2413 D4	3469 D8	F476 F1
2414 D3	3470 G7	F478 D10
2416 D4	3471 G6	F481 C8
2417 D5	3472 G6	F482 F6
2418 D5	3473 F5	F483 F6
2419 D4	3474 C10	I402 B2
2422 G1	3476 F6	I410 E3
2425 G3	3477 C9	I413 D1
2427 A4	3479 D5	I414 D1
2431 B4	3480 B7	I415 F3
2432 E9	3485 B10	I418 D2
2437 G2	3486 C8	I419 D2
2448 D7	3487 D8	I420 E2
2449 D8	3488 F4	I423 F3
2450 B9	3490 D2	I428 D5
2451 B8	3491 B7	I432 A5
2452 F7	3492 B9	I435 E9
2453 F7	3493 E4	I436 E10
2454 C2	3499 F2	I437 E8
2457 E5	5401 B4	I438 F8
2458 C2	5402 D2	I439 C8
2459 E5	5406 C4	I440 C9
2460 E6	5408 D4	I442 E4
2461 E8	5409 C4	I443 E4
2462 F6	5410 A5	I445 F1
2463 F6	5411 D5	I446 F2
2464 F8	5450 A6	I447 G2
2465 G8	5452 B1	I448 E4
2466 C9	5453 E8	I449 E5
2468 F8	5455 A2	I450 B4
2469 C8	5456 B1	I453 C3
2470 E8	6403 E5	I455 C5
2471 E6	6404 D4	I457 B3
2473 F7	6405 D5	I458 B7
2476 C9	6424 F1	I459 D7
2477 C9	6425 F2	I460 C10
2478 E3	6426 G2	I462 E2
2479 F6	6427 F4	I463 E3
2487 B10	6452 C3	I464 E4
2488 D2	6453 C3	I466 C2
2489 B10	6456 E5	I468 B10
2490 D9	6457 E7	I469 C8
2492 C7	6458 E7	I470 B2
2493 C3	6459 E9	I473 D4
2494 B3	6461 D7	I475 E5
2495 F5	6464 D2	I476 E7
2496 G2	6465 E3	I480 F8
2497 D1	6466 C7	I481 F8
2498 F8	6469 B9	I482 F7
2499 F8	6471 F3	I487 B8
3401 A1	6474 C10	I488 D2
3402 D1	6476 C8	I489 B4
3403 C3	6478 B8	I490 F3
3408 D1	6480 C9	I491 G1
3412 B4	7403 E4	I492 D7
3414 E2	7404 D1	I493 E5
3415 E2	7405 D3	I494 C9
3416 D3	7406 F3	I495 E8
3417 F5	7407 D9	I496 F2
3418 F2	7408 C9	I497 F5
3419 E3	7455 E7	I499 F3
3421 E2	7456 E10	
3422 F1	7486 E10	
3423 F1	9401 C4	
3424 F1	9402 B5	
3425 F3	9410 A5	
3426 G3	9411 B3	
3432 E3	9412 D5	
3433 A5	9447 C7	
3434 F3	F401 A1	
3435 F1	F402 A1	
3436 G4	F404 B1	
3437 G1	F416 B4	

LSP: Class D Audio Amplifier (Res)



1901 C9 5913 A8
1902 D9 5914 B8
1904 F1 6904 E3
2911 A8 6905 B6
2913 B8 6906 A6
2914 A3 6962 C3
2930 B2 7901-1 A3
2931 A2 7901-2 E3
2933 B2 7902 C5
2934 B2 7903 D3
2935 E2 7904 C2
2936 D2 9917 B1
2938 F2 9918 E1
2939 E2 F901 C1
2942 C4 F903 D9
2945 D5 F904 C9
2946 D5 F905 D9
2947 B5 F910 F1
2948 B5 F912 B4
2949 B5 F913 D5
2950 A5 I901 A5
2951 A5 I902 A8
2952 C6 I903 F2
2953 D6 I904 E3
2954 D7 I908 B2
2955 C7 I909 A2
2957 C8 I913 B2
2960 C4 I914 B3
2961 A5 I915 C3
2963 B6 I916 B4
2964 A7 I918 D2
2965 B7 I920 C2
2970 D7 I921 C4
2971 D7 I922 D4
2977 A4 I924 A5
2978 B8 I925 E2
2979 B8 I926 B8
2982 C8 I927 B8
2983 E8 I928 A5
2984 E8 I930 A6
3930 B2 I934 C6
3931 A2 I935 C7
3932 B2 I936 C7
3933 B2 I938 D6
3934 B3 I941 A3
3935 B3 I943 D7
3936 E2 I945 D4
3937 E2 I948 F3
3938 F2
3939 F2
3940 F3
3941 F3
3942 B4
3943 C4
3947 C3
3949 C4
3952 C6
3953 D6
3955 C7
3956 C8
3958 A5
3959 C3
3960 B5
3961 C3
3962 C1
3971 D7
3972 E8
3973 A3
3974 C4
4930 A1
4931 E1
5901 C7
5902 D7
5910 B8

LSP: Audio Amplifier

A4 AUDIO AMPLIFIER



For Europe

ITEM	SIZE/TUBE			
	29RF A68ERF182X044	28WSRF A66ERF172X044	32WSRF A66ERF172X044	28BLD A66EAK075X054
1910	NOT USED	NOT USED	NOT USED	NOT USED
1911	USED	USED	USED	USED
4984	NOT USED	NOT USED	NOT USED	NOT USED
7962	NOT USED	NOT USED	NOT USED	NOT USED
9916	USED	USED	USED	USED

"985" ~ "999"

3139 123 5895.4

F_15040_004.eps
230305

1910 B8
1911 A8
2975 B1
2976 C2
2981 B2
2985 B2
2986 A6
2987 A5
2988 D5
2989 B3
2990 B3
2991 A5
2992 C3
2993 C3
2994 B6
2995 C6
2996 B7
2997 C7
2998 D5
3957 C7
3985 B2
3988 B3
3989 B7
3991 C2
3992 C3
3993 C7
4984 B2
7962 D2
7990 A4
7991 D4
9916 B2
F911 D2
F950 B2
F951 C2
F952 A7
F955 B7
F956 B7
F958 C4
F959 D2
I951 B4
I952 C4
I953 B3
I954 C3
I956 B7
I957 C7
I958 C6
I959 B6
I960 C6
I962 B4
I963 C7
I964 D6
I965 D5
I967 A6

LSP: Tuner IF

1232 B2	1245 D2	1269 B1	2233 D4	2247 C9	2251 C3	3239 B4	3242 C4	5248 B3	5251 B5	6239 C2	9233 E1	9646 E1	F234 C3	F242 B5	F247 D2	F250 B7	I240 B4	I247 E2	I253 E2	I256 A3	I261 B5
1241 B6	1246 D2	1270 B6	2235 D3	2248 D3	2268 C7	3240 C4	4220 E1	5249 C3	6234 D3	9230 E1	9234 E1	F232 B2	F235 C3	F243 B5	F248 A2	I232 C4	I241 B4	I248 D4	I254 E2	I259 C10	
1243 B8	1268 B6	2232 C4	2236 D3	2250 C3	3238 D2	3241 B4	5247 C10	5250 B5	6238 C2	9231 E1	9235 E1	F233 B2	F241 B5	F246 B7	F249 A2	I239 B4	I242 C4	I249 A8	I255 E2	I260 B5	



For Europe

ITEM	SIZE/TUBE 29RF A68ERF182X044	28WSRF A66ERF172X044	32WSRF A66ERF172X044	28BLD A66EAK075X054
1232	UV1316E/A1-4	UV1316E/A1-4	UV1316E/A1-4	UV1316E/A1-4
1243	NOT USED	NOT USED	NOT USED	NOT USED
1245	NOT USED	NOT USED	NOT USED	NOT USED
1268	NOT USED	NOT USED	NOT USED	NOT USED
1270	NOT USED	NOT USED	NOT USED	NOT USED
6238	BAS316	BAS316	BAS316	BAS316
9230	NOT USED	NOT USED	NOT USED	NOT USED
9231	USED	USED	USED	USED
9235	NOT USED	NOT USED	NOT USED	NOT USED

F_15040_005.eps
220305

LSP: Interfacing

A6 INTERFACING

TO SSB PANEL

TO 1936 OR 0240 OF D SIDE I/O PANEL

TO 1340 OF B CRT PANEL

TO 2T PIP DW PANEL

TO 0215 OF E TOP CONTROL

TO A10 2T PIP DW PANEL

FROM 1506 OF A1 POWER SUPPLY

TO 0203 OF Q1 FRONT INTERFACE PANEL OR TO 0242/0247 OF Q1 MAINS SWITCH PANEL

TO PIXEL PLUS FRONT INTERFACE

For Europe

	SIZE/TUBE			
ITEM	29RF A68ERF182X044	28WSRF A66ERF172X044	32WSRF A66ERF172X044	28BLD A66EAK075X054
1620	USED	USED	USED	USED
1623	NOT USED	NOT USED	NOT USED	NOT USED
1624	USED	USED	USED	USED
1625	NOT USED	NOT USED	NOT USED	NOT USED
1645	USED	USED	USED	USED
4683	USED	USED	USED	USED
4694	NOT USED	NOT USED	NOT USED	NOT USED
9620	NOT USED	NOT USED	NOT USED	NOT USED
9621	USED	USED	USED	USED
9626	USED	USED	USED	USED

	9674	9664	4624	4625	9675	9686
PIXEL PLUS	--	--	--	JMP	JMP	--
SALSA	JMP	JMP	JMP	--	--	JMP

1607 H1, 1608 I1, 1620 A13, 1621 A9, 1623 B2, 1624 C2, 1625 D2, 1629 C12, 1630 C12, 1631 D13, 1635 D12, 1645 E13, 1646 F13, 1669 H3, 1670 I1, 1683 F12, 1684 E2, 2663 H11, 2666 B12, 2667 B12, 2669 B12, 2670 B12, 2671 B12, 2672 B12, 2673 B13, 2674 C7, 2675 E12, 2676 H7, 2677 H7, 2678 H7, 2679 H6, 2680 H8, 2681 H7, 2682 H6, 2688 E6, 2689 E7, 2690 E8, 2691 C8, 2692 C5, 2693 H9, 2694 H9, 2695 H10, 2696 H11, 2697 H11, 2698 H6, 3623 B3, 3624 B3, 3625 C3, 3626 C3, 3627 H6, 3628 H6, 3629 A5, 3630 A5, 3670 D7, 3677 H6, 3683 C5, 3685 D6, 3686 G6, 3687 H6, 3688 G6, 4624 D3, 4625 D3, 4683 H12, 4684 F9, 4694 A11, 5680 H8, 5681 E8, 5682 C7, 5683 H12, 5684 H12, 5685 H10, 5686 H10, 5687 H2, 5688 H3, 6681 G9, 6682 H9, 6683 C6, 6684 H5, 6685 H6, 7673 E7, 7674 B6, 7675 A6, 7676 B5, 9620 A10, 9621 A10, 9626 A11, 9664 C3, 9669 E3, 9670 E3, 9671 F3, 9672 F3, 9674 C3, 9675 E6, 9686 E6, 9691 H4, F620 A13, F627 B12, F628 B12, F629 C12, F630 C12, F631 C12, F632 B12, F672 C12, F673 C7, F674 I12, F675 I12, F676 I12, F677 H3, F678 E6, F679 E7, I602 E12, I603 E12, I604 H7, I605 B5, I606 D6, I608 B2, I609 D3, I610 F2, I611 B11, I612 B13, I616 D3, I621 A12, I622 A12, I623 A12, I624 A12, I625 A12, I626 A12, I627 C3, I628 C3, I629 C2, I630 C3, I631 C2, I632 E2, I633 F2, I634 C5, I635 A10, I636 C7, I637 I4, I638 H6, I639 H6, I640 I6, I650 H9, I672 H3, I674 H4, I677 H7, I678 H1, I680 H8, I685 B3, I686 C3, I687 C3, I688 H9, I689 H6, I690 I7, I691 I10, I693 B7, I694 C6, I695 E8, I696 H10

F_15040_006.eps 250405

LSP: SCART I/O



ITEM	SIZE/TUBE 29RF A68ERF182X044	28WSRF A66ERF172X044	32WSRF A66ERF172X044	28BLD A66EAK075X054
3725	USED	USED	USED	USED
9702	USED	USED	USED	USED
9703	USED	USED	USED	USED
9704	USED	USED	USED	USED
9705	USED	USED	USED	USED
9706	USED	USED	USED	USED

3139 123 5895.4

F_15040_007.eps 220305

1701-1 A7 3736 E7 F724 E2
1701-2 A3 3737 E2 I701 A2
1703 B3 3738 E3 I702 A6
1704 C7 3739 E6 I703 A2
1705-1 D2 3740 E7 I704 B6
1705-2 D1 3741 F2 I705 B4
1705-3 D2 3742 F3 I707 B2
2703 B2 3743 B3 I708 B6
2704 B2 3744 B7 I709 B4
2705 B6 3745 B7 I710 B8
2706 B6 3746 B4 I711 D5
2708 B4 3747 F6 I712 E3
2710 C8 3748 F5 I713 E7
2711 C5 3749 F6 I714 E6
2712 D7 5704 E7 I715 E2
2713 E3 5705 F6 I716 F2
2714 E2 5706 E2 I717 F2
2715 F2 5707 F2 I719 A1
2716 E6 5708 F2 I720 B1
2717 B8 6701 B2 I721 A4
2718 B8 6702 B5 I722 B3
2719 B4 6703 C5 I723 C4
2720 B4 6704 C8 I724 C4
2721 F6 6705 C4 I725 C4
2722 E7 6706 C8 I726 D4
3701 A1 6707 D3 I727 E4
3702 A2 6708 D4 I728 E4
3703 A5 6709 D1 I729 F4
3704 A6 6710 D5 I731 A5
3705 A3 6711 D3 I732 A8
3706 A7 6712 D8 I733 A5
3707 A1 7701-1 E6 I734 B8
3708 A2 7701-2 F6 I735 B6
3709 A5 9701 E6 I736 C8
3710 A6 9702 B1 I737 D8
3711 B3 9703 C3 I738 D6
3712 B7 9704 C3 I739 D6
3713 B1 9705 D4 I740 D6
3714 B3 9706 D7 I741 B3
3715 B2 F701 A2
3716 B4 F702 A6
3717 B6 F703 A3
3718 B7 F704 A7
3719 C8 F705 A2
3720 C3 F706 B6
3721 C3 F708 B7
3722 C3 F710 B7
3723 C7 F711 B2
3724 C4 F712 C6
3725 C7 F713 C3
3726 D3 F714 C6
3727 D3 F715 C3
3728 D1 F716 C7
3729 D5 F717 C3
3730 D4 F718 D2
3731 D7 F719 D6
3732 D3 F720 D3
3733 D7 F721 D7
3734 E2 F722 E1
3735 E3 F723 E2

Layout LSP (Top Side)



3139 123 5895.4

F_15040_008.eps
220305

1232 E7 1401 C5 1504 C1 1550 B2 1624 D4 1669 D6 1904 E4 2404 C5 2416 B5 2454 A7 2490 C6 2507 A3 2535 C3 2551 B4 2584 D3 2948 D3 2998 D4 3418 C5 3434 C5 3467 C6 3485 B6 3502 A1 3511 B4 3524 B3 3566 D3 3628 D6 3717 D7 3730 D7 3971 E2 5411 B5 5502 A2 5552 B4 5681 D5 9560 C4
1241 E7 1402 A6 1505 A1 1551 C2 1625 D4 1670 E5 1910 E3 2405 A6 2417 B5 2458 C6 2500 A1 2508 C1 2536 C3 2552 C4 2588 C3 2949 D3 3240 E6 3419 B7 3450 B7 3468 C6 3486 B7 3503 B1 3513 A4 3525 B3 3571 C4 3670 E6 3720 D7 3731 D7 5247 E5 5450 B6 5504 C2 5561 B3 5682 D5 9561 D4
1243 E6 1404 B4 1506 D3 1552 C3 1629 D6 1683 E4 1911 E3 2406 A6 2418 B5 2460 A7 2501 C1 2510 C3 2537 D2 2561 C3 2674 D5 2957 D2 3401 C5 3421 C4 3451 B7 3469 C6 3487 B6 3504 A1 3514 A4 3529 B2 3575 B4 3683 D5 3722 D7 3930 E2 5401 A5 5452 C6 5505 D3 5562 B3 5683 D4 9562 D4
1245 E5 1452 C6 1532 B2 1607 D6 1630 D6 1684 E6 2235 E6 2407 B4 2419 B5 2461 C6 2502 C1 2511 A4 2539 C3 2562 C3 2676 D5 2960 E2 3402 D5 3422 C5 3455 A7 3470 C6 3488 C5 3505 A1 3515 A4 3531 B2 3579 C4 3687 D6 3724 D7 3933 E3 5402 A5 5453 C7 5506 B1 5564 D2 5684 D4 9570 A2
1246 E7 1500 A1 1538 D4 1608 D6 1631 D6 1701 D7 2248 E6 2411 A5 2431 A5 2468 C6 2503 A3 2514 A4 2540 C2 2563 C4 2688 D5 2977 E2 3403 B4 3425 C5 3456 A7 3471 C6 3490 A4 3507 C1 3516 A3 3535 B2 3587 C3 3701 C7 3725 D7 3936 E2 5406 B4 5455 A5 5511 A3 5565 D3 5901 D3 9574 B2
1268 E5 1501 A1 1542 B3 1620 E4 1635 D6 1705 E7 2250 E6 2412 A5 2449 B7 2469 C6 2504 A3 2523 B2 2541 C2 2565 C3 2689 D4 2978 E2 3412 A5 3426 C5 3458 B6 3472 C6 3492 C5 3508 B2 3519 B3 3536 B2 3592 B2 3703 C7 3726 D7 3955 E3 5408 B5 5456 C6 5512 B4 5566 D4 5902 D2 9620 E4
1269 E7 1502 A1 1543 B3 1621 E6 1645 D4 1901 D2 2402 A6 2413 B5 2450 A7 2488 C6 2505 A3 2524 D3 2542 B3 2570 B3 2692 D5 2984 D2 3414 A5 3432 B7 3462 C6 3473 C5 3499 C5 3509 C1 3520 A3 3550 A4 3598 B2 3713 D7 3728 D7 3957 D3 5409 B5 5500 B1 5532 B2 5567 D3 5913 D2 9621 E4
1270 E5 1503 C2 1544 B3 1623 D4 1646 E4 1902 D2 2403 A7 2414 A5 2451 A7 2489 C6 2506 B2 2528 B3 2544 B2 2580 C2 2945 D2 2991 D4 3415 A5 3433 B6 3466 C7 3477 B6 3501 C1 3510 B2 3523 C2 3563 C3 3627 D6 3714 D7 3729 D7 3959 D3 5410 B5 5501 B1 5551 B4 5680 E5 5914 D2 9622 D4

6404 B5 9623 D5
6426 C5 9624 D4
6452 A7 9625 E6
6453 B6 9626 E4
6456 A7 9627 D5
6457 C6 9628 D5
6469 B6 9629 D4
6471 C5 9630 D5
6474 C6 9631 E4
6476 B6 9632 E4
6480 C6 9633 E6
6500 A3 9634 D4
6509 C3 9635 D5
6511 A4 9636 E4
6535 C2 9637 D4
6536 C3 9641 E4
6537 C2 9642 D4
6548 C2 9644 D6
6549 B4 9646 E5
6550 C3 9650 D5
6551 C4 9653 D6
6562 C3 9654 D6
6563 B3 9655 E4
6575 A3 9656 D4
6582 C2 9658 D6
6905 E3 9659 D6
7403 C4 9660 E6
7405 A5 9661 D5
7406 C5 9662 D5
7455 C6 9663 D6
7512 A4 9665 D6
7513 B4 9666 D6
7516 C3 9667 D4
7525 B2 9668 E5
7542 C3 9669 E5
7571 B4 9670 E6
7673 D5 9671 E6
7674 D5 9672 E5
7902 E2 9673 D4
7990 E4 9674 D4
9230 E5 9675 D5
9231 E5 9677 E4
9233 E5 9680 D4
9234 E5 9681 E4
9235 E5 9682 E4
9401 B4 9683 E4
9402 A5 9685 E4
9410 B5 9686 D5
9411 A5 9687 E5
9412 B5 9688 E5
9413 C6 9689 E6
9415 C6 9690 E4
9417 C7 9691 E5
9422 C6 9692 E5
9423 D6 9693 E5
9424 C5 9694 E6
9425 C6 9695 E6
9426 C6 9696 E5
9427 C5 9699 D6
9429 A5 9702 D7
9434 C4 9703 D7
9435 C6 9704 D7
9436 C6 9705 D7
9437 C5 9706 D7
9438 C5 9720 D7
9440 C5 9721 C7
9441 C6 9722 D7
9442 B5 9723 E6
9443 C7 9903 E3
9444 B5 9904 D3
9447 C6 9905 D4
9500 A1 9906 D4
9501 B1 9907 D2
9502 B1 9908 E2
9503 B1 9909 E3
9504 B1 9910 D4
9506 A2 9916 E4
9507 D3 9917 E4
9511 B2 9918 E4
9512 D3 9942 D3
9513 D3 9949 E2
9514 B3 9951 E2
9524 D3 9952 E4
9527 C4 9953 D3
9530 C4 9990 D3
9532 D4
9533 D3
9535 B3
9539 D4
9540 B3
9543 A3
9544 A3
9547 B3
9548 A4
9549 C4
9552 D3
9553 D3
9554 C4
9555 C3
9556 C3
9557 C4

Layout LSP (Overview Bottom Side)

2232 A7 2410 D7 2452 C7 2465 C7 2478 C4 2496 C5 2515 D4 2526 E4 2572 C4 2583 D3 2663 B4 2673 A4 2682 B5 2697 B4 2710 B7 2717 B7 2913 B2 2936 A2 2951 A2 2964 B3 2981 A3 2989 A3 2997 A3 3417 C5 3452 C6 3474 D6 3518 E4 3532 D2 3542 C3 3549 E4 3568 D3 3584 C4 3593 D3 3625 B4 5707 A7
2233 A6 2422 C5 2453 C7 2466 D6 2479 C6 2497 C4 2516 E4 2538 C2 2575 C3 2585 C3 2666 A4 2675 B6 2690 B5 2698 A5 2711 A7 2718 C7 2914 A2 2938 A2 2952 A3 2965 B3 2982 B2 2990 A4 3238 A6 3423 C5 3453 E7 3476 C6 3521 D3 3533 D2 3543 C3 3551 C3 3573 D4 3585 C4 3594 D3 3626 B4 5708 A7
2236 A7 2425 C5 2457 D7 2470 C6 2487 D6 2498 B6 2517 E4 2543 C3 2576 C4 2586 C3 2667 A4 2677 B5 2691 B5 2703 C7 2712 A7 2719 C7 2930 A2 2939 A2 2953 A2 2970 A2 2983 B2 2992 B3 3239 A7 3424 C5 3459 C6 3479 C5 3522 E4 3534 C3 3544 C3 3552 C3 3574 D4 3586 C4 3595 D3 3629 B5 5910 A2
2247 A5 2427 D5 2459 E7 2471 C6 2492 D6 2499 C6 2519 D2 2546 C4 2577 C4 2587 D4 2669 A4 2678 B5 2693 A5 2704 B7 2713 A7 2720 B7 2931 A2 2942 A2 2954 A3 2971 A2 2985 B3 2993 B3 3241 A7 3435 C5 3460 C6 3480 C5 3526 D2 3537 B3 3545 B3 3553 C3 3576 D4 3588 D3 3596 D3 3630 B5 6234 A6
2251 A6 2432 C6 2462 C6 2473 C7 2493 E7 2509 D3 2520 D3 2553 C3 2578 C3 2589 B3 2670 A4 2679 B5 2694 A5 2705 C7 2714 A7 2721 A7 2933 A3 2946 B2 2955 A2 2975 B4 2986 A4 2994 A3 3242 A6 3436 C5 3461 C6 3491 C5 3527 D3 3538 D2 3546 C4 3554 C4 3580 D3 3589 C3 3597 D3 3677 B5 6238 A6
2268 A5 2437 C5 2463 C6 2476 D6 2494 D6 2512 E4 2521 D3 2564 C3 2579 C4 2590 C4 2671 A4 2680 A5 2695 A5 2706 C7 2715 A7 2722 A7 2934 A2 2947 A2 2961 A3 2976 B4 2987 A3 2995 A3 3408 C4 3437 C5 3463 C6 3512 E4 3528 D2 3540 C4 3547 C4 3565 C3 3581 C4 3590 C4 3623 B4 3685 B5 6239 A6
2409 E4 2448 D7 2464 C6 2477 D6 2495 C5 2513 E4 2522 C3 2571 D4 2582 C3 2591 C4 2672 A4 2681 A5 2696 B5 2708 B6 2716 A7 2911 B2 2935 A2 2950 B3 2963 A3 2979 A2 2988 A4 2996 A3 3416 E5 3443 C6 3465 C6 3517 E4 3530 D3 3541 C2 3548 C3 3567 D3 3583 C4 3591 C4 3624 B4 3686 B5 6403 D7



3688 B5 6405 C5
3702 C7 6424 C5
3704 C7 6425 C5
3705 C7 6427 C5
3706 C7 6458 C6
3707 B7 6459 C6
3708 B7 6461 D7
3709 C7 6464 C4
3710 C7 6465 C4
3711 B7 6466 D6
3712 B7 6478 C5
3715 B7 6512 C3
3716 B7 6514 E4
3718 B7 6532 D2
3719 B7 6533 D2
3721 B7 6538 D3
3723 B7 6539 D3
3727 B7 6541 C2
3732 B7 6564 C3
3733 B7 6565 C3
3734 A7 6567 D3
3735 A7 6574 C4
3736 A6 6576 C4
3737 A7 6578 D3
3738 A7 6581 C3
3739 A7 6681 B5
3740 A7 6682 B5
3741 A7 6683 B5
3742 A7 6684 B6
3743 C7 6685 B5
3744 C7 6701 B7
3745 C7 6702 C7
3746 B7 6703 B6
3747 A7 6704 B7
3748 A7 6705 B6
3749 A7 6706 B7
3931 A2 6707 B7
3932 A2 6708 A7
3934 A3 6709 B7
3935 A3 6710 A7
3937 A2 6711 B7
3938 A2 6712 B6
3939 A2 6904 A2
3940 A2 6906 A3
3941 A2 6962 B3
3942 A2 7404 C4
3943 A2 7407 C6
3947 A2 7408 C6
3949 A2 7456 C6
3952 A3 7486 C6
3953 A2 7510 D3
3956 B3 7511 E4
3958 A3 7517 E4
3960 A3 7532 D3
3961 A3 7535 B3
3962 B3 7541 C2
3972 B2 7545 C4
3973 A2 7547 C4
3974 A2 7548 C4
3985 A3 7549 D3
3988 A3 7561 C3
3989 A3 7562 C3
3991 B3 7567 D2
3992 B3 7573 C4
3993 A3 7575 C3
4220 A5 7576 C4
4403 D7 7583 C4
4420 B5 7584 C4
4421 C6 7675 B5
4501 E4 7676 B5
4550 C3 7701 A7
4624 B4 7901 A2
4625 B4 7903 B3
4626 A6 7904 B3
4628 A5 7962 B3
4630 A6 7991 A3
4683 B4 9664 B4
4684 A5 9701 A7
4694 A4
4695 B5
4720 B7
4721 C7
4722 B7
4723 B7
4905 B3
4930 A4
4931 A4
4973 A2
4974 A3
4984 A4
5248 A7
5249 A7
5250 A7
5251 A7
5685 A4
5686 A4
5687 B6
5688 B6
5704 A7
5705 A7
5706 A7

Layout LSP (Part 1 Bottom Side)



Layout LSP (Part 2 Bottom Side)



Layout LSP (Part 3 Bottom Side)



Layout LSP (Part 4 Bottom Side)



SSB: If & SAW Filter

1112-A A4	1114-A B5	2102 A1	2126 A6	2132 B10	2136 C10	3102 C4	3106 D1	3132 D7	3137 C10	4103 B3	5101 C1	5129 B6	6102 C4	7131 B10	F132 E10	F138 B4	I103 A4	I107 C9
1112-B A10	1114-B A10	2103 D2	2127 A6	2133 B1	2137 B2	3103 B3	3112 D3	3133 E7	3138 A6	4104 B3	5102 A1	5134 A2	7100-C A6	F114 E10	F134 D6	F139 A8	I104 B6	I108 E6
1113-A B4	1115 D10	2115 D5	2128 C6	2134 A2	2138 A2	3104 B3	3116 D6	3134 B1	4101 A3	4107 A3	5112 B2	5134 A2	7101 D2	F115 D10	F134 D6	I101 B1	I105 B6	
1113-B A10	2101 C1	2119 B2	2130 E7	2135 B1	3101 C2	3105 D3	3131 D7	3135 B9	4102 A3	4108 A3	5128 B6	6101 C2	7104 D4	F116 E10	F137 D3	I102 A4	I106 C6	



SSB: Video Source Selection & Data Link

1116 E1	2064 C2	2068 D2	2072 E2	2076 E2	2082 A7	2086 D4	3061 A8	3065 C2	3070 B1	3074 E3	5060 E3	7060-B B2	F060 B1	F076 E1	F088 F7	I063 D3	
2060 A3	2065 C2	2069 D2	2073 E2	2078 E3	2083 C4	2087 C2	3062 B3	3066 A8	3071 B3	4062 E2	5061 F3	7062 B8	F064 B7	F077 E1	F089 F7	I064 D3	
2062 B4	2066 D2	2070 D2	2074 E2	2079 F4	2084 C4	2088 A8	3063 B3	3067 B7	3072 E3	4152 D1	5063 A8	7063 B7	F074 E2	F078 E1	I061 C3		
2063 C2	2067 D2	2071 D2	2075 E2	2081 F3	2085 D3	3060 A2	3064 C2	3068 B7	3073 E3	4153 E2	7060-A A3	7100-B B4	F075 F1	F080 B4	I062 C3		

B2 VIDEO SOURCE SELECTION AND DATA LINK



SSB: Audio Source Select

1009 A8	2005 A8	2011 D1	2018 C2	2027 E2	2033 D9	2042 E4	2048 A2	3004 C2	3010 A2	3019 A1	3029 A10	6030 A10	7031-2 E9	F020 E8	F047 E2	I006 A8
1117 E1	2006 A8	2012 B2	2019 C2	2028 E2	2037 C9	2043 E3	2049 A2	3005 C2	3011 B2	3022 D9	3030 C10	7029-1 A9	7100-A A4	F021 E8	I001 B3	I007 C9
1118 B9	2007 B2	2013 C2	2021 D2	2029 A10	2038 C9	2044 E3	2050 A2	3006 A9	3012 E3	3024 E9	3031 D10	7029-2 A9	F014 E8	F041 E2	I002 E3	I008 C9
2002 A9	2008 B2	2014 C3	2022 D2	2030 D9	2039 D9	2045 A2	2051 B2	3007 A9	3013 E3	3026 C9	3032 D10	7030-1 C9	F015 E8	F042 E2	I003 E3	I009 D9
2003 A9	2009 C1	2015 C2	2024 D2	2031 C9	2040 D9	2046 A2	3002 D2	3008 E3	3016 A1	3027 D9	3033 E10	7030-2 D9	F016 E8	F045 B10	I004 E3	I010 D9
2004 C1	2010 C1	2016 C2	2025 D2	2032 E9	2041 E4	2047 A2	3003 C2	3009 E3	3018 A1	3028 A10	6029 A10	7031-1 D9	F017 E8	F046 E2	I005 E3	

B3 AUDIO SOURCE SELECT



SSB: MPIF-Supply, E/W, & Control

B4 MPIF-SUPPLY,E/W, & CONTROL



2150 A5
2151 C4
2152 C4
2154 C5
2155 D5
2156 D5
2157 E5
3150 A5
3151 B5
3152 B5
3153 C5
3154 B4
3155 E4
5150 D5
5151 D5
5152 E5
7100-D A2
7150-A A5
7150-B B5
F150 A8
F152 C8
F159 F8
I151 B3
I152 B3
I153 B3
I154 C3

SSB: Video Decoder

2281 A9 | 2282 C9 | 2284 D9 | 2285 D9 | 3281 C1 | 3282 D2 | 3283 D2 | 3284 D2 | 5281 A9 | 5282 C9 | 5283 D9 | 5285 D9 | 7300-J A3 | F281 D9 | F282 C2 | I281 D2

B5 VIDEO DECODER



3139 123 5536.2

CL 36532058_026.eps
211103

SSB: Feature Box

B6 FEATURE BOX

7300
BACK END PROCESSING



7300
MEMORY BASED PROCESSING



7300
FRONT END PROCESSING



CL 36532058_027.eps
020903

SSB: RGB Processing

2300 B1	2311 A9	2324 D4	2329 B8	3303 D7	3308 A5	3313 A8	3320 B8	3326 D4	3332 D8	3337 B4	3347 D6	5307 A5	6326 D4	7303 D8	7320-B B9	I301 C5	I306 A6
2305 E6	2317 B6	2325 C5	2331 C9	3304 D7	3309 A8	3316 B8	3321 C8	3328 C5	3333 D8	3338 D8	3348 D6	5317 B5	6327 E5	7304 D7	7330-A D8	I302 C6	I307 A5
2307 A6	2318 B5	2326 C6	2339 D8	3305 E7	3310 A8	3317 A5	3322 C8	3329 C8	3334 A4	3339 B5	3349 C6	5327 B5	7300-H A1	7310-A A8	7330-B D9	I303 D4	I308 A6
2308 A5	2319 A8	2327 B6	2346 E5	3306 E7	3311 A8	3318 D5	3323 C8	3330 C8	3335 B4	3343 E4	3356 E5	5328 C5	7301 A8	7310-B A9	7346 D5	I304 D5	I309 B5
2310 A9	2321 B9	2328 B5	3302 B1	3307 A8	3312 A8	3319 B8	3324 D5	3331 D8	3336 B4	3345 E5	5300 A1	6301 E7	7302 C8	7320-A B8	7356 E5	I305 A5	I310 B6



SSB: Sync & Deflection Processing

2341 B2	2350 A7	2360 C6	2365 D8	2379 E10	3351 A7	3357 C7	3363 B9	3368 C10	3375 E9	4363 B8	6341 C1	6368 C9	F346 E3	F357 C8	I344 C7	I349 E10
2342 C2	2351 A8	2361 C8	2366 C9	3340 A2	3352 A9	3358 A6	3364 B9	3371 D9	3376 D8	5342 C2	6353 A9	7300-F B3	F348 D10	F358 C9	I345 B9	I350 E10
2343 C2	2352 A9	2362 B9	2371 D9	3341 B2	3353 A9	3360 B8	3365 C8	3372 C8	3377 C8	5343 C2	6361 B9	7361 B8	F351 E6	I341 C6	I346 B8	
2344 C1	2358 D7	2363 B7	2372 D9	3346 D2	3354 A10	3361 B8	3366 C9	3373 C8	3378 B8	5344 C1	6365 C9	7365 C8	F354 A9	I342 C6	I347 C8	
2345 C1	2359 C6	2364 C8	2377 E10	3350 A8	3355 C6	3362 B9	3367 B10	3374 E9	4361 C9	5345 C1	6367 C9	F341 C3	F355 B8	I343 C6	I348 C9	



SSB: Protection

2380 B2 2386 B5 2395 E5 | 2395 D6 2397 D3 3380 B2 | 3382 A4 3384 E5 3385 B5 | 3386 B5 3388 C5 3390 C5 | 3391 E4 3392 E3 3393 D5 | 3394 D4 3395 E5 3396 D4 | 3397 C4 3398 C2 6381 A3 | 6382 A3 6384 B3 6385 A4 | 6397 C3 6398 C3 7300-G C6 | 7382 A4 7383-A E6 7383-B E5 | 7393 D5 F381 C6 F382 C6 | F383 C6 F384 A4 F385 B3 | F386 B2 F387 E4 F389 C3 | F390 C4 F391 B4 I381 A2 | I382 C4

1 2 3 4 5 6 7

B9 PROTECTION



CL 36532058_030.eps
211103

3139 123 5536.2

1 2 3 4 5 6 7

SSB: Audio Processing

2430 C7 2431 C6 2432 C6 2433 C5 2434 C5 2435 C6 2436 C6
2437 C7 2438 B9 2439 B9 2440 D7 2441 D7 2442 D8 2443 E7
2444 E7 2445 E7 2447 D1 2450 C4 2451 A8 2452 C4 2453 A7
2454 A4 2457 A2 2458 C6 2461 E9 2462 E9 2465 A5 2467 C6
2468 B6 2480 C8 2481 E8 2483 C9 2484 D8 2485 E9 2486 C9
2487 C9 2488 D10 2489 D10 3333 B9 3434 B8 3435 A8 3436 A8
3437 A8 3439 A7 3440 A7 3441 A7 3442 B7 3443 B7 3444 A7
3445 A4 3446 A4 3447 B4 3448 B4 3449 A5 3450 A4 3452 A3
3453 A2 3454 A3 3455 B3 3456 B3 3457 A3 3458 A5 3459 A5
3460 A6 3461 B5 3462 B6 3463 A6 3465 A9 3468 B6 3480 C8
3481 E8 3482 D8 3483 C9 3484 D9 3485 E9 3486 D10 3487 E10
4430 B3 4431 B4 4432 B6 4433 B7 4434 B8 4435 E3 4436 E3
4437 E3 4450 A10 4451 A10 4452 A10 4453 A10 4480 C8 4481 E8
5450 C4 5452 C4 5480 C8 6480 D10 6481 E10 7300-B C2 7430-A A8
7430-B A9 7431-A A7 7431-B A7 7432-A A4 7432-B A4 7433-A A3 7433-B A3 F437 E4
7434-A A6 7434-B A6 7480-A D9 7480-B E9 7486-A D10 7486-B E10
F438 E4 F439 E4 F448 C4 F449 C4 F480 C7 F481 E8 I431 A2
I432 A4 I433 A5 I434 A7 I435 A8 I436 C5 I437 C6 I438 C6
I439 C6 I440 C7 I441 D5 I442 D5 I443 E5 I444 E5 I445 C8
I446 D8 I447 D10 I448 E10

B10 AUDIO PROCESSING

7300
AUDIO DEMODULATION
DEMDEC & DD_DSP
SSIF
DOWNMIX
PREPROCESSING
SRC
DEMATRIX AND SELECT
DDEP
FROM VIDDEC
A_ADC1
A_ADC2
A_ADC3
A_ADC4
DECIMATION FILTER
TO AUDIO PROCESSING

UAB 12 NEED TO BE RAISE :
AE25 : AUD-SPKR-R-VRNEG
AF26 : AUD-SPKR-R-VRPOS

7300-B
ADOC

B4-68 VREF_AUD_POS
VREF_AUD_NEG
2447 100u

AE25 AUD-SPKR-R-VRPOS
AF26 AUD-SPKR-R-VRNEG
AD24 AUD-SPKR-L-VRPOS
AD26 AUD-SPKR-L-VRNEG
AF25 AUD-SPKR-SW-VRPOS
AF24 AUD-SPKR-SW-VRNEG
AF23 AUD-SPKR-C-VRPOS
AD23 AUD-SPKR-C-VRNEG
AA26 AUD-SPKR-SL-VRPOS
AB24 AUD-SPKR-SL-VRNEG
V26 AUD-DAC2-R-VRPOS
W24 AUD-DAC2-R-VRNEG
Y23 AUD-DAC2-L-VRPOS
W25 AUD-DAC2-L-VRNEG
AC26 AUD-HP-R-VRPOS
AC24 AUD-HP-R-VRNEG
AB25 AUD-HP-L-VRPOS
AC23 AUD-HP-L-VRNEG
Y24 AUD-DAC1-R-VRPOS
Y26 AUD-DAC1-R-VRNEG
AA25 AUD-DAC1-L-VRPOS
AA23 AUD-DAC1-L-VRNEG

FROM AUDIO DEMDEC & DD-DSP
LEVEL ADJ
INPUT X-BAR
PROCESSING
INPUT X-BAR
NOISE SHAPER
I2SIN
WS PLL
I2SOUT
AUDIO DSP
DAC
5D/A
2D/A
4D/A

AUD-SPKR-R AE26
AUD-SPKR-L AD25
AUD-SPKR-SW AE24
AUD-SPKR-C AE23
AUD-SPKR-SL AB23
AUD-DAC2-R W23 I441 1V6
AUD-DAC2-L W26 I442 1V6
AUD-HP-R AC25
AUD-HP-L AB26
AUD-DAC1-R Y25 I443 1V6
AUD-DAC1-L AA24 I444 1V6

SDI AF16
SCKI AE16
WSI AD16
SDO2 AD17
SCKO2 AD18
WSO2 AD19
SDO1 AE17
SCKO1 AE18
WSO1 AE19
SDAC1-VSSA AE22
SDAC1-3V3
SDAC1-VDDA

4435
4436
4437
F439 F438 F437

+8V
3453 47K I431
3452 1K2
7433-B BC847BPN
2457 2u2
3454 56K
7V3
2V7
7433-A BC847BPN
3457 1K5
3455 56K
3456 1K2
4V
4430

3445 47K I432
3450 1K2
7432-B BC847BPN
2454 2u2
3446 56K
7V3
2V7
7432-A BC847BPN
3449 1K5
3447 56K
3448 1K2
4431

FOR SUBWOOFER SET
3458 47K I433
3460 1K2
7434-B BC847BPN
2465 2u2
3459 56K
7434-A BC847BPN
3463 1K5
3461 56K
3462 1K2
4432

FOR DPL SET
3439 47K I434
3440 1K2
7431-B BC847BPN
2453 2u2
3441 56K
7431-A BC847BPN
3444 1K5
3443 56K
3442 1K2
4433

3436 47K I435
3437 1K2
7430-B BC847BPN
2451 2u2
3435 56K
7430-A BC847BPN
3465 1K5
3434 56K
3433 1K2
4434

4450 AUDIO-R B18-94
4451 AUDIO-L B18-95
4452 AUDIO-SW B18-96
4453 AUDIO-C B18-97
R_TV_IN
L_TV_IN
SW_TV_IN
C_TV_IN
AUDIO-SURR B18-98

PROVISION FOR DVD INTERFACE
REFER TO SHT B10a
ALL STRAPS TO BE
REMOVE FOR DVD

VDDE
5450 100MHZ / 220R
2450 10n
F448 AC22
SDAC1-3V3

VDDCO
5452 100MHZ / 220R
2452 10n
F449 AD22
SDAC1-VDDA

AUDSPKR_R
AUDSPKR_L
AUDSPKR_C
AUDSPKR_SR

2434 470n I436
2435 470n I437
2467 470n I438
2436 470n I439
2437 470n I440
2433 1n
2432 1n
2458 1n
2431 1n
2430 1n

2468 1n
3468 100R
2440 1n
2441 1n
2442 1n
2445 1n
2444 1n
2443 1n

2438 470n DSNDR2 B3-62
2439 470n DSNDL2 B3-63

HEADPHONE AMPLIFIER
4480
F480
2480 470n
3480 2K7
I445
3483 8K2
2483 1n
5480 100MHZ / 220R
+5V
2487 10u 16V
2486 100n
4V9
I447
3482 4K7
I446
3484 4K7
2484 10u 16V
2V5
7480-A TDA1308T
2488 100u
6480 BZX384-C12
HEADPHONE-R B18-99
7486-A BC847BS
3486 1K8
F481
2481 470n
3481 2K7
7480-B TDA1308T
2489 100u
6481 BZX384-C12
7486-B BC847BS
3487 1K8
SOUND-ENABLE_2
B3
2485 1n
3485 8K2
I448
4481
HEADPHONE-L B18-100

2461 470n DSNDR1 B3-64
2462 470n DSNDL1 B3-65

F480 100mV / div AC 1ms / div
F481 100mV / div AC 1ms / div
I436 20mV / div AC 500µs / div
I437 20mV / div AC 200µs / div
I438 100mV / div AC 1ms / div

3139 123 5536.2
CL 36532058_031.eps 211103

SSB: Control

0201 A10	2525 C3	2583 D5	3507 B3	3513 B2	3542 A9	3549 B9	3565 D8	3581 C4	4560 D8	6589 C10	7581 E5	F513 C10	F519 C10	F527 A1	F539 B7	F550 B9	I502 E6
0202 A10	2546 C9	2584 D5	3508 B2	3515 B2	3543 B9	3550 A9	3570 E8	3582 E4	4570 E9	7300-A E8	F508 B1	F514 B10	F520 A9	F532 D2	F540 B7	F551 B3	
1581 C5	2557 C9	3501 A3	3509 B3	3518 A3	3544 A9	3557 C9	3571 E9	3583 E6	4571 E9	7300-C A4	F509 B1	F515 B10	F521 A9	F533 B7	F541 B7	F570 E7	
1582 E4	2571 E7	3502 A4	3510 B3	3523 C3	3546 B9	3561 C9	3572 E9	3586 E6	4573 E9	7300-D A8	F510 C10	F516 B9	F522 A9	F534 B3	F542 B7	F582 E5	
2514 B1	2581 C4	3503 B1	3511 B1	3530 E3	3547 C9	3562 D8	3573 E8	3590 D6	5570 E7	7300-K C6	F511 C10	F517 B9	F523 A9	F537 A4	F543 B7	F584 D6	
2516 C1	2582 C4	3504 A2	3512 B1	3541 A10	3548 B9	3564 D9	3580 C3	4501 E9	5583 D4	7525 D2	F512 C10	F518 B9	F524 A4	F538 B3	F544 B7	I501 A1	



SSB: Control-Memory Interface (EBIU)

0290 B7
0291 B9
2792 B4
2793 B6
4790 F1
4791 E4
5792 A4
7300-E B1
7790 B4
F790 E1
F791 E1
F792 F1
F793 E3
F794 E3
F795 D3
F797 E5
F798 E3
F799 E3

B 1 2 CONTROL-MEMORY INTERFACE (EBIU)



3139 123 5536.2

CL 36532058_033.eps
211103

SSB: Control-Memory Interface (SDRAM)

2730 B6
2731 B6
2732 B5
2733 B7
2734 B7
3737 E4
5730 A6
5731 A7
7300-I B2
7730 B6
F730 D2

B13 CONTROL-MEMORY INTERFACE (SDRAM)



3139 123 5536.2

CL 36532058_034.eps
030903

SSB: ADOC Supply

2600 C10 2601 C10 2604 C10 2607 C9 2609 C9 2611 C9 2612 C9 2615 C8 2618 C8 2620 C8 2622 C7 2623 C7 2628 C7 2629 C6 2630 C6 2633 C6 2634 C6 2638 C2 2644 D7 2645 C1 2649 C2 5600 C1 5601 D7 7300-L B6 7300-M A1 F601 C1 I601 D8

B14 ADOC SUPPLY



SSB: Low Voltage Supply ADOC

B15 LOW VOLTAGE SUPPLY - ADOC



2651 A4
2652 A4
2654 A2
2655 A2
2656 E2
2657 D2
2658 D5
2659 C2
3651 D5
3652 D5
3653 D5
5651 A4
5652 A4
5654 A2
5659 C2
6651 A3
7650 C2
7651 B3
F650 C3
F651 A5
F652 D2
I651 A2

3139 123 5536.2

CL 36532058_036.eps
211103

SSB: Connector Interface

B18 SSB-CONNECTOR INTERFACE



3139 123 5536.2

CL 36532058_037.eps
211103

Layout SSB (Overview LOT Side)

1113 C2 2022 B3 2047 B2 2088 A1 2133 C2 2156 A2 2326 D4 2359 C5 2435 A4 2447 A3 2467 A4 2514 B4 2601 B4 2628 B5 2654 C6 2792 C6 2949 C3 2977 C4 3018 A2 3068 A2 3448 A4 3928 C5 5600 B6
1116 B1 2031 A2 2048 B2 2101 C2 2134 B2 2157 A2 2341 C4 2360 C5 2436 A3 2450 B4 2468 A3 2516 C4 2604 B4 2629 B5 2655 C6 2793 B6 2950 C4 2978 C3 3019 B3 3070 A1 3449 A4 3929 C5 5601 C5
1118 A1 2032 B2 2049 B2 2102 C2 2135 C2 2281 B5 2342 C5 2371 C4 2437 A5 2451 A4 2480 A5 2525 B3 2607 B4 2630 B4 2656 C7 2904 D2 2951 C4 2979 D6 3024 A3 3101 C2 3450 A4 3937 D3 5651 B7
1581 C3 2033 B2 2050 B2 2103 C2 2136 B2 2282 B4 2343 C5 2372 C4 2438 A4 2452 B4 2481 A5 2546 B4 2609 C4 2633 B4 2657 C7 2915 D2 2962 C6 3002 B3 3026 A3 3102 C2 3452 A4 3938 C4 5652 B7
1582 A6 2038 A3 2051 B2 2115 C2 2137 B2 2284 B5 2344 C4 2377 C4 2439 A4 2453 A3 2483 A6 2557 B4 2611 C5 2634 C5 2658 C6 2918 D2 2967 C7 3004 B3 3027 B3 3103 C2 3453 A4 3950 C4 5654 C6
2002 A3 2039 B3 2060 C1 2119 B2 2138 B2 2285 C4 2345 C4 2379 C4 2440 A4 2454 A4 2484 A5 2571 A5 2612 C5 2638 B4 2659 C6 2919 D2 2968 C7 3006 A3 3060 C1 3104 C2 3454 A4 3951 C4 5659 C6
2006 A2 2040 A3 2062 B1 2126 B2 2150 B1 2300 B4 2346 C4 2430 A4 2441 A4 2457 A4 2485 A6 2581 C3 2615 B5 2644 B4 2730 A6 2920 D3 2972 D7 3010 B2 3061 A1 3105 C2 3455 A4 3962 C6 5730 A6
2014 B2 2043 B2 2078 A2 2127 B2 2151 B1 2305 C5 2350 C5 2431 A4 2442 A4 2458 A4 2486 A6 2582 C3 2618 B5 2645 B5 2731 A6 2937 D3 2973 D7 3011 B2 3062 C1 3106 C2 3456 A4 3963 D2 5731 A6
2015 B2 2044 B2 2079 A2 2128 B3 2152 B1 2310 C4 2351 C5 2432 A4 2443 A4 2461 A5 2487 A6 2583 C4 2620 B5 2649 B5 2732 A7 2938 C4 2974 D7 3012 B2 3063 C1 3112 C2 3457 A4 3964 D2 5792 C6
2016 B3 2045 B2 2081 A2 2130 B2 2154 C1 2324 C5 2352 C5 2433 A4 2444 A4 2462 A4 2488 A6 2584 A7 2622 B5 2651 B6 2733 A6 2941 C4 2975 D7 3013 B1 3066 B1 3116 B2 3458 A3 3972 D7 6101 C2
2021 B2 2046 A2 2082 B1 2132 C2 2155 B2 2325 C4 2358 C5 2434 A4 2445 A4 2465 A3 2489 A7 2600 B5 2623 B5 2652 B6 2734 B6 2948 C3 2976 D7 3016 B2 3067 B1 3131 B2 3459 A4 3973 D7 6102 C2
3132 B2 3460 A3 3974 D7 6301 C5
3133 B2 3461 A4 3975 D7 6326 C4
3134 C2 3462 A4 3976 D7 6327 C4
3135 B2 3463 A4 3977 C4 6341 C4
3137 C2 3465 A5 3978 C3 6480 A6
3138 B2 3468 A4 3979 D6 6481 A5
3150 B1 3480 A6 3980 C3 6589 A7
3151 B1 3481 A5 4062 B1 6651 B6
3152 B1 3482 A5 4108 B3 7060 C1
3281 A5 3483 A6 4153 B1 7062 A1
3282 A5 3484 A5 4430 A4 7063 B1
3283 A5 3485 A5 4431 A4 7101 C2
3284 A5 3501 C4 4432 A4 7104 C2
3302 C4 3502 C4 4433 A3 7131 C2
3303 D5 3503 C4 4434 A4 7150 B1
3304 D4 3504 C4 4435 B4 7304 D5
3305 C5 3507 C4 4436 B4 7346 C4
3306 C4 3508 C4 4437 B4 7430 A4
3318 C4 3511 B4 4450 A7 7431 A3
3324 C4 3512 C4 4451 A7 7432 A4
3326 C4 3513 B3 4452 A7 7433 A4
3328 C4 3515 B3 4453 A7 7434 A4
3334 C4 3518 C4 4480 A5 7480 A6
3335 C4 3523 B3 4481 A5 7525 B3
3336 C4 3530 B4 4560 B4 7581 B7
3337 C4 3541 A7 4570 A5 7650 C7
3340 C4 3542 B3 4571 A5 7651 C7
3341 C4 3543 B4 4573 A5
3343 C4 3544 B3 4790 B6
3346 C4 3546 B4 4791 B6
3347 C4 3547 B4 5060 A2
3348 C4 3548 B4 5061 A2
3349 D4 3549 B4 5062 A2
3350 C5 3550 A3 5063 B1
3351 C5 3557 B4 5101 C2
3352 C5 3561 B4 5102 C2
3355 C5 3563 B4 5112 B2
3357 C5 3564 B4 5128 C2
3358 C5 3565 B4 5134 B2
3371 C4 3570 A5 5135 B2
3374 C4 3571 A5 5150 B2
3375 C4 3572 A5 5151 A2
3388 C4 3573 A5 5152 A2
3390 C4 3580 A5 5281 B5
3433 A5 3581 A5 5282 B4
3434 A5 3582 B7 5283 B5
3435 A4 3583 B7 5285 B4
3436 A4 3586 A7 5300 C4
3437 A4 3590 B7 5328 C4
3439 A3 3651 C6 5342 C5
3440 A3 3652 C6 5343 B5
3441 A3 3653 C6 5344 B4
3442 A3 3737 B5 5345 B4
3443 A3 3904 C2 5450 B4
3444 A3 3909 D2 5452 B4
3445 A4 3911 D2 5480 A6
3446 A4 3918 C2 5570 A5
3447 A4 3919 C2 5583 B4



3139 123 5536.2

CL 36532058_038.eps
030903

Layout SSB (Part 1 LOT Side)



Layout SSB (Part 2 LOT Side)



CL 36532058_38b.eps
030903

Layout SSB (Part 3 LOT Side)



CL 36532058_38c.eps
030903

Layout SSB (Part 4 LOT Side)



Layout SSB (Overview Tuner Side)

0201	B5	1901	D7	1911	D6	1924	D5	1934	D5	1949	D3	1959	D3	1967	D2	1976	D2	2008	B7	2028	B5	2066	B7	2074	A7	2307	C3	2328	C4	2365	C3	2933	C5	3022	A5	3154	B7	3313	C3	6397	C5
0202	B5	1902	D7	1913	D6	1925	D5	1935	D5	1950	D3	1960	D3	1968	D2	1977	D2	2012	B5	2030	A6	2067	B7	2075	A7	2308	C4	2329	C4	2366	D3	2935	D5	3064	C7	3155	A7	3316	C4	6398	C5
0290	C2	1903	D7	1915	D6	1926	D5	1936	D4	1951	D3	1961	D3	1969	D2	1978	D2	2013	B6	2037	A5	2068	B7	2076	A7	2311	C4	2331	D4	2380	C5	2936	D5	3065	B7	3307	C3	3317	C4	7100	B6
0291	B2	1904	D6	1918	D6	1928	D5	1937	D4	1952	D3	1962	D3	1970	D2	1979	D1	2018	B6	2041	A7	2069	C7	2083	B7	2317	C4	2339	C4	2384	C5	3003	B5	3071	C7	3308	C4	3319	D4	7300	B3
1112	B5	1906	D6	1919	D6	1929	D5	1938	D4	1953	D3	1963	D2	1972	D2	1980	D1	2019	B5	2042	A7	2070	B7	2084	B7	2318	C4	2361	C3	2386	C4	3005	B5	3072	A7	3309	D3	3320	D4	7301	C3
1114	C6	1907	D6	1920	D5	1931	D5	1939	D4	1955	D3	1964	D2	1973	D2	2003	A5	2024	B6	2063	C7	2071	B7	2085	B7	2319	C4	2362	C3	2395	C5	3007	A5	3073	A7	3310	D4	3321	C4	7302	C4
1115	A7	1909	D6	1921	D5	1932	D5	1941	D4	1956	D3	1965	D2	1974	D2	2005	A6	2025	B5	2064	C7	2072	A7	2086	B7	2321	D4	2363	C3	2397	C5	3008	A7	3074	A7	3311	C3	3322	C4	7303	C4
1117	B7	1910	D6	1923	D5	1933	D5	1948	D3	1958	D3	1966	D2	1975	D2	2007	C7	2027	B6	2065	B7	2073	A7	2087	B7	2327	C4	2364	C3	2932	C5	3009	A7	3153	B7	3312	C3	3323	C4	7310	D3
																																						3329	D4	7320	D4
																																						3330	D4	7330	D4
																																						3331	C4	7356	C5
																																						3332	C4	7361	C2
																																						3333	C4	7365	D3
																																						3338	C4	7382	C4
																																						3339	C4	7383	C5
																																						3345	C6	7393	C5
																																						3353	C5	7730	A2
																																						3354	C5	7790	C2
																																						3356	D5		
																																						3360	C3		
																																						3361	C3		
																																						3362	D3		
																																						3363	C3		
																																						3364	C3		
																																						3365	D3		
																																						3366	D3		
																																						3367	C3		
																																						3368	D3		
																																						3372	D3		
																																						3373	C3		
																																						3376	C3		
																																						3377	D3		
																																						3378	D3		
																																						3380	C5		
																																						3382	C4		
																																						3384	C5		
																																						3385	C5		
																																						3386	C4		
																																						3391	C5		
																																						3392	C5		
																																						3393	C5		
																																						3394	C5		
																																						3395	C5		
																																						3396	C5		
																																						3397	C5		
																																						3398	C5		
																																						3509	C5		
																																						3510	C5		
																																						3936	D6		
																																						3939	D6		
																																						4101	C6		
																																						4102	C6		
																																						4103	C6		
																																						4104	C6		
																																						4107	C6		
																																						4152	C7		
																																						4361	D3		
																																						4363	C2		
																																						4501	A2		
																																						5129	B5		
																																						5307	C4		
																																						5317	C4		
																																						5327	C4		
																																						6353	C5		
																																						6361	C2		
																																						6365	C3		
																																						6367	C3		
																																						6368	C3		
																																						6381	C5		
																																						6382	D5		
																																						6384	C5		
																																						6385	C4		

Layout SSB (Part 1 Tuner Side)



CL 36532058_39a.eps
030903

Layout SSB (Part 2 Tuner Side)



CL 36532058_39b.eps
030903

Layout SSB (Part 3 Tuner Side)



Layout SSB (Part 4 Tuner Side)



Side I/O Panel (FL9)



1326-1 C1	6808 B2
1326-2 C1	7811 B4
1326-3 D1	7812 B5
1327 E1	7813 A5
1328 B1	9800 F6
1344 F9	9810 A6
1346 E9	9811 A6
1800 E2	9812 F9
1801 C2	9820 C3
1802 F2	9821 D3
1803 F2	9827 E5
1804 E3	9829 F3
1805 B2	F001 A2
1806 A2	F002 B2
1936 C9	F003 B2
2803 C3	F005 C2
2804 C4	F006 D2
2805 D4	F007 D2
2806 D3	F008 E2
2807 A3	F009 E2
2810 B4	F010 E2
2811 B5	F011 A6
2813 C6	F013 A8
2832 E6	F014 C9
2834 F4	F015 A8
2840 F2	F016 C6
2841 F2	F017 C8
3801 A3	F018 B8
3802 C3	F019 C7
3803 C3	F020 F9
3804 D3	F021 F9
3805 C3	F022 F9
3806 D3	F023 F6
3808 A4	F024 F7
3809 A3	I801 B3
3810 C4	I802 A3
3811 C4	I803 A4
3812 B4	I804 A4
3813 B5	I805 A3
3814 C5	I806 A4
3815 C3	I807 A5
3816 B3	I808 B5
3826 E5	I809 B5
3827 E5	I810 B5
3828 F3	I811 B4
3829 F3	I812 C4
3830 F4	I813 B3
3835 D5	I814 C3
3842 E5	I815 D3
3845 A3	I816 E3
3846 A4	I817 A3
3847 A4	I818 B4
3848 A5	I819 D2
3849 A5	I820 E2
3850 A4	I821 D2
3999 F6	I822 F5
4800 D2	I823 F6
4801 D2	
4803 F5	
4804 C6	
4805 A3	
4806 F8	
4808 F9	
4809 E8	
4810 F8	
4811 F8	
4812 F8	
4830 E3	
4831 F3	
5801 F3	
5802 F3	
6801 B3	
6802 C2	
6803 C3	
6804 D2	
6805 D3	
6806 E2	
6807 A3	

Layout Side I/O Panel (FL9) (Top Side)



1326 D2
1327 C2
1328 E2
1344 A2
1346 C1
1936 B1
2811 D1
2813 B1
3802 E2
3803 D1
3804 C2
3826 A2
3827 A2
3828 B2
3829 B2
3830 B2
3835 B2
3842 A2
3850 E1
3999 A1
9800 C1
9802 B1
9803 C1
9804 C1
9805 D1
9806 A2
9810 B1
9811 D1
9812 A2
9820 D1
9821 C2
9827 A2
9829 B2

Layout Side I/O Panel (FL9) (Bottom Side)



2803 D1
2804 D1
2805 C1
2806 D1
2807 E1
2810 E2
2832 A2
2834 A2
2840 B1
2841 B1
3801 E2
3805 D1
3806 C1
3808 D2
3809 E2
3810 E2
3811 D2
3812 E2
3813 D2
3814 C2
3815 E1
3816 E2
3845 E2
3846 E2
3847 E2
3848 E2
3849 E2
4800 C1
4801 C2
4802 B2
4803 B2
4804 C2
4805 E1
4806 C2
4808 C2
4809 C2
4810 B1
4811 A1
4812 A2
4813 B1
4830 B1
4831 B1
5801 B1
5802 B1
6801 E2
6802 E1
6803 D1
6804 D1
6805 C1
6806 D1
6807 E2
6808 E2
7811 D2
7812 D2
7813 E2

Side I/O Panel (SL5/PV2)



Personal Notes:

Layout Side I/O Panel (SL5/PV2) (Top Side)

0240	A3	1256	A2	2292	A2	2297	A4	3287	A1	3291	A3	9231	A3
1254	A4	2286	A2	2294	A3	3285	A2	3288	A1	3293	A3	9232	A4
1255	A3	2288	A1	2296	A4	3286	A2	3289	A1	3295	A2		



Layout Side I/O Panel (SL5/PV2) (Bottom Side)

3292	A3	3297	A1	4241	A3	4291	A1	5292	A1	6293	A1	6296	A3
3294	A2	4201	A3	4242/2243	A1	4292	A1	6291	A2	6294	A1	6297	A3
3296	A1	4202	A4	4243	A2	5291	A1	6292	A1	6295	A3		

Front Control Panel

0215 A1 1093 A4 2010 A1 3089 B3 3092 A2 3095 A4 6091 A4 I003 A3 I006 A2 I009 A4
1091 A2 1094 B4 3087 B4 3090 B2 3093 A3 3096 B4 I001 A1 I004 A4 I007 A2 I012 B3
1092 A3 1095 A4 3088 B3 3091 A2 3094 A3 3098 B3 I002 A2 I005 A4 I008 A3 I021 A4



Personal Notes:

Layout Front Control Panel (Top Side)



0215 A1
1091 C1
1092 C1
1093 B1
1094 B1
1095 B1

Layout Front Control Panel (Bottom Side)



2010 A1
3087 B1
3088 B1
3089 C1
3090 C1
3091 A1
3092 C1
3093 C1
3094 C1
3095 B1
3096 B1
3098 B1
6091 B1

Top Control Panel (PV2)



0215 A1
0216 E1
0217 D1
1090 D2
1091 B2
1092 B3
1093 B4
1094 B4
1095 B4
2010 A2
2011 D2
2012 D3
2013 E2
2014 E3
2015 E2
2016 E3
2017 E4
2018 E4
2019 D3
2020 E2
3010 D2
3011 D2
3012 E2
3086 A4
3087 B4
3088 B3
3089 B3
3090 B2
3091 A2
3092 A2
3093 A3
3094 A3
3095 A4
3096 B4
3097 B3
3098 B3
4089 B3
4090 B2
4091 A2
4092 A2
4093 A3
4094 A3
6091 B4
6092 B4
6093 B4
7091 D3
F001 D2
F002 E2
F003 E2
F004 E3
I001 A2
I002 A2
I003 A3
I004 A4
I005 A4
I006 A2
I007 B2
I008 B3
I009 B4
I010 D3
I011 D2
I012 C3
I013 D2
I016 D3
I017 E3
I019 E4
I020 E4
I021 B4

Personal Notes:

Layout Top Control Panel (PV2) (Top Side)



0215 A1
0216 F1
0217 D1
1090 F1
1091 B1
1092 C1
1093 D1
1094 E1
1095 C1
2011 F1
2015 E1
6091 B1

Layout Top Control Panel (PV2) (Bottom Side)



2010 A1
2012 E1
2013 D1
2014 D1
2016 D1
2017 E1
2018 F1
2019 F1
2020 E1
3010 F1
3011 E1
3012 D1
3086 C1
3087 D1
3088 C1
3089 B1
3090 B1
3091 A1
3092 B1
3093 B1
3094 B1
3095 C1
3096 D1
3097 D1
3098 C1
4010 E1
4011 F1
4089 B1
4090 B1
4091 A1
4092 B1
4093 B1
4094 B1
6092 D1
6093 C1
7091 D1

Top Control Panel (FL9)

0215 A1	1093 A4	2010 A1	3093 A2	3096 B4	6092 B3	I001 A1	I004 A3	I007 B2
1091 A2	1094 B4	3091 A2	3094 A3	3099 B1	F001 B1	I002 A2	I005 A4	I008 B3
1092 A3	1095 A3	3092 A2	3095 A4	6091 A4	F002 B1	I003 A2	I006 A4	I009 A4



3139 123 5699.2

Personal Notes:

Layout Top Control Panel (FL9) (Top Side)



Layout Top Control Panel (FL9) (Bottom Side)



CRT Panel



For Europe

ITEM	SIZE/TUBE 29RF A68ERF182X044	28WSRF A66ERF172X044	32WSRF A66ERF172X044	28BLD A66EAK075X054
1354	NON-DAF SOCKET	DAF SOCKET	DAF SOCKET	NON-DAF SOCKET
2371	5.6pF	5.6pF	5.6pF	5.6pF
2372	5.6pF	5.6pF	5.6pF	5.6pF
2373	5.6pF	5.6pF	5.6pF	5.6pF
2374	330nF	330nF	330nF	330nF
3306	5R6	5R6	5R6	6R8
3307	5R6	5R6	5R6	3R3
3358	4K7	4K7	4K7	4K7
3359	6K8	6K8	6K8	6K8
3360	220R	220R	220R	220R
4301	NOT USED	NOT USED	NOT USED	NOT USED
4302	NOT USED	NOT USED	NOT USED	NOT USED
4303	USED	USED	USED	USED
4304	USED	USED	USED	USED
4305	USED	USED	USED	USED
4306	USED	USED	USED	USED
4307	USED	USED	USED	USED
4308	USED	USED	USED	USED
4310	USED	USED	USED	USED
4311	NOT USED	NOT USED	NOT USED	NOT USED
4312	NOT USED	NOT USED	NOT USED	NOT USED
4313	NOT USED	NOT USED	NOT USED	NOT USED
6335	BAV99	BAV99	BAV99	BAV99
6336	BAV99	BAV99	BAV99	BAV99
6390	NOT USED	NOT USED	NOT USED	NOT USED
6391	NOT USED	NOT USED	NOT USED	NOT USED
9302	USED	USED	USED	USED
9324	NOT USED	NOT USED	NOT USED	NOT USED
Rotation crt	NOT USED	USED	USED	NOT USED

F_15040_011.eps
290405

Layout CRT Panel (Top Side)

1316	B4	1336	D1	1388	D2	2339	D3	2390	B1	3331	D3	3337	D3	3349	D3	3367	A3	5304	C3	5349	D2	7332	B4	7366	A1	9331	A2
1317	E2	1340	E2	2313	C4	2340	D3	3305	A2	3332	D2	3341	D4	3350	A2	3371	A4	5308	B2	5361	B4	7333	B4	9301	D3	9332	D2
1330	D3	1351	A1	2317	D1	2347	D2	3306	A2	3333	D4	3344	E4	3351	C4	3372	A4	5339	A3	6386	E1	7340	D4	9302	C3	9333	E3
1331	D4	1354	C1	2319	C1	2363	A4	3307	A1	3334	C3	3345	C4	3352	D4	3373	A3	5346	B3	6387	E1	7350	D4	9324	B3	9334	C1
1334	D4	1361	A4	2324	C1	2368	A4	3317	E3	3335	D2	3347	D1	3356	C4	3395	A2	5347	D3	6388	E2	7363	B4	9328	C3		
1335	B1	1382	B1	2338	D4	2381	B2	3318	B1	3336	D2	3348	C1	3361	B3	5303	B2	5348	D4	7330	D3	7364	B4	9330	E4		



Layout CRT Panel (Bottom Side)

2332	D2	2353	D1	2360	E3	2370	A4	2388	A3	3339	D2	3362	A2	3377	B2	3388	D3	4304	E3	4312	D1	4387	D3	5344	E3	6333	D1
2333	D2	2354	E3	2361	B3	2382	A2	2389	A4	3340	E2	3363	A2	3378	A3	3392	A1	4305	E3	4313	D1	4388	D3	5345	E3	6334	B4
2336	D2	2355	E3	2362	E3	2383	A1	3319	A4	3342	D1	3364	A1	3379	A2	3394	B1	4306	E3	4314	D1	4389	D3	6307	D2	6361	B2
2343	D1	2356	D1	2364	B2	2384	A1	3320	B4	3343	E1	3365	A1	3380	A3	3396	B4	4307	E3	4315	D2	5340	E3	6308	A3	7331	A3
2344	E1	2357	B2	2365	B2	2385	B1	3321	A4	3354	E1	3366	A1	3381	A3	3999	B3	4308	E3	4321	E1	5341	E3	6325	E2	7361	A2
2346	D1	2358	E3	2367	A4	2386	B2	3322	B4	3355	E1	3368	B1	3386	D4	4302	C3	4309	D3	4330	A3	5342	E3	6331	D2	7362	A2
2352	E1	2359	E3	2369	D2	2387	B2	3325	E2	3357	B4	3370	B2	3387	D4	4303	E3	4311	D3	4386	D3	5343	E3	6332	D3	7365	A2



Mains Switch Panel (FL9)

MAINS SWITCH PANEL(FL9)

M

RC5 RECEIVER

TO 1624 OF A6 INTERFACING

TO 0010 OF A1 OR TO 1505 OF A1 POWER SUPPLY

only for AP 178 - 250V

3139 123 6041.2

F_15040_035.eps 310305

0201 E2
0202 E7
0247 A7
1010 A2
1051 E4
2030 A2
2031 C5
2032 D6
3057 E3
3066 E3
3078 A4
3081 B3
3082 A3
3083 C3
3084 B1
3085 B5
3086 C5
3087 C7
3088 C5
3089 C4
3090 C4
3091 D6
3092 A4
3093 B3
3099 E5
4000 C3
4001 B4
4003 C4
4004 D7
4006 B3
4008 B3
4009 A3
4010 A3
6001 C3
6053 B1
6054 C6
7000 B5
7001 C3
7002 C5
7003 C7
F003 E2
F004 E7
F005 E2
F006 E7
F007 B7
F008 B7
F009 B5
F010 D3
F011 E6
F012 E5
I001 A2
I002 B3
I003 A4
I004 B3
I005 E3
I006 B6
I007 C5
I008 C5
I009 C7
I010 C4
I011 C5
I012 C6
I014 D6
I015 D3
I016 D4

Layout Mains Switch Panel (FL9) (Top Side)



Layout Mains Switch Panel (FL9) (Bottom Side)



Mains Switch Panel (SL5)



0201 B7
0202 B9
0241 A1
0242 B2
1002 D5
1003 D5
1004 C6
1005 D6
1006 D5
1031 A8
1032 C9
1693 D2
2001 D3
2002 E3
2003 C4
2004 B6
2030 B8
3001 A4
3002 A5
3003 A5
3004 A4
3005 B4
3006 C3
3007 D3
3008 E3
3009 E3
3010 C2
3011 C4
3013 C5
3014 C5
3015 C5
3016 C5
3017 C5
3018 D6
3019 C6
3020 D4
3021 A5
3022 A5
3023 A6
3030 B8
3031 B7
3032 C7
4001 A4
4002 A4
4003 A4
4004 B4
4005 B4
4006 B5
4007 A3
4008 E3
6001 A4
6002-1 B5
6003 C6
6004 C3
6005 D3
6006 E3
6007 B6
6008 A5
6009 A6
6022-2 B4
7001 E3
7002 A6
7003 B6
9010 C2
9011 C4
9013 C5
9015 C5
9017 C5
9019 D4
9020 E4
9031 A8
9032 B8
F001 A2
F002 A2
F003 A2
F004 A2
F005 A2
F007 B2
F008 B2
F009 B2
F010 B7
F011 B7
F012 B9
F013 B9
I002 B7
I003 C7
I004 A4
I005 D2
I006 B5
I009 D3
I010 C4
I011 D4
I012 A5
I013 D2
I016 E3
I018 D5
I019 D5
I020 B4
I021 C5
I023 C6
I024 D6
I025 C4
I026 C5
I027 A5
I028 A6
I029 A6
I030 B6
I031 B6

Layout Mains Switch Panel (SL5) (Top Side)



0201 C4
0202 B4
0241 G3
0242 H3
1002 J1
1003 I1
1004 I1
1005 H1
1006 B2
1031 B3
1032 D3
1693 E3
2001 D1
2003 H2
2030 D4
3001 E2
3007 D2
3010 G2
3011 I2
3013 I2
3014 I2
3015 I2
3016 I2
3017 I2
3018 I1
3019 H2
3020 C2
3030 D4
3031 C3
3032 D2
6001 D1
6002 D2
6003 H2
6004 D1
6006 E1
6007 C2
6022 D2
9010 H2
9011 I2
9013 I2
9015 I2
9017 I2
9019 F3
9020 C2
9031 B3
9032 C3
9040 E2
9041 E2
9043 F2
9044 F1
9045 G2
9046 G2
9047 G2
9048 G2

Layout Mains Switch Panel (SL5) (Bottom Side)



2002 E4
2004 D3
3002 E3
3003 E4
3004 E3
3005 D4
3006 D4
3008 E4
3009 E4
3021 D3
3022 E3
3023 D4
4001 E3
4002 E3
4003 E3
4004 E4
4005 E4
4006 D4
4007 F2
4008 E4
4040 G3
6005 D4
6008 D3
6009 D3
7001 E4
7002 D4
7003 D3

Front Interface Panel (PV2)

Q1 FRONT INTERFACE PANEL PV2



3139 123 5499.3

F_15040_043.eps
310305

0201 D2
0202 D7
0203 A6
1910 A2
1951 D4
2930 A1
2931 C4
2932 D6
3957 E3
3966 E3
3978 A3
3981 A3
3982 A2
3983 C3
3984 A1
3985 A5
3986 B5
3987 B7
3988 B4
3989 B4
3990 C3
3991 C6
4900 C3
4901 B3
4903 B3
4904 D7
6901 B3
6953 A1
6954 C6
7900 B4
7901 B3
7902 C5
7903 D6
F903 D3
F904 D6
F905 D3
F906 D6
F907 A5
F908 A5
F909 A5
F910 C3
I901 A1
I902 B3
I903 A2
I904 B2
I905 E3
I906 B5
I907 B4
I908 B5
I909 C7
I910 C4
I911 B4
I912 C6
I913 A5
I914 D5
I915 E3

Layout Front Interface Panel (PV2) (Top Side)

0201 D1 0203 A3 1951 C2 2931 A4 3957 B3 3982 A3 6901 B4 7902 B3
0202 A1 1910 B4 2930 A4 2932 A1 3966 B3 3991 A2 6954 B2 7903 B3



Layout Front Interface Panel (PV2) (Bottom Side)

3978 A2 3983 C1 3985 A2 3987 A2 3989 A1 4900 C1 4903 A2 6953 C1 7901 A1
3981 A2 3984 B1 3986 A2 3988 A2 3990 A1 4901 A2 4904 B1 7900 A2



8. Alignments

Index of this chapter:

8.1 General Alignment Conditions

8.1.1 Default Alignment Settings

Perform all electrical adjustments under the following conditions:

- Power supply voltage: 230 V_{AC} / 50 Hz (± 10 %).
- Connect the set to the mains via an isolation transformer with low internal resistance.
- Allow the set to warm up for approximately 20 to 30 minutes.
- Measure voltages and waveforms in relation to chassis ground (with the exception of the voltages on the primary side of the power supply).
  Caution: never use heatsinks as ground.
- Test probe: 100 : 1, Ri > 10 Mohm, Ci < 3.5 pF.
- Use an isolated trimmer/screwdriver to perform alignments.

Perform all electrical adjustments with the following default settings (for all CRTs):

- Choose "Soft" picture mode with the "Smart Picture" button on the remote control.
- Set "Dynamic Contrast" and "Active Control" to "off" (if either one of them is present).
- Set "Brightness" to aligned value unless otherwise specified.
- Set "Contrast value" to 99.

8.1.2 Adjustment Sequence

Use the following adjustment sequence:

1. Set the correct TV-set OPTIONS as described in paragraph "Options". After storing, re-start the set.
2. Rough adjustment of VG2 and FOCUS (potentiometers in “midway” positions).
3. RF-AGC alignment.
4. IF-PLL OFFSET adjustment.
5. Rough adjustment of GEOMETRY.
6. Allow the set to warm up.
7. Precise adjustment of VG2 and FOCUS.
8. Precise adjustment of GEOMETRY.
9. PIP alignments (if present).
10. COLOUR alignments.
11. Other software alignments.

8.2 Hardware Alignments

Notes:

- The Service Alignment Mode (SAM) is described in chapter 5 "Service Modes, Error Codes, and Fault Finding".
- Use the cursor-, menu-, and OK-buttons of the remote control (RC) transmitter for navigation.



Figure 8-1 Top view LSP

8.2.1 Vg2 Adjustment

In the frame-blanking period of the R, G, and B signals applied to the CRT, the video processor inserts a measuring pulse with different DC levels. Measure the black level pulse during the vertical flyback at the RGB cathodes of the CRT.

1. Connect the RF output of a pattern generator to the antenna input. Input a "black" picture (blank screen on CRT without any OSD info) test pattern.
2. In the SAM mode, set the “Normal Red”, “Normal Green” and “Normal Blue” values to “0” for “White Tone”.
3. Disable the black current loop (via the AKB bit).
4. Use the MENU key to enter the "user" menu, select "Picture", and set "Brightness" and "Contrast" to “0”.
5. Set the oscilloscope to 20 V/div and the time base to 20 us/div. Use external triggering on the vertical pulse.
   Caution: use a trigger point on the "**cold**" side!
6. Ground the scope on the CRT panel ("**cold**" side) and connect a 10:1 probe to one of the cathodes of the picture tube socket (see circuit diagram B1).
7. Measure at test points F338, F339 and F341 on the picture tube socket the DC-level of the measuring pulse (1st full line after the frame blanking) with respect to earth.
8. Select the pin with the highest level found and adjust V_cutoff by means of the Vg2-potmeter (lowest-one) on the Line Output Transformer (LOT) to 160 +/- 5 V_{DC} (for all screen sizes).
9. Reset "Contrast" and "Brightness" to their original values.



Figure 8-2 Waveform Vg2 alignment

8.2.2 Focus alignment

The LOT has the following outline:
– Focus 1 (F1) = Static alignment (red wire).
– Focus 2 (F2) = Dynamic alignment (white wire).

1. Use an external video pattern generator to input a "circle" or "crosshatch" test pattern to the set.
2. Choose "Natural" picture mode with the "Smart Picture" button on the remote control transmitter.
3. Adjust the "dynamic focus 2" potentiometer (in the middle on the LOT) until the horizontal lines at the centre of the screen are of minimum width without introducing a visible haze.
4. Adjust the "static focus 1" potentiometer (highest of the LOT) until the horizontal lines at the sides of the screen are of minimum width without introducing a visible haze.
5. Repeat these two steps to achieve the best result.

8.3 Software Alignments

Put the set in the SAM (see the "Service Modes, Error Codes and Fault Finding" section). The SAM menu will now appear on the screen. The different alignment parameters are described further on.

Notes:
- All changes to menu items and alignments must be stored manually.
- If an empty EAROM (permanent memory) is detected, all settings are set to pre-programmed default values, so the set must be re-aligned.

8.3.1 Tuner

AGC
1. Set an external pattern generator to a colour bar video signal and connect the RF output to the aerial input of the TV. Set the amplitude to 10 mV and the frequency to 475.25 MHz. Use system PAL B/G if possible, otherwise match the system of your generator with the received signal in the set.
2. Put the set in the SAM mode.
3. Select via the TUNER menu, the AGC sub-menu.
4. Connect a DC multi-meter to pin 1 of the tuner (F235, AGC pin).
5. Adjust the AGC until the voltage at pin 1 (F235, AGC pin) of the tuner is 3.3 V (+/- 0.1 V). The value can be incremented or decremented by pressing the right/left CURSOR button on the RC.
6. After alignment, save the value(s) with the STORE command in the SAM main menu.

IF PLL OFFSET
No adjustments needed: default value is "35".

If the mentioned default value does not give the required result, use the following alignment method:
1. Set an external pattern generator to a crosshatch video signal and connect the RF output to the aerial input of the TV. Set the amplitude to 10 mV and the frequency to 475.25 MHz. Use system PAL B/G if possible, otherwise match the system of your generator with the received signal in the set.
   – For "Negative modulation", the **sound** signal must be a non-modulated FM signal.
   – For "Positive modulation", the **video** signal must have high modulation (100% or above).
2. Put the set in the SAM mode.
3. Select via the TUNER menu, the IF-PLL OFFSET sub-menu.
4. Measure and align:
   – For "Negative modulation", on SCART pin 1 or 3 (**audio** out): Adjust IF-PLL OFFSET until the largest Signal Noise Ratio (SNR) is reached.
   – For "Positive modulation", on SCART pin 19 (**video** out): Adjust IF-PLL OFFSET until you get minimal V-sync disturbance.

8.3.2 Geometry

Notes:
- Set an **external** pattern generator to a crosshatch video signal and connect the RF output to the aerial input of the TV. Set the amplitude at least 1 mV_{RMS} (60 dBµV) and the frequency to 475.25 MHz. Use system PAL B/G if possible, otherwise match the system of your generator with the received signal in the set.
  Note: Do **not** use the internal test pattern from the GEOMETRY menu!
- Use the default alignment settings, but set "Brightness" to "32".
- For wide screen models, set to "wide screen" mode, for "classic" models, set to "4:3".
- After alignment, save the value(s) with the STORE command in the SAM main menu.

Service tip: When the set is equipped with a rotation coil, use this menu item to check its correct alignment. If alignment is not correct, go to the user MENU, choose FEATURES, and select ROTATION. With the use of a crosshatch test pattern, align it to a correct horizontal picture.



Figure 8-3 Geometry Alignments

Use the following software regulations to modify the geometry:

1. VER. SHIFT (Vertical Shift): Align for the vertical picture centre, range from -32 to +32.
2. VER. AMPL (Vertical Amplitude): Compensating for any gain error in amplifier, adjust range from -32 to +32 to the proper amplitude.
3. VER. SCOR (Vertical S-Correction): Align for equal height of the blocks in the top, the bottom and the middle, range from -63 to +63.
4. VER. U_LIN (Vertical Upper Linearity): Align for linearity of the upper screen, range from -63 to +63.
5. VER. L_LIN (Vertical Lower Linearity): Align for linearity of the lower screen, range from -63 to +63.
6. HOR. SHIFT (Horizontal Shift): Adjust for the horizontal centre of the screen, range from -127 to +128.

Next step is to align the East/West geometry.

1. First, set the parameters EW_5 and EW_6 to "0"
2. EW. WIDTH (East-West Width): This sets the (overall) horizontal size of the picture on the screen. Range from -63 to +63 (with the following EW alignments, these lines can be straightened).
3. EW_1 (East-West parameter 1): Has effect on the length of the upper part of the vertical E/W lines.
4. EW_2 (East-West parameter 2): Has effect on the length of the vertical E/W lines just below EW_1.
5. EW_3 (East-West parameter 3): Has effect on the length of the vertical E/W lines just below EW_2.
6. EW_4 (East-West parameter 4): Has effect on the length of the vertical E/W lines just below EW_3.
7. EW_5 (East-West parameter 5): Has effect on the length of the vertical E/W lines just below EW_4.
8. EW_6 (East-West parameter 6): Has effect on the length of the vertical E/W lines just below EW_5.
9. EW_7 (East-West parameter 7): Has effect on the length of the vertical E/W lines just below EW_6.
10. EW_8 (East-West parameter 8): Has effect on the length of the vertical E/W lines just below EW_7.
11. EW_9 (East-West parameter 9): Has effect on the length of the vertical E/W lines just below EW_8.
12. EW_10 (East-West parameters 10): Has effect on the length of the lowest part of the vertical E/W lines.
13. HOR. BOW (Horizontal Bow): Align the EW parabola to be symmetrical, range from -63 to +63.
14. HOR. PARALLEL (Horizontal Parallel): Align for straight vertical lines on the picture sides, range from -63 to +63.
15. HOR. LIN (Horizontal Linearity): Align for equal width of horizontal blocks on the left, the right and the centre, range from -63 to +63.
16. HOR. SCOR (Horizontal S-correction): Align for equal height of the blocks on the left, the right and the centre, range from -63 to +63.
17. HOR. IN_PIN (Horizontal Inner Pincushion): Align for the inner straight vertical lines, range from -15 to +15.

8.3.3 White Tone

In the WHITE TONE sub menu, the colour values for the different colour temperatures can be changed.
The colour temperature mode (NORMAL, DELTA COOL, DELTA WARM) can be selected per colour (R, G, and B) with the RIGHT/LEFT cursor keys. The mode or value can be changed with the UP/DOWN cursor keys.
First, the values for the NORMAL colour temperature must be selected. Then the offset values for the DELTA COOL and DELTA WARM mode can be selected. Note that the alignment values are non-linear.

Alignment
Normally, no adjustments are needed.
If the white tone alignment values used in CSM of the the TV set do not give the required result, use the following alignment method:

1. Set the external pattern generator to a 100% white pattern, and connect its RF output to the aerial input of the TV. Set the amplitude to at least 1 mV_{RMS} (60 dBuV) and the frequency to 475.25 MHz. Use system PAL B/G if possible, otherwise match the system of your generator with the received signal in the set.
2. Set "Smart Picture" to "Natural".
3. Set "Dynamic NR" to "off".
4. Put the set in the SAM mode.
5. Select via the WHITE TONE menu, the PATTERN sub-menu.
6. Set PATTERN to "on".
7. Set NORMAL GREEN to "0".
8. Measure with the colour analyser (Minolta CA100 Colour Analyser or equivalent), calibrated with the spectra, on the centre of the screen.
9. Adjust with the cursor left/right command the Red and Blue register for the right xy-coordinates (see the table below).
10. Repeat the white tone adjustment also for the colour temperatures COOL and WARM.

Table 8-1 White tone alignment (with colour analyser)

White D mode	Temperature	DUV	x	y
Normal	8500 K	+-0.004	288 +/- 4	300 +/- 4
Cool	11500 K	+-0.005	273 +/- 5	282 +/- 5
Warm	7000 K	+-0.005	305 +/- 5	312 +/- 5

8.3.4 Sound

No adjustments needed. Use the given default values:

- PRESCALE LEVEL
  - FM: "+1".
  - NICAM: "+3".
  - EXTAM Gain: "0".
  - PIPMONO: "0".
  - ExtLR-in: "0".
- THRESHOLD LEVEL
  - Over Mod Tresh: "+3dB".
  - NIC ErrLmt_Hi: "200".
  - NIC ErrLmt_Lo: "100".
  - NoiseThres SC2: "+2".
  - NoiseHyst SC2: "+4".
- EFFECTS LEVEL
  - BMT CutOffFrq: "50Hz".
  - Incredible SND: "60%".
  - VDolby: "100%".

8.3.5 Smart Settings

No adjustments needed.

8.4 Option Settings

8.4.1 Introduction

The microprocessor communicates with a large number of I^2C ICs in the set. To ensure good communication and to make digital diagnosis possible, the microprocessor has to know which ICs to address. The presence / absence of these specific ICs (or functions) is made known by the option codes.

Notes:

- After changing the option(s), save them with the STORE command.
- All changes are disregarded when the OPTIONS submenu is left without using the STORE command.
- The new option setting is only active after the TV is switched "off" and "on" again with the Mains switch (the EAROM is then read again).

8.4.2 Changing Options

Options are used to control the presence / absence of certain features and hardware. There are two ways to change the option settings. All changes in the option settings are saved by selecting STORE and pressing the CURSOR RIGHT key. Some changes will only take affect after the set has been switched OFF and ON with the mains switch (cold start).

Changing Multiple Options by Changing Option Byte Values
Option Bytes (OB) makes it possible to set all options very fast. An option byte represents a number of different options. All options are controlled via option bytes (OB1 to OB13; each “OB” number represents 16 bits; bit numbers that are not used are omitted in the second column). Select an Option Byte you want to change with the CURSOR UP/DOWN keys, and key in the new value. See the table for more details. An explanation per option is listed in paragraph "Option Bit Definition".

Changing a Single Option
It is also possible to change an option one at a time. Therefore, select the option with the CURSOR UP/DOWN keys and change its setting with the LEFT/RIGHT keys.

8.4.3 Option Settings

In the table below, you will find the option settings.

Table 8-2 Option bit overview

Option Bytes (OB1... OB13)	Number of Bits	Decimal value	Name	Features	32PW8720/12	28PW8720/12	32PW8620/12	28PW8620/12	29PT8640/12	29PT8520/12	28PT7120/12	28PW8720/05	32PW8720/05	32PW8820/12	32PW8820/12	32PW8820/12	32PW8820/12
1	5	32	RCMX	RC for Teletext Mix Mode	0	0	0	0	0	0	0	0	0	0	0	0	0
	6	64	EQTO	Equalizer/Tone	0	0	0	0	0	0	0	0	0	0	0	0	0
	8	256	WSSB	Wide Screen Signal Bit	1	1	1	1	0	0	0	1	1	1	1	0	0
	12	4096	DGSC	Digital Scan	1	1	1	1	1	1	1	1	1	1	1	1	1
	14	16384	SSHT	Subtitle Shift	1	1	1	1	0	0	0	1	1	1	1	0	0
2	5	32	DBYV	Dolby Virtual	1	1	1	1	1	1	1	1	1	1	1	1	1
	7	128	SWOF	Swoofer** (1st bit)	0	0	0	0	0	0	0	0	0	0	0	0	0
	8	256	SWOF	Swoofer** (2nd bit)	0	0	0	0	0	0	0	0	0	0	0	0	0
	9	512	P50	P50	1	1	1	1	1	1	1	1	1	1	1	1	1
	11	2048	QPEAK	AV Sound Mode Detection	0	0	0	0	0	0	0	0	0	0	0	0	0
3	0	1	AV3	Side AV Source	1	1	1	1	1	1	1	1	1	1	1	1	1
	1	2	SCT3	Scart 3 Input	0	0	0	0	0	0	0	0	0	0	0	0	0
	8	256	ASPR	Aspect Ratio	1	1	1	1	0	0	0	1	1	1	1	0	0
	9	512	ROTI	Rotation Tilt	1	1	1	1	0	0	0	1	1	1	1	0	0
4	3	8	PITN	Philips tuner*** (1st bit)	1	1	1	1	1	1	1	1	1	1	1	1	1
	4	16	PITN	Philips tuner*** (2nd bit)	0	0	0	0	0	0	0	0	0	0	0	0	0
5	6	64	AAVL	Automatic Volume Leveller	1	1	1	1	1	1	1	1	1	1	1	1	1
6	12	4096	BASF	Bass Feature* (1st bit)	1	1	1	1	1	1	1	1	1	1	1	1	1
	13	8192	BASF	Bass Feature* (2nd bit)	0	0	0	0	0	0	0	0	0	0	0	0	0
8	4	16	PIPC	PIP control	0	0	0	0	0	0	0	0	0	1	1	1	1
	5	32	PIPT	PIP tuner	0	0	0	0	0	0	0	0	0	0	0	0	0
	6	64	W4X3	DW 4:3	0	0	0	0	0	0	0	0	0	1	1	1	1
	7	128	W169	DW 16:9	0	0	0	0	0	0	0	0	0	1	1	1	1
9	0	1	APC	Auto Picture Control (Auto TV)	1	1	1	1	1	1	1	1	1	1	1	1	1
	5	32	VMOD	Virgin Mode	0	0	0	0	0	0	0	1	1	0	0	0	0
	7	128	TIME	Timer	1	1	1	1	1	1	1	1	1	1	1	1	1
	8	256	DNR	Dynamic Noise Reduction	1	1	1	1	1	1	1	1	1	1	1	1	1
	9	512	BBD	Black Bar Detect	1	1	1	1	0	0	0	1	1	1	1	0	0
10	5	32	UKPNP	UK plug and play	0	0	0	0	0	0	0	1	1	0	0	0	0
	6	64	DTXT	Dual Text	1	1	1	1	0	0	0	1	1	1	1	0	0
	7	128	VTXT	Video Text	1	1	1	1	0	0	0	1	1	1	1	0	0
	8	256	SBNP	Auto Standby with no picture	1	1	1	1	1	1	1	1	1	1	1	1	1
	9	512	AUSB	Auto Standby Auto On	0	0	0	0	0	0	0	0	0	0	0	0	0
	10	1024	CZOM	Continuous Zoom	1	1	1	1	0	0	0	1	1	1	1	0	0
	11	2048	HSHT	Heading Shift	1	1	1	1	0	0	0	1	1	1	1	0	0
	13	8192	HOSP	Hospitality Mode	1	1	1	1	1	1	1	1	1	1	1	1	1
	14	16384	CHLK	Child Lock	1	1	1	1	1	1	1	1	1	1	1	1	1
11	3	8	SOSD	Smart OSD	0	0	0	0	0	0	0	0	0	0	0	0	0
	9	512	T1H0	100 Page Text	0	0	0	0	0	0	0	0	0	0	0	0	0
	13	8192	FAPG	Favorite page	1	1	1	1	1	1	1	1	1	1	1	1	1
	14	16384	ACI	Automatic Channel Installation	1	1	1	1	1	1	1	1	1	1	1	1	1
12	8	256	PLST	Program List	1	1	1	1	1	1	1	1	1	1	1	1	1
	12	4096	HPMN	Headphone Menu	1	1	1	1	1	1	1	1	1	1	1	1	1
13	0	1	T2H5	250 Page Text	0	0	0	0	0	0	0	0	0	0	0	0	0
	2	4	T12H	1200 Page Text	1	1	1	1	1	1	1	1	1	1	1	1	1
	7	128	SMCK	Smart clock	1	1	1	1	1	1	1	1	1	1	1	1	1
	8	256	ATS	Automatic Tuning System	1	1	1	1	1	1	1	1	1	1	1	1	1
	12	4096	SSD	SplitScreenDemo	1	1	1	1	1	1	1	1	1	1	1	1	1

8.4.4 Option Bit Definition

Sources

AV3: Side AV source.
Function: Disable/Enable side AV source.
Values: OFF= Disabled, side AV source is not available. ON= Enabled, side AV source is available.

SCT3: SCART 3 input.
Function: Disable/Enable Scart3 input.
Values: OFF= Disabled. ON= Enabled.

Video

ASPR: Aspect Ratio Setting.
Function: Select between 4 by 3 or 16 by 9 set.
Values: OFF= 4 by 3 set. ON= 16 by 9 set.

W4X3: Screen size 4x3.
Function: Disable/Enable Screen size 4x3.
Values: OFF= Disabled. Screen size 4x3 is not available. ON= Enabled. Screen size 4x3 is available.

W169: Screen size 16x9.
Function: Disable/Enable Screen size 16x9.
Values: OFF= Disabled. Screen size 16x9 is not available. ON= Enabled. Screen size 16x9 is available.

DNR: Dynamic Noise Reduction.
Function: Disable/Enable (Dynamic) Noise Reduction function.
Values: OFF=Disabled. ON= Enabled.

BBD: Black Bar Detection.
Function: Disable/Enable Black Bar Detection.
Values: OFF=Disabled, Black Bar Detection not available. ON= Enabled, Black Bar Detection available.
Note: The Auto Screen Fit will not be included in the picture size loop when BBD is OFF (WS = 1; 4 : 3 = 0).

CZOM: Continuous Zoom.
Function: Disable/Enable Continuous Zoom.
Values: OFF=Disabled. ON= Enabled (WS = 1; 4 : 3 = 0).

HSHT: Heading Shift.
Function: Disable/Enable Heading Shift.
Values: OFF=Disabled. ON= Enabled (WS = 1; 4 : 3 = 0).

SSHT: Subtitle Shift.
Function: Disable/Enable Subtitle Shift.
Values: OFF=Disabled. ON= Enabled (WS = 1; 4 : 3 = 0).

APC: Auto Picture Control (Auto TV).
Function: Disable/Enable Auto picture control.
Values: OFF= Disabled. ON= Enabled.

WSSB: Wide Screen Signalling Bit.
Function: Disable/Enable Wide screen Signalling bit function.
Values: OFF= Disabled. ON= Enabled (WS = 1; 4 : 3 = 0).

ROTI: Rotation Tilt.
Function: Change the tilt level of picture tube.
Values: OFF= Disabled, menu item ROTATION is not available. ON= Enabled, menu item ROTATION is available (WS = 1; 4 : 3 = 0).

DGSC: Digital Scan.
Function: Enable/Disable the Digital Scan in the DIGITAL OPT menu.
Values: OFF= Disabled, menu item DIG SCAN is not available. ON= Enabled, menu item DIG SCAN is available.

SSD: Split Screen Demo.
Function: Disable/Enable Split Screen Demo.
Values: OFF= Disabled. Split Screen Demo is not available. ON= Enabled. Split Screen Demo is available.

Audio

AAVL: Automatic Volume Level control.
Function: Disable/Enable automatic volume leveller function.
Values: OFF=Disabled, menu item AVL is not available. ON= Enabled, menu item AVL is available.

DBYV: Dolby Virtual.
Function: Select surround setting.
Values: OFF= Disabled, DOLBY VIRTUAL setting is not available. ON= Enabled, DOLBY VIRTUAL setting is available.
Note: Incredible surround & Dolby virtual are mutually exclusive.

EQTO: Equalizer or Tone control.
Function: Selection between Equalizer and Tone control (Bass and Treble).
Values: OFF= Tone control (Bass and Treble). ON= Equalizer.
Note: Equalizer and Tone (Bass and treble) control are mutually exclusive.

QPEAK: AV Sound Mode detection.
Function: The current Sound Mode detection in AV is not working correctly. The optimal threshold value for the correct sound mode detection is still being investigated. Therefore, this is needed to disable the Sound Mode detection in AV until the correct threshold is identified.
Value: OFF= Disabled, AV sound auto detection is not available. ON= Enabled. AV sound auto detection is available.

BASF: Bass Feature.
Function: Disable/Enable Bass Feature.
Values: OFF= Disabled. Bass Feature is not available. ON= Enabled. Bass Feature is available.
Note: For this feature, 2 bits are used: bit 5 and bit 4 of NVM address 21_{hex}. The following combinations are possible:
00 = Disable DBE and DUB;
01 = Enable DBE (bit 5 @ 21_{hex} = 0; bit 4 @ 21_{hex}= 1);
10 = Enable DUB (bit 5 @ 21_{hex}= 1; bit 4 @ 21_{hex}= 0);
11 = not used.

HPMN: Headphone menu.
Function: Disable/Enable Headphone menu.
Values: OFF= Disabled. Headphone menu is not available. ON= Enabled. Headphone menu is available.

SWOF: Subwoofer.
Function: Disable/Enable Subwoofer.
Values: OFF= Disabled. Subwoofer is not available. ON= Enabled. Subwoofer is available.
Note: For this feature, 2 bits are used: bit 1 of NVM address 19_{hex} and bit 7 of NVM address 18_{hex}. The following combinations are possible:
00 = None;
01 = Subwoofer (bit 1@19_{hex} = 0; bit 7@18_{hex} = 1);
10 = Woox (bit 1@19_{hex} = 1; bit 7@18_{hex} = 0);
11 = not used.

Tuning

PITN: Philips Tuner.
Function: Choose the tuner type that is configured in the hardware.
Values: OFF= Disabled, Other (non-Philips) tuner is used. ON= Enabled, Philips compatible tuner is used.
Note: For this feature, 2 bits are used: bit 4 and bit 3 of NVM address $1C_{hex}$. The following combinations are possible:
00 = Other tuner;
11 = Philips tuner (bit 4 and bit 3@ $1C_{hex}$ = 1).

Installation

ACI: Automatic Channel Installation.
Function: Disable/Enable automatic channel installation.
Values: OFF= Disabled Automatic Channel Installation. ON= Enabled Automatic Channel Installation.
Note: Download present program when ACI is ON.

ATS: Automatic Tuning System.
Function: Disable/Enable automatic tuning system.
Values: OFF= Disabled, automatic tuning system is ignored. ON= Enabled Automatic Tuning System, sort the program in an ascending order starting from Program 1.
Note: Sort the program in an ascending order starting from Program 1 when ATS is ON.

VMOD: Virgin Mode.
Function: Disable/Enable virgin mode.
Values: OFF= Disabled, cannot access virgin mode. ON= Enabled, can access virgin mode.
Note: Plug and Play menu item will be displayed to perform installation at the initial start up of the TV when MOD is ON and after installation is done, VMOD will be automatically set to OFF.

UKPNP: UK Plug and Play.
Function: Disable/Enable UK's default Plug and Play setting.
Values: OFF= Disabled, UK's default Plug and Play setting is not available. ON= Enabled, UK's default Plug and Play setting is available.
Note: When UKPNP and VMOD are ON at the initial set-up, LANGUAGE= ENGLISH, COUNTRY= GREAT BRITAIN and after auto store is complete, VMOD will be set automatically to OFF while UKPNP remain ON.

Program Selection
PLST: Program List.
Function: Disable/Enable Program List function.
Values: OFF= Disabled, the access to Program List Command is ignored. ON= Enabled, the access to Program List Command is processed.

Picture In Picture
PIPC: PIP Control.
Function: Disable/Enable submenu to adjust PIP Picture settings
Values: OFF= Disabled, PIP feature is not available. ON= Enabled, PIP feature is available
Note: PIP is present in FEATURES submenu when PIPC is ON. When PIPC is switched OFF, bits PIPT, W4X3, and W169 must be automatically set to OFF.

PIPT: PIP Tuner.
Function: To determine the presence of second tuner.
Values: OFF= Disabled, second tuner is not available. ON= Enabled, second tuner is available.
Note: When PIPC is switched OFF, bits PIPT, W4X3, and W169 must be automatically set to OFF.

Clock
SMCK: Smart Clock/Autochron.
Function: Disable/Enable smart clock/AutoChron function.
Values: OFF= Disabled, menu item smart clock function not available. ON= Enabled, menu item smart clock function available.
Note: For NAFTA, AUTOCHRON is present in INSTALL submenu when SMCK is ON. For AP-PAL and EUROPE, Smart clock downloaded from Teletext is enabled when SMCK is ON.

TIME: Timer.
Function: Disable/Enable menu item TIMER.
Values: OFF= Disabled, menu item TIMER not available. ON= Enabled, menu item TIMER available.
Note: TIMER submenu is present in FEATURES submenu when TIME is ON.

Data Service
DTXT: Dual Text.
Function: Disable/Enable Dual Text.
Values: OFF= Disabled. Dual text is not available. ON= Enabled. Dual text is available (WS = 1; 4 : 3 = 0).

RCMX: RC for Teletext Mix Mode.
Function: Disable/Enable RC for Teletext Mix mode support.
Values: OFF= Disabled. RC for mix mode is not available. ON= Enabled, RC for mix mode is available.

FAPG: Favourite Page.
Function: Disable/Enable favourite page in Teletext mode.
Values: OFF= Disabled favourite page in Teletext mode. ON= Enabled favourite page in Teletext mode.

T1H0: 100-Page Text.
Function: Disable/Enable 100-page Text.
Values: OFF= Disabled. 100-page text is not available. ON= Enabled, 100-page text is available.

T2H5: 250-Page Text.
Function: Disable/Enable 250-page Text.
Values: OFF= Disabled. 250-page text is not available. ON= Enabled, 250-page text is available.

T12H: 1200-Page Text.
Function: Disable/Enable 1200-page Text.
Values: OFF= Disabled. 1200-page text is not available. ON= Enabled, 1200-page text is available.

VTXT: Video Text.
Function: Disable/Enable Video Text.
Values: OFF= Disabled. Video text is not available. ON= Enabled. Video text is available (WS = 1; 4 : 3 = 0).

Lock Features
CHLK: Child Lock.
Function: Disable / Enabled function to block/unblock channels.
Values: OFF= Disabled. ON= Enabled.

OSD/Menu Related
SOSD: Smart OSD.
Function: Disable/Enable full display of SMART SOUND and SMART PICTURE OSD.
Values: OFF= Disabled, full display of SMART SOUND and SMART PICTURE OSD not available. ON= Enabled, full display of SMART SOUND and SMART PICTURE OSD available.

Miscellaneous
HOSP: Hospitality mode.
Function: Disable/Enable Hospitality mode.
Values: OFF= Disabled. Hospitality mode is not available. ON= Enabled. Hospitality mode is available.

SBNP: Auto Standby with No Picture.
Function: Disable/Enable automatic switch to standby after 15 minutes when no ident.
Values: OFF= Disabled, no automatic switch to standby. ON= Enabled, set switches to standby after 15 minutes when no ident.

AUSB: Auto Standby Auto On.
Function: Disable/Enable automatic switch to standby if no RC or local keyboard response after 4 hours provided that the set is ON from standby mode by the timer.
Values: OFF= Disabled, no automatic switch to standby. ON= Enabled, set switches to standby after 4 hours.

P50: P50 (Easylink).
Function: Disable/Enable P50 feature.
Values: OFF= Disabled, P50 feature not available. ON= Enabled, P50 feature is available.

9. Circuit Descriptions, Abbreviation List, and IC Data Sheets

Index of this chapter:

Note: Only **new** circuits (circuits that have not been published recently) are described. For the other circuits, see the A02E manual.

9.1 Introduction

The ES1E is a flat screen type CRT TV set for the year 2005 - 2006. It is based on the SSB of the A02, but the LSP, called Esplanade, has been redesigned in order to reduce the “hot” part of the chassis. In this chapter, only the deflection circuits, the correction circuits and the X-ray protection circuits are described.

9.1.1 Large Signal Panel

The Esplanade chassis has a full sized LSP, which is has been redesigned with respect to the previous A02 chassis in order to reduce the “hot” parts of the circuit.

The main functionalities of the LSP are:
- Supply,
- Deflection,
- Sound amplification.

The LSP (single sided) is built up very conventional, with hardly any surface mounted components on the copper side.

9.2 Deflection

Deflection Principle Diagram ES1E



Figure 9-1 Deflection Principle

9.2.1 Basic Description.

T0 - T1

Deflection T0-T1



Figure 9-2 Deflection T0 - T1

At switch on of the TV set Scap (2417/2418) is charged by Vbatt. At T0 line transistor 7405 starts conducting. Now the current flows as shown in figure (T0 - T1), as a result of which the horizontal deflection will bend the electron beam from the centre of the screen to the right. Note that the deflection current has an almost linear waveform.

T1 - T2

Deflection T1-T2



Figure 9-3 Deflection T1 - T2

At T1 line transistor 7405 is switched off and the line fly-back starts. When the line transistor stops conducting, the line current is at its maximum level. The current charges fly-back capacitors 2412 and 2413, and also capacitor 2414. This causes a decrease of line current. (Note that this current has a half-cosine waveform). The deflection position (i.e. the electron beam) is in the middle of the screen now.

T2 - T3

Deflection T2-T3



Figure 9-4 Deflection T2 - T3

At T2 the deflection current is 0 Amp. The fly-back capacitor (2412/2413/2414) is charged to approximately 1200 V and will discharge now. As a result of this, the deflection current will bend the electron beam to the left of the screen.

T3 - T4

Deflection T3-T4



Figure 9-5 Deflection T3 - T4

When the fly-back capacitor (2412/2413/2414) is discharged, the current is at its maximum negative level. This maximum negative current will then charge the fly-back capacitor (2412/2413/2414) with a negative voltage. At this moment, fly-back diode 6404 will start conducting. The voltage at Scap 2418 causes a linear current flow from T3 - T4. This causes a deflection current which bends the electron beam back from the left to the centre of the screen.

9.2.2 Standby and Start Up

In Standby mode, both +5V and Vbatt are not available in order to meet the standby power saving requirement.

During the start-up phase, +5V is switched on by STANDBY via 7548/7547/7545 and Vbatt is switched on by STANDBY via 7573.

After this, Hdrive is output from the SSB to driver 7404 (see circuit diagram A2), and consequently to the deflection output stage (7405). During the slow start-up phase, the Hdrive duty cycle gradually increases from small to normal. At the

beginning of the start-up phase, the driver receives its +5V supply via 3421 and 6465 (see circuit diagram A2). During the slow start-up phase, the LOT 5450 pin9 voltage gradually increases, and finally takes over the supply of the +5V voltage, to supply 5402/7404 via 6403/3493/3451/3419/3432/3415/3414.

At the end of the slow start-up phase, the deflection stage is operating at its normal operating condition and all the voltages are stabilized. Then, the +13V volt supply has fully replaced the +5V supply to power the horizontal output stage.

At that moment, not only the horizontal deflection, but also the vertical deflection is functioning at its normal operating conditions.

9.2.3 Normal Operation and Horizontal Deflection

In normal operation mode, the Hdrive with its 45/55 duty cycle is switching on and off 7404 (see circuit diagram A2). The driver stage is working in flyback mode: When 7404 is on, 5402 retains its flux energy and also switches off 7405 via its secondary coil during flyback mode. When 7404 is switched off, 5402 releases its energy and turns on 7405. By means of the on-off switching process, a sawtooth yoke deflection current is generated.

There are various circuits that are part of the horizontal deflection circuit.
These will be discussed below:

Horizontal Output Stage:
This a standard circuit (see circuit diagram A2), in which the main horizontal output stage consists of driver 7404/5402, line output transistor 7405, tuning capacitor 2411/2414, Scap 2417/2418 and diode modulator 6404/2413/2416.

Anti-Curtain Effect (Anti-Beta Ringing) Circuit:
5410/2427/3433 (see circuit diagram A2) are the anti-beta ringing circuit that is tuned to and suppresses the parasitic ringing frequencies normally occurring in Slot type LOTs to an acceptable level. For Layer type LOTs, these components are not required and 9410 is the jumper alternative for Layer type LOTs.

Beta Ringing, if not suppressed, will cause a type of interference which is visible as a curtain effect at the left edge of the screen. This interference is caused by the high amplitude ringing energy being coupled magnetically or via an electrically conducting path from the LOT to the small signal circuit. If the ringing is suppressed to a specific level, the interference will not be visible anymore.

DAF Circuit:
5455/2402/2403/2405/2406 (see circuit diagram A2) are the DAF circuit that will be used in DAF or double focus CRT tubes. For single focus tubes, these components are not required; 9411 is the jumper alternative for non-DAF tubes.

The DAF circuit is used to improve the dynamic focusing of the tube, particularly in the edge areas. The DC high voltage of constant level which is supplied to the focus electrode is referred to as static focus or single focus. In addition to that, an AC parabolic waveform (derived from the vertical and/or the horizontal deflection voltages) can be superimposed onto the DC static focus voltage; this extra AC focusing voltage will then correct the focus dynamically, corresponding to the scan position at that particular moment. This is what we refer to as DAF (Dynamic Astigmatism and Focusing; a method to keep the electron spot round and focused during the whole scan).

Transformer 5455 takes the horizontal deflection current as its input and transfers its energy to the capacitor (2402/2403/2405/2406) on its secondary side. The current in the secondary coil of the transformer charges the capacitor and this results in a parabolic waveform. The parabolic waveform is fed to connector 1402 of the LOT focus cable and is coupled via an internal 500 pF capacitor inside the LOT and superimposed onto the static focus voltage.

2nd order S-correction circuit:
5406/2407/3403 (see circuit diagram A2) are the 2nd order S-correction circuit, which is used mainly in large wide screen tubes, because they are prone to scanning imperfections that need 2nd order S-correction. For 4x3 tubes or relatively small wide screen tubes, these components are not required, and then 9401 is the jumper alternative for them.

Due to the relatively wide angle of large wide screen flat tubes, the inner tube surface (which is flat) and the surface scanned by the electron beam (which is spherical) are very far apart, especially at the edges. This is because both areas are nowhere parallel with respect to each other (as they ideally would have to be). The larger and wider the screen size is, the more visible the unwanted phenomenon resulting from this optical misalignment will be. The phenomenon manifests itself, because the horizontal scanning will be wider at the 1/4 and 3/4 position, but narrower at the centre and edge position. Note that this is different from S-correction (correct centre-versus-edge scanning) and Linearity Correction (correct left-versus-right scanning).

To carry out the 2nd order S-correction, transformer 5406 takes the horizontal deflection current as its input and transfers it to capacitor 2407 on its secondary side. Together with the yoke coil, capacitor 2407 forms a tuning circuit, and this circuit modifies the yoke current during the 1/4 and 3/4 scanning position. In this way, the modified yoke currect compensates the imperfections that are caused by the CRT geometry.

The function of resistor 3403 is to prevent the secondary circuit from floating. It pulls DC components of the correction voltages to gnd.

Dynamic S-correction Circuit (Inner-Pincushion):
5408/5409/2419 (see circuit diagram A2) form the dynamic S-correction circuit, which is mainly used in relatively large wide screen tubes. This is, because they are prone to optical inner pincushion distortions. For 4x3 tubes or relatively small wide screen tubes, these components are not required; in that case, 9412 is the jumper alternative for them.

As has been explained earlier, due to the relatively wide angle of large wide screen flat tubes, the inner tube surface (flat) and the scanning surface (spherical) can never be perfectly parallel to each other, so optical distortions will be the result, especially at the edges of the screen. The first imperfection that will become visible is the phenomenon called pin-cushion distortion; this can be corrected by the East West circuit for distortions in the proportions of the top/bottom versus centre area (distortions in the proportions in the vertical direction have to be corrected as well, see further down in this text).

Additionally, the larger and wider the screen size becomes, the more clearly a second unwanted phenomenon will become visible, called inner pincushion distortion. This happens because, when two corresponding horizontal scanning lines are compared, the top one and the centre one will have different centre-versus-edge scanning length ratios (when the vertical line at the edge of the screen has been corrected by the East West circuit, the vertical lines at the 1/4 and 3/4 positions will still be concave. Note that this phenomenon is different from 2nd-order S-distortion.)

To correct the dynamic S-distortion, the East West correction circuit has to generate a deflection current which is higher at the centre scanning position of the screen than at the top/bottom positions. With the Bridge coil 5408/5409, this higher

extra current generates a parabolic waveform across 2419 at the centre scanning position. The parabolic waveform is superimposed (series-added) onto the S-cap voltage (2417/2418); in this way, a more parabolic waveform is obtained which corrects the inner pincushion distortion.

East West correction Circuit:
Together with diode modulator 2413/2416/6404, components 6471/7406/3425/2425 form the main East-West correction circuit. The circuit is a current drive circuit driven by MOSFET 7406. 3425 and 2425 function as a simple RC filter with the task of filtering the horizontal pulses in the diode modulator stage. The parabolic current source for the EW-drive comes from the SSB and modulates the diode modulator voltage by means of 7406. Because 7406 is in series with Scap 2417/2418), the diode modulator voltage plus the Scap voltage are always equal to Vbatt. So, by modulating the diode modulator voltage, we are able to modulate the Scap voltage, and so the deflection current and scanning width as well.

EHT-info Compensation:
In addition to the EHT-info compensation feedback to the SSB IC, components 3422/3423/6424/3424/3435/6425/3437/2437/2422 are the EHT-info compensation circuit that injects beam information into the East-West correction circuit to achieve better compensation.

Waveform "EHT-info" is a voltage source which is derived from Ibeam; the voltage is injected via the EHT-info compensation circuit mentioned above, and modulates the East West circuit.

Beam Current and Horizontal Flyback:
The beam current is determined by 3480/3491/3453/3492/6478 (see circuit diagram A2), while 2450/2451 filters out the high frequency info.

The horizontal flyback circuit is provided with an X-ray protection function; for this reason the combined circuit bears the name Hfb_Xray_Prot. Hfb is derived from the heater pulses via 2477 and 2476 and clamped by 3477/6474. The protection is realized by 7486. The SSB monitors the Hfb_Xray_Prot voltage and will go into protection mode if this voltage is low without pulses.

9.2.4 Vertical Deflection

IC 7455 (see circuit diagram A2) is the differential vertical deflection amplifier. The amplification gain is determined only by 3461/3476 and 3470/3471/3472. The SSB IC output is a differential vertical current source to 7455 and its signal is amplified and output as a vertical deflection current through the vertical yoke coil.

IC 7455 has a separate flyback supply (on its VFB pin) which is tapped from the positive portion of the heater voltage. The flyback heater voltage charges 2461 via 6476/3487 and is clamped by 6458.

The vertical scanning voltage (on pin V-OUT of 7455) varies between +13V and -14V.

Components 3466/2468 are for pole-zero compensation purposes and suppress oscillation tendencies.

Components 3467/3468 suppress horizontal coupling, and also suppress noise.

Components 3459/6459 are part of the circuit which protects the CRT tube from burning in, in case someone accidentally unplugs the vertical yoke or disconnects the power supply of 7455. Without this protection, the picture tube neck may be damaged if the vertical scanning circuit is not working and all the beam energy is concentrated on one spot of the CRT neck.

The function of diode 6457 is to isolate the small signal supply from the flyback supply boost up voltages.

9.2.5 Protection

The protections are realized by 7407/7456/7486. All the protection voltages coming from the various protection circuits like: the vertical protection (3459/6459), the bridge coil protection (5411/6405/3479), the X-ray protection (6480/7408/3460/3462/3465/3469) and the East West protection (7403/3473/3488/3417/2495) are combined in 7407/7456/7586.

If a protection circuit is triggered, the protection triggering voltage will turn on 7407 and consequently 7486, which will pull the Hfb-Xray_Prot voltage low. The SSB will respond to this triggering signal and will shut down the deflection circuit

9.3 Software Upgrading

In this chassis, you can **upgrade** the software via ComPair. This offers the possibility, to replace the entire SW image without having to remove the flash-RAM from its socket. You can find more information on how this procedure works in the ComPair file. It is possible that not all sets are equipped with the hardware, needed to make software upgrading possible. To speed up the programming process, the firmware of the ComPair interface can be upgraded. See Chapter "Service Modes ..."; paragraph "ComPair" - “How To Order” for the order number.

9.4 Abbreviation List

0/6/12	SCART switch control signal on A/V board. 0 = loop through (AUX to TV), 6 = play 16:9 format, 12 = play 4:3 format
2CS	2 Carrier Sound
A2	Commonly known as 2 Carrier Sound (2CS) system
AC	Alternating Current
ACI	Automatic Channel Installation: algorithm that installs TV channels directly from a cable network by means of a predefined TXT page
ADC	Analogue to Digital Converter
ADOC	Analogue Digital One Chip
AFC	Automatic Frequency Control: control signal used to tune to the correct frequency
AGC	Automatic Gain Control: algorithm that controls the video input of the feature box
AM	Amplitude Modulation
ANC	Automatic Noise Reduction; One of the algorithms of Auto TV
AP	Asia Pacific
AR	Aspect Ratio: 4 by 3 or 16 by 9
ASD	Automatic Standard Detection
AUDIO-SL	Audio Surround Left
AV	Audio Video
AVL	Automatic Volume Level control
B-SC1-IN	Blue SCART1 in
B-SC2-IN	Blue SCART2 in
B-TXT	Blue teletext
B/G	Monochrome TV system. Sound carrier distance is 5.5 MHz
BBD	Black Bar Detection
BCL	Beam Current Limiter
BC-PROT	PROTection signal to the microprocessor in case of a too high Beam Current.
BLC-INFO	BLack Current INFO.
BLD	BLack Level Detection.
BS	BLack Stretch.
BTSC	Broadcast Television Standard Committee; Multiplex FM stereo sound system, originating from the USA and used e.g. in LATAM and AP-NTSC countries.
C	Centre channel (audio) or Chroma; The NTSC/PAL/SECAM video signal contains two parts that make up what we see on the display; the luminance (or intensity) part and the colour (or chroma) part
CBA	Circuit Board Assembly (or PWB)
CL	Constant Level: audio output to connect with an external amplifier
CLUT	Colour Look Up Table
ComPair	Computer aided rePair
CRT	Cathode Ray Tube (or picture tube)
CSM	Customer Service Mode
CTI	Colour Transient Improvement; Manipulation of the steepness of the chroma transients
CVBS	Composite Video Blanking and Synchronisation
CVBS-EXT	CVBS signal from external source (VCR, VCD, etc.)
CVBS-INT	CVBS signal from Tuner
CVBS-MON	CVBS monitor signal
CVBS-TER-OUT	CVBS terrestrial out
CVI	Component Video Input
D/K	Monochrome TV system. Sound carrier distance is 6.5 MHz. D= VHF-band, K= UHF-band
DAC	Digital to Analogue Converter
DAF	Dynamic Astigmatism and Focusing; a method to keep the electron spot round and focused during the whole scan
DBE	Dynamic Bass Enhancement; extra low frequency amplification
DC	Direct Current
DCC	Dynamic Contrast Control
DC-filament	Filament supply voltage
DEGAUSS	Control line. Logic LOW to enable CRT degaussing. Logic HIGH to disable the CRT degaussing.
DFU	Directions For Use: owner's manual
DNR	Digital Noise Reduction; Noise reduction feature of the set / Dynamic Noise Reduction
DNR	Digital Noise Reduction; Noise reduction feature of the set / Dynamic Noise Reduction
DOP	Digital Output Processor (Part of ADOC which takes care of RGB control and deflection)
DPL	Dolby Pro Logic
DPL	Dolby Pro Logic
DRAM	Dynamic RAM; dynamically refreshed RAM
DRAM	Dynamic RAM; dynamically refreshed RAM
DS	Digital Scan
DSP	Digital Signal Processing
DST	Dealer Service Tool; Special remote control designed for dealers to enter e.g. service mode (a DST-emulator is available in ComPair)
DTS	Digital Theatre Sound
DVD	Digital Versatile Disc
DVI(-d)(-i)	Digital Visual Interface (d= digital only) (i= integrated); A digital video interface to a display, designed to replace the analogue YPbPr or RGB interface
DW	Double Window
DYN-FASE-COR	Dynamic phase correction, to correct the phase of the H-drive
EEPROM	Electrically Erasable and Programmable Read Only Memory
EHT	Extreme High Tension; the voltage between the cathode and the shadow mask that accelerates the electrons towards the screen (around 25 kV)
EHT-INFO	Extra High Tension INFOrmation, used for contrast reduction, vertical and horizontal amplitude correction, beam current protection, and flash detection
EMI	Electro Magnetic Interference; Leakage of high-frequency radiation from a transmission medium
EPG	Electronic Program Guide; System used by broadcasters to transmit TV guide information (= NexTView)
EPLD	Erasable Programmable Logic Device
EU	EUrope
EW	East West, related to horizontal deflection of the set
EW-DRIVE	East -West correction drive signal.
EXT	EXTernal (source), entering the set by SCART or by cinches (jacks)
FBL	Fast Blanking: DC signal accompanying RGB signals
FBL-SC1-IN	Fast blanking signal for SCART1 in
FBL-SC2-IN	Fast blanking signal for SCART2 in

FBL-TXT	Fast Blanking Teletext
FBX	Feature BoX; Part of the small signal board /separate module which contains 100 Hz processing, extra features and AutoTV algorithms (FBX6= based on PICNIC, FBX7= based on PICNIC and Eagle, FBX8= based on PICNIC, Eagle, and Columbus)
FE	Front End; Tuner and RF part together
FLASH	FLASH memory
Field	Each interlaced broadcast FRAME is composed of two Fields, each Field consists of either Odd or Even lines
Filament	Filament of CRT
FLASH	FLASH memory
FM	Field Memory / Frequency Modulation
FM-Radio	Radio receiver that can receive the FM Band 87.5 - 108 MHz
FMR	FM Radio
Frame	A complete TV picture comprising all lines (625/525)
FRAMEDRIVE -	Differential frame (vertical) drive signal (negative)
FRAMEDRIVE +	Differential frame (vertical) drive signal (positive)
FRC	Frame Rate Converter
FRONT-C	Front input chrominance (SVHS)
FRONT-DETECT	Control line for detection of headphone insertion, Service Mode jumper, power failure detection
FRONT-Y_CVBS	Front input luminance or CVBS (SVHS)
FTV	Flat TeleVision
G	Green
G-SC1-IN	Green SCART1 in
G-SC2-IN	Green SCART2 in
G-TXT	Green teletext
Gb/s	Giga bits per second
H	H_sync to the module
H-2FH	Horizontal sync input for the 2fH source
H-A50	Horizontal Acquisition 1fH: horizontal sync pulse coming out of the HIP
H-D100	Horizontal Drive 2fH; Horizontal sync pulse coming out of the Feature Box
H-DRIVE	Horizontal Drive
H-FLYBACK	Horizontal Flyback
H-OUT	H_sync output of the module / Horizontal Output pulse
HA	Horizontal Acquisition; horizontal sync pulse
HD	High Definition: 720p, 1080i, 1080p
HDMI	High Definition Multimedia Interface, digital audio and video interface
HEADPHONE-L	Stereo headphone (Left) signal output.
HEADPHONE-R	Stereo headphone (Right) signal output.
HFB	Horizontal Flyback Pulse; Horizontal sync pulse from large signal deflection
HP	Head Phone
HW	Hardware
I	Monochrome TV system. Sound carrier distance is 6.0 MHz. VHF- and UHF-band
I^2C	Inter IC bus (also called IIC)
I^2S	Inter IC Sound bus
IC	Integrated Circuit
IDRIVE-	Vertical drive -
IDRIVE+	Vertical drive +
IF	Intermediate Frequency
IF-TER	IF signal from main tuner
IIC	Inter IC bus (also called I2C)
Interlaced	Scan mode where two fields are used to form one frame. Each field contains half the number of the total amount of lines. The fields are written in "pairs", causing line flicker.
IO	In/Out
IR	Infra Red
IROM	Internal ROM (inside the microcontroller)
IRQ	Interrupt ReQuest
ITV	Institutional TV
JTAG	Joint Test Action Group; Definition for a standardised serial test interface
KEYB	Front panel keyboard
KEYBOARD	Input line. Carries the voltage value of the corresponding tact switch on TOP-control or FRONT-control keypad
L	Left audio channel
L/L'	Monochrome TV system. Sound carrier distance is 6.5 MHz. L' is Band I, L is all bands except for Band I
Last Status	The settings last chosen by the customer and read and stored in RAM or in the NVM. They are called at start-up of the set to configure it according to the customer's preferences
LATAM	LATin AMerica
LCD	Liquid Crystal Display
L-CL_VLOUT	REAR CINCH stereo output
LED	Light Emitting Diode
LFE	Low Frequency Enhancement audio channel
L-FRONT-IN	EXT3 stereo input
LIGHT-SENSOR	Ambient light intensity signal.
LINE DRIVE	Horizontal (line) deflection drive signal (for the Line transistor)
LNA	Low Noise Adapter / Low Noise Amplifier
LOT	Line Output Transformer (also called FBT); The transformer in which the EHT is generated
LS	Loud Speaker
Ls, Rs	Left surround and Right surround channel (audio)
LSP	Large Signal Panel
Lt, Rt	Left total and Right total in case of a Dolby ProLogic encoded signal (audio)
LTI	Luminance Transient Improvement
LTP	Luminance Transient Processor
LUT	Look Up Table
LVDS	Low Voltage Differential Signalling, data transmission system for high speed and low EMI communication.
M/N	Monochrome TV system. Sound carrier distance is 4.5 MHz. M= 525 lines @ 60 Hz, N= 625 lines @ 50 Hz
Mb/s / Mbps	Mega bits per second
MCS	Multi Channel Sound: refers to Dolby Pro Logic Surround in ES1E ADOC
MDO	Mode control data output
MIPS	Microprocessor without Interlocked Pipeline-Stages; A RISC-based microprocessor
Mips	Million instructions per second
MMI	Multi Media Interface
MOSFET	Metal Oxide Semiconductor Field Effect Transistor
MPEG	Motion Pictures Experts Group
MPIF	Multi Platform InterFace (Part of Salsa chipset, sister-chip of ADOC IC)
MPIP	Multi Picture in Picture; Commercial feature showing several frozen or moving pips
MPX	MultiPleX
MSP	Multi-standard Sound Processor: ITT sound decoder

MUTE	MUTE Line
NAFTA	North American Free Trade Association: Trade agreement between Canada, USA and Mexico
NC	Not Connected
NDF	No vertical Deflection; Vertical fly back protection
NHF	No Horizontal deflection; Horizontal fly back protection
NICAM	Near Instantaneously Companded Audio Multiplexing; This is a digital sound system, mainly used in Europe
NTC	Negative Temperature Coefficient, non-linear resistor (resistance decreases if temperature increases)
NTSC	National Television Standard Committee. Colour system used mainly in North America and Japan. Colour carrier NTSC M/N = 3.579545 MHz, NTSC 4.43 = 4.433619 MHz (this is a VCR norm, it is not transmitted off-air)
NVM	Non Volatile Memory; IC containing data such as alignment values, preset stations
O/C	Open Circuit
OB	Option Byte
OC	Open Circuit
ON/OFF LED	On/Off control signal for the LED
ON/STBY	On/Standby
ON-OFF-LED	Active-LOW control line. Logic LOW = red LED "on", HIGH = red LED "off"
OP	Option Byte
OSD	On Screen Display
P50	Project 50; Communication protocol between TV and peripherals
PAL	Phase Alternating Line; Colour system mainly used in West Europe (colour carrier= 4.433619 MHz) and South America (colour carrier PAL M= 3.575612 MHz and PAL N= 3.582056 MHz)
PC	Personal Computer
PCB	Printed Circuit Board (or PWB)
PCM	Pulse Code Modulation
PILOT	Pilot Signal
PIG	Picture In Graphic
PIP	Picture In Picture
PLL	Phase Locked Loop; Used for e.g. FST tuning systems. The customer can directly provide the desired frequency
POR	Power On Reset; Signal to reset the µP
POR-FLASH	Signal that informs the micro controller (painter) that set will switch "off"
Progressive Scan	Scan mode where all scan lines are displayed in one frame at the same time, creating a double vertical resolution.
PTC	Positive Temperature Coefficient, non linear resistor (resistance increases if temperature increases)
PTP	Picture Tube Panel
PWB	Printed Wiring Board (also called PCB or CBA)
PWM	Pulse Width Modulation
QSS	Quasi Split Sound
R	Right audio channel / Red
RAM	Random Access Memory
RC	Remote Control transmitter
RC5 (6)	Remote Control system 5 (6), the signal from the remote control receiver
RDS	Radio Data System (European); This is an MPX signal carried in FM radio channels (87.5 … 108 MHz)
RESET	RESET signal
RF	Real Flat (picture tube) or Radio Frequency
RGB	Red, Green, and Blue colour space; The primary colour signals for TV. By mixing levels of R, G, and B, all colours (Y/C) are reproduced
RGBHV	Red, Green, Blue, Horizontal sync, and Vertical sync
RISC	Reduced Instruction Set Computer; A processor architecture based on ultra-high speed processing technology that uses a far simpler set of operating commands than a normal microprocessor does
RMS	Root Mean Square value
ROM	Read Only Memory
S	Surround channel or mono surround channel (audio)
SALSA	System Application for Low Segment of Analogue TV
SAM	Service Alignment Mode
SAP	Secondary Audio Program; Generally used to transmit audio in a second language
SAW	Surface Acoustic Wave
SC	SandCastle: two-level pulse derived from sync signals
SCART	Syndicat des Constructeurs d'Appareils Radiorécepteurs et Téléviseurs; This is a 21-pin connector used in EU, that carries various audio, video, and control signals (it is also called Péritel connector)
SCAVEM	Scan Velocity Modulation; Advanced beam control technology, which results in sharper edges on all images for outstanding clarity
SC1-OUT	SCART output of the MSP audio IC
SC2-B-IN	SCART2 Blue in
SC2-C-IN	SCART2 chrominance in
SC2-OUT	SCART output of the MSP audio IC
S/C	Short Circuit
SCL	Serial Clock signal on I^2C bus
SCL-F	Serial CLock signal on Fast I^2C bus
SD	Standard Definition
SDA	Serial Data line of I^2C bus
SDA-F	Data Signal on Fast I^2C bus
SDM	Service Default Mode
SDAM	Service Default / Alignment Mode
SDRAM	Synchronous DRAM
SECAM	SÉquence Couleur Avec Mémoire; Colour system mainly used in France and East Europe. The chroma is FM modulated and the R-Y and B-Y signals are transmitted line sequentially. Colour carriers= 4.406250 MHz and 4.250000 MHz
SEL-SVHS-RR-STATUS2	SVHS Selection Signal
SIF	Sound Intermediate Frequency
SIMM	Single In-line Memory Module; 80-fold connector between LSP and SSB
SL	Single In-line Memory Module; 80-fold connector between LSP and SSB
SLDP	Smart Local Dooming Prevention (HW and SW)
SMC	Surface Mounted Component
SMPS	Switched Mode Power Supply
SND	SouND
SNDL-SC1-IN	Sound left SCART1 in
SNDL-SC1-OUT	Sound left SCART1 out

SNDL-SC2-IN	Sound left SCART2 in
SNDL-SC2-OUT	Sound left SCART2 out
SNDR-SC1-IN	Sound right SCART1 in
SNDR-SC1-OUT	Sound right SCART1 out
SNDR-SC2-IN	Sound right SCART2 out
SNDR-SC2-OUT	Sound right SCART2 out
SNDS-VL-OUT	Surround sound left variable level out
SNDS-VR-OUT	Surround sound right variable level out
SNERT	Synchronous No parity Eight bit Reception and Transmission
SOG	Sync On Green
SOPS	Self Oscillating Power Supply
SOUND-ENABLE	Control line to do hardware mute or un-mute of loudspeakers.
SRAM	Static RAM
SRAM	Static RAM
SS	Small Screen
ST-BY	STandBY
STANDBY (POR)	Signal coming from Main Supply informing the supply is switching "off"
STATUS	Status signal from pin 8 of SCART connector
STBY	STandBY
SVHS	Super Video Home System
SW	Software or Subwoofer or Switch
TBD	To Be Defined
THD	Total Harmonic Distortion
TILT	PWM Output signal (variable DC level) to control the picture tilt from the DOP block of the ADOC.
TXT	Teletext; TXT is a digital addition to analogue TV signals that contain textual and graphical information (25 rows x 40 columns). The information is transmitted within the first 25 lines during the Vertical Blank Interval (VBI)
TXT-SW	Teletext switch
U-100	U signal 1fH (after Feature Box)
UART	Universal Asynchronous Receiver Transmitter
UBE	Ultra Bass Enhancement
µC	Microcontroller
UI	User Interface
UOC	Ultimate One Chip
µP	Microprocessor
UV	Colour difference signals
V	V_sync
V-100	V_sync from Feature Box (2fH)
V-2FH	Vertical sync input for the 2fH source.
VA50	Vertical Acquisition 1fH
V-AMP	Vertical Amplitude DAC output
V-BAT	Main supply for deflection (usually 141 V)
VD-100	Vertical Drive 2fH; vertical sync pulse from deflection
VD-NEG	One of the symmetrical drive signals for the DC frame output stage.
VD-POS	One of the symmetrical drive signals for the DC frame output stage
V-OSD	Vertical sync OSD
VA	Vertical Acquisition
VBI	Vertical Blanking Interval; Time during which the video signal is blanked when going from bottom to top of the display
V-chip	Violence chip. Adds content filtering capabilities to NTSC video
VCR	Video Cassette Recorder
VD	Vertical Drive; Vertical sync pulse coming from the Feature Box
VDS	Virtual Dolby Surround
VERT	Vertical Output pulse
VESA	Video Electronics Standards Association
VGA	Video Graphics Array
VGND	Video ground
VGUARD	Vertical guard voltage
VIF	Video Intermediate Frequency
VL	Variable Level out; Processed audio output towards external amplifier
VOL (+/-)	Volume (+/-)
V-SYNC-VGA	V_sync on VGA connector
WD	Watch Dog
WE	Write Enable control line
WS	Wide Screen; Screens with an aspect ratio of 16:9
WSS	Wide Screen Signalling; Used by broadcasters to transmit e.g. PALPLUS and 16:9 Aspect Ratio
WST	World System Teletext
WXGA	1280x768 (15:9) or 1366x768 (16:9)
WYSIWYR	What You See Is What You Record: record selection that follows main picture and sound
XGA	Extended Graphics Array; 1024x768 (4:3)
XTAL	Quartz crystal
Y	Luminance signal
YPbPr	Component video (Y= Luminance, Pb/Pr= Colour difference signals B-Y and R-Y, other amplitudes w.r.t. to YUV)
Y/C	Y consists of luminance signal, blanking level and sync; C consists of chroma (colour) signal
Y-OUT	Luminance-signal
YUV	Colour space used by the NTSC and PAL video systems. Y is the luminance and U/V are the colour difference signals

9.5 IC Data Sheets

This section shows the internal block diagrams and pin layouts of ICs that are drawn as "black boxes" in the electrical diagrams (with the exception of "memory" and "logic" ICs). This is not applicable to this manual.

10. Spare Parts List

Set Level

Various

0158	3104 311 02021	Cable 3p/1000/3pp
1099▲	4822 131 11046	CRT A66EAK175X44/L
1099▲	4822 131 11307	CRT A66EAK175X54/L
1099▲	9301 934 30307	CRT W66ERF112X044
1099▲	9301 966 60314	CRT A68ERF182X044/M
1099▲	9301 967 10307	CRT W66ERF172X044
1099▲	9301 982 90314	CRT W76ERF182X044
1111	4822 242 82104	Bead 100MHz
8911	3104 328 19311	Cable + Ferrite Assy

—∿—

5203	2422 549 00128	Coil Degaus 32WR DC-1362A
5203	2422 549 00129	Coil Degaus 28WS DC-1373A
5203▲	2422 549 00132	Coil Degaus 28"/29"WR DC-1398
5205	3104 308 20961	Coil canceller
5213	2422 264 00485	Loudsp. 8Ω 15W FR
5213	2422 264 00491	Loudsp. 8Ω 10W FR
5214	2422 264 00485	Loudsp. 8Ω 15W FR
5214	2422 264 00491	Loudsp. 8Ω 10W FR

Large Signal Panel [A]

Various

1050	3139 188 69401	MC-29PT8500/12-EU
1232	3139 147 20911	Tuner UV1316E/A I-4
1241	4822 267 10748	Connector 3p
1401	4822 265 41113	Connector 7p
1404▲	4822 265 20723	Connector 2p
1452	2422 025 16382	Connector 3p m
1500▲	2422 086 10914	Fuse 4A 250V
1501▲	2422 090 01101	Soc Fuse 1P Female
1502▲	2422 090 01101	Soc Fuse 1P Female
1503▲	2422 132 07467	Relay 1p 12V 5A LKS1AF
1504▲	4822 265 20723	Connector 2p
1504	4822 267 10774	Connector 2p male (red)
1505▲	2422 025 16374	Connector 2p m
1620	2422 025 12485	Connector 11p m
1620	4822 267 10968	Connector 11p
1621	4822 267 10734	Connector 5p
1624	4822 267 10734	Connector 5p
1629	4822 265 30735	Connector 5p
1645	2422 025 16382	Connector 3p m
1670	2422 025 18686	Connector 80p f
1670	2422 025 19493	Connector 80p f
1701	4822 267 10771	Socket 2 x SCART
1705	4822 267 10982	Connector 2p
1911	4822 267 10565	Connector 4p
8361	3104 311 00141	Cable 3p/340/3p
8361	3104 311 05971	Cable 3p/340/3p
8401	3104 311 00451	Cable 7p/480/7p
8401	3104 311 10991	Cable 7p/560/7p
8401	3139 131 03591	Cable 7P 560mm
8401	3139 131 06231	Cable 7p/480/7pP
8404	3104 311 01951	Cable 2p3/560/2p4 Bk
8452	3104 311 00131	Cable 3p/560/3p
8452	3104 311 06261	Cable 2p/560/2p3
8542	3139 131 03611	Wire Sin/400/Sin Bk
8542	3139 131 05581	Cable Sin/340/Sin
8544	3139 131 06051	Cable Sin/220/Sin Bk
8620	3139 131 05271	Cable 11p/560/11p
8620	3139 131 06041	Cable 11p/560/11p Bk
8629	3139 121 09041	Cable 5p/560/5p
8629	3139 131 06021	Cable 5p/480/5p

—||—

2232	3198 017 42240	220nF 16V Y5V 0603
2232	4822 126 13879	220nF +80-20% 16V
2233	3198 024 44730	47nF 50V 0603
2235	2038 035 21307	68µ 25V
2236	5322 126 11583	10nF 10% 50V 0603
2248	4822 124 41751	47µF 20% 50V
2250	3198 037 01020	1000µ 6.3V
2251	4822 126 13193	4.7nF 10% 63V
2402	2020 558 00039	220pF 10% 3.15kV
2402	4822 126 11254	330pF 10% 2kV
2402	4822 126 14237	470pF 10% 2kV
2403	2020 558 00039	220pF 10% 3.15kV
2403	4822 126 14237	470pF 10% 2kV
2404	2038 035 13805	47µF 20% 160V
2404	4822 124 11936	47µF 20% 160V
2405	2020 558 00039	220pF 10% 3.15kV
2406	2020 558 00041	330pF 10% 3.15kV
2407	2022 333 00295	68nF 5% 400V
2409	4822 126 12105	33nF 5% 50V 0805
2410	4822 126 14585	100nF 10% 0805 50V
2411▲	2020 558 90611	1.8nF 10% 2kV
2411	4822 126 13435	1.2nF 10% 2kV
2411▲	4822 126 13451	2.2nF 10% 2kV
2412▲	4822 121 70617	10nF 5% 1.6kV
2413▲	4822 121 10575	27NF 5% 1600V
2413▲	4822 121 10653	22nF 5% 630V
2417	2022 333 00091	680nF 10% 250V
2418	2022 330 00019	680nF 275V
2418	2022 333 00163	360nF 5% 250V
2418	2022 333 00277	430nF 5% 250V
2418	2222 479 90021	390nF 5% 250V
2419	2038 301 00312	1.2µF 5% 250V
2422	2020 552 00033	330nF 10% 16V 0603
2422	2238 586 59812	100nF 20% 50V 0603
2425	5322 126 11583	10nF 10% 50V 0603
2427	5322 122 31866	6.8nF 10% 63V
2432	2238 586 59812	100nF 20% 50V 0603
2437	2238 916 15641	22nF 10% 25V 0603
2437	3198 017 33330	33nF 20% 16V 0603
2448▲	2238 930 55618	470pF 200V
2449	4822 124 80791	470µF 20% 16V
2450	4822 121 40434	330nF 10% 100V
2451	4822 121 40434	330nF 10% 100V
2452	4822 126 14238	2.2nF 50V 0603
2453	4822 126 14238	2.2nF 50V 0603
2454	2020 012 00037	2200µF 20% 16V
2454	4822 124 80791	470µF 20% 16V
2457▲	2238 930 55618	470pF 200V
2458	2022 318 00109	100nF 250V
2459▲	2238 930 55618	470pF 200V
2460	2020 012 00037	2200µF 20% 16V
2460	4822 124 80791	470µF 20% 16V
2461	4822 124 40248	10µF 20% 63V
2461	4822 124 41751	47µF 20% 50V
2462	2020 552 96683	220nF 10% 50V
2463	2020 552 96683	220nF 10% 50V
2464	2222 780 19867	2.2µF 16V 0805
2464	2238 586 59812	100nF 20% 50V 0603
2465	2222 780 19867	2.2µF 16V 0805
2466	2020 557 00005	330pF 100V
2468	5322 121 42578	100nF 5% 250V
2469	5322 124 40641	10µF 20% 100V
2470	2222 930 56627	2.2nF 10% 200V 0805
2471	4822 126 14238	2.2nF 50V 0603
2473	4822 126 14238	2.2nF 50V 0603
2476	4822 122 33177	10nF 20% 50V
2477	2238 580 15637	12nF 10% 50V 0805
2477	4822 122 33177	10nF 20% 50V
2478	4822 126 14241	330pF 0603 50V
2479	2020 552 96275	12nF 10% 50V 0603
2488	4822 121 51319	1µF 10% 63V
2489	4822 124 40248	10µF 20% 63V
2489	4822 124 40769	4.7µF 20% 100V
2490	4822 124 81286	47µF 20% 16V
2492▲	2238 930 55618	470pF 200V
2493▲	2238 930 55618	470pF 200V
2494▲	2238 930 55618	470pF 200V
2495	2020 552 96424	C1608X7R1H104KT
2497	4822 126 13883	220pF 5% 50V
2498	4822 126 14585	100nF 10% 0805 50V
2499	4822 126 14585	100nF 10% 0805 50V
2500▲	2222 338 22474	470nF 20% 275V
2501▲	4822 126 12793	2.2nF 10% 2kV
2503▲	4822 126 12793	2.2nF 10% 2kV
2504▲	4822 126 12793	2.2nF 10% 2kV
2505	2020 024 90773	330µF 400V
2506	4822 121 10798	33nF 5% 400V
2508	2222 338 22104	100nF 20% 275V
2509	4822 126 14335	1nF 10% 0805 100V
2510	4822 124 81151	22µF 50V
2511	4822 124 81151	22µF 50V
2512	2238 586 59812	100nF 20% 50V 0603
2513	4822 126 13881	470pF 5% 50V
2514▲	4822 126 13862	1.5nF 10% 2kV
2515	5322 126 11578	1nF 10% 50V 0603
2516	2238 586 59812	100nF 20% 50V 0603
2517	5322 126 11578	1nF 10% 50V 0603
2519	4822 126 13881	470pF 5% 50V
2520	2238 586 59812	100nF 20% 50V 0603
2521	3198 017 34730	47nF 16V 0603
2522	4822 126 13881	470pF 5% 50V
2523▲	3198 019 63310	330pF 10% 1000V
2523▲	4822 126 11254	330pF 10% 2kV
2523▲	4822 126 13682	100pF 5% 1kV
2526	2020 552 94427	100pF 5% 50V
2528	4822 121 51252	470nF 5% 63V
2535	2020 021 00092	4700µ 6.3V
2536	4822 124 81144	1000µF 16V
2538	5322 126 11578	1nF 10% 50V 0603
2539▲	4822 122 31177	470pF 10% 500V
2541	4822 124 40433	47µF 20% 25V
2542▲	2020 554 90199	1.5nF 250V
2543	2238 586 59812	100nF 20% 50V 0603
2544▲	4822 126 10206	2.2nF 10% 500V
2546	2020 552 00035	2.2µF 6.3V 10% 0603
2546	2020 552 00183	2.2µF 10% 6.3V 0603
2551▲	4822 126 13449	1nF 10% 2kV
2552	2020 021 00112	150µ 160V
2553	4822 126 14226	82pF 5% 50V 0603
2561	5322 122 32331	1nF 10% 100V
2562	4822 124 12417	2200µF 20% 25V
2563	4822 124 12417	2200µF 20% 25V
2564	2222 580 15649	100nF 10% 50V 0805
2565	5322 122 32331	1nF 10% 100V
2570▲	2252 811 95017	470pF 10% 250V
2571	3198 017 31530	15nF 20% 50V 0603
2572	5322 126 11583	10nF 10% 50V 0603
2575	5322 126 11583	10nF 10% 50V 0603
2576	2238 586 59812	100nF 20% 50V 0603
2577	2020 552 96637	10µF 10% 6.3V 0805
2578	4822 126 14238	2.2nF 50V 0603
2579	3198 017 34730	47nF 16V 0603
2582	2020 552 96723	1µF 20% 25V 0805
2583	2020 552 96637	10µF 10% 6.3V 0805
2584	4822 124 42027	470µF 20% 6,3V
2585	2020 552 96723	1µF 20% 25V 0805
2591	2020 552 00027	4.7µF 2% 6.3V 0603
2663	4822 126 13883	220pF 5% 50V
2666	2020 552 94743	5.6nF 50V 0603
2667	2020 552 94743	5.6nF 50V 0603
2669	2020 552 94743	5.6nF 50V 0603
2670	5322 126 11578	1nF 10% 50V 0603
2670	5322 126 11583	10nF 10% 50V 0603
2671	2020 552 94743	5.6nF 50V 0603
2672	3198 016 31590	15pF 10% 50V 0603
2672	4822 122 33752	15pF 5% 50V
2673	3198 016 31590	15pF 10% 50V 0603
2673	4822 122 33752	15pF 5% 50V
2674	4822 124 11947	10µF 20% 16V
2676	4822 124 40769	4.7µF 20% 100V
2677	5322 122 31647	1nF 10% 63V
2678	2238 586 59812	100nF 20% 50V 0603
2679	5322 126 11578	1nF 10% 50V 0603
2680	2238 586 59812	100nF 20% 50V 0603
2682	3198 017 41050	1µF 10V 0603
2688	4822 124 40433	47µF 20% 25V
2689	4822 124 40248	10µF 20% 63V
2690	4822 126 14043	1µF +80-20% 16V 0805
2691	4822 126 14043	1µF +80-20% 16V 0805
2692	4822 124 81286	47µF 20% 16V
2693	5322 126 11578	1nF 10% 50V 0603
2694	5322 126 11578	1nF 10% 50V 0603
2695	5322 126 11578	1nF 10% 50V 0603
2697	4822 126 13883	220pF 5% 50V
2698	3198 017 34730	47nF 16V 0603
2703	5322 126 11578	1nF 10% 50V 0603
2704	5322 126 11578	1nF 10% 50V 0603
2705	5322 126 11578	1nF 10% 50V 0603
2706	5322 126 11578	1nF 10% 50V 0603
2708	4822 126 14241	330pF 0603 50V
2710	4822 126 14241	330pF 0603 50V
2713	5322 126 11578	1nF 10% 50V 0603
2715	5322 126 11578	1nF 10% 50V 0603
2716	3198 017 41050	1µF 10V 0603
2717	5322 126 11578	1nF 10% 50V 0603
2718	5322 126 11578	1nF 10% 50V 0603
2719	5322 126 11578	1nF 10% 50V 0603
2720	5322 126 11578	1nF 10% 50V 0603
2721	4822 126 11785	47pF 5% 50V 0603
2722	4822 126 11785	47pF 5% 50V 0603
2975	4822 126 13883	220pF 5% 50V
2976	4822 126 13883	220pF 5% 50V
2986	2020 552 96424	C1608X7R1H104KT
2986	2238 586 59812	100nF 20% 50V 0603
2987	2020 552 96424	C1608X7R1H104KT
2987	2238 586 59812	100nF 20% 50V 0603
2988	2020 552 96424	C1608X7R1H104KT
2988	2238 586 59812	100nF 20% 50V 0603
2989	4822 126 13879	220nF +80-20% 16V

2990	3198 016 31020	1nF 25V 0603
2991	4822 124 80604	47µF 20% 50V
2992	4822 126 13879	220nF +80-20% 16V
2993	3198 016 31020	1nF 25V 0603
2994	3198 017 34730	47nF 16V 0603
2995	3198 017 34730	47nF 16V 0603
2996	3198 017 34730	47nF 16V 0603
2997	3198 017 34730	47nF 16V 0603
2998	4822 124 80604	47µF 20% 50V

–WW–

3238	4822 051 30103	10kΩ 5% 0.062W
3239	4822 051 30101	100Ω 5% 0.062W
3240	4822 116 52175	100Ω 5% 0.5W
3241	4822 051 30101	100Ω 5% 0.062W
3242	4822 051 30101	100Ω 5% 0.062W
3401	4822 050 24703	47kΩ 1% 0.6W
3402	4822 116 52219	330Ω 5% 0.5W
3403	4822 050 11002	1kΩ 1% 0.4W
3408	4822 117 13632	100kΩ 1% 0603 0.62W
3409▲	4822 116 21239	VDR 1mA/612V
3410▲	4822 116 21239	VDR 1mA/612V
3414	4822 050 24708	4.7Ω 1% 0.6W
3414	4822 050 25608	5.6Ω 1% 0.6W
3415	4822 050 24708	4.7Ω 1% 0.6W
3415	4822 050 25608	5.6Ω 1% 0.6W
3416	4822 051 20479	47Ω 5% 0.1W
3417	4822 051 30154	150kΩ 5% 0.062W
3418	4822 050 11002	1kΩ 1% 0.4W
3418	4822 116 52269	3.3kΩ 5% 0.5W
3419	4822 050 24708	4.7Ω 1% 0.6W
3419	4822 050 25608	5.6Ω 1% 0.6W
3421	4822 116 52182	15Ω 5% 0.5W
3422	4822 116 83884	47kΩ 5% 0.5W
3423	2322 702 60684	680kΩ 5% 0603
3423	4822 051 30334	330kΩ 5% 0.062W
3423	4822 051 30474	470kΩ 5% 0.062W
3424	4822 051 30123	12kΩ 5% 0.1W
3424	4822 051 30223	22kΩ 5% 0.062W
3425	2312 915 16803	68kΩ 1% 0.5W
3425	4822 050 21004	100kΩ 1% 0.6W
3425	4822 050 28203	82kΩ 1% 0.6W
3426▲	4822 052 10398	3.9Ω 5% 0,33W
3432	4822 050 24708	4.7Ω 1% 0.6W
3432	4822 050 25608	5.6Ω 1% 0.6W
3433	4822 053 12279	27Ω 5% 3W
3435	4822 051 30684	680kΩ 5% 0.062W
3437	4822 051 30103	10kΩ 5% 0.062W
3437	4822 051 30223	22kΩ 5% 0.062W
3437	4822 051 30392	3.9Ω 5% 0.063W 0603
3443	4822 051 30223	22kΩ 5% 0.062W
3450▲	4822 052 10108	1Ω 5% 0.33W
3450	4822 052 10189	18R00 5% 0,33W
3450▲	4822 052 10828	8.2Ω 5% 0,33W
3451	4822 050 24708	4.7Ω 1% 0.6W
3451	4822 050 25608	5.6Ω 1% 0.6W
3452	2138 112 01568	5.6Ω 5% 0805
3453	4822 051 30563	56kΩ 5% 0.062W
3455▲	4822 052 11108	1Ω 5% 0.5W
3456▲	2306 207 03277	0Ω
3458▲	4822 052 11108	1Ω 5% 0.5W
3459	4822 051 30102	1kΩ 5% 0.062W
3461	4822 051 30152	1.5Ω 5% 0.062W
3463	4822 051 30152	1.5Ω 5% 0.062W
3466▲	4822 052 10568	5.6Ω 5% 0.33W
3467	4822 116 83872	220Ω 5% 0.5W
3468	4822 116 83872	220Ω 5% 0.5W
3470	3198 039 20080	2Ω
3470	4822 050 23908	3.9Ω 1% 0.6W
3471	2312 915 11808	1.8Ω
3471	2312 915 12708	2.7Ω
3471	3198 039 20080	2Ω
3471	4822 050 23908	3.9Ω 1% 0.6W
3471	4822 050 24708	4.7Ω 1% 0.6W
3472	2312 915 11508	1.5Ω 1%
3472	4822 050 22208	2.2Ω 1% 0,6W
3472	4822 050 23908	3.9Ω 1% 0.6W
3472	4822 050 24708	4.7Ω 1% 0.6W
3473	2322 194 63109	10Ω 5% 2W
3474	4822 116 52231	820Ω 5% 0.5W
3477	4822 116 52231	820Ω 5% 0.5W
3480	4822 051 30123	12kΩ 5% 0.1W
3485	4822 052 10158	1.5Ω 5% 0.33W
3485▲	4822 052 10228	2.2Ω 5% 0.33W
3486▲	4822 052 10108	1Ω 5% 0.33W
3487	2120 105 00041	820Ω 5% 2W
3487	4822 053 11102	1KΩ 5% 2W
3488	4822 053 20224	220KΩ 5% 0.25W
3490	4822 050 21501	150Ω 1% 0,6W
3491	4822 051 30103	10kΩ 5% 0.062W
3491	4822 051 30123	12kΩ 5% 0.1W
3491	4822 051 30153	15kΩ 5% 0.062W
3491	4822 051 30183	18kΩ 5% 0.062W
3492	4822 116 52283	4.7kΩ 5% 0.5W
3493▲	4822 052 11228	2R20 5% 0,5W
3499	4822 050 21003	10kΩ 1% 0.6W
3499	4822 116 52285	470kΩ 5% 0.5W
3502	4822 116 83872	220Ω 5% 0.5W
3503	4822 252 11215	DSP301N-A21F
3504▲	4822 053 21155	1.5MΩ 5% 0.5W
3505▲	2122 550 00171	1mΩ 612V
3508	3198 013 04710	470Ω 20% 0.5W
3510▲	2122 612 00055	4.7Ω 3W
3511	4822 050 24708	4.7Ω 1% 0.6W
3512	4822 117 11817	1.2kΩ 1% 0.0625W
3513▲	4822 052 10222	2.2kΩ 5% 0.33W
3514▲	4822 052 10479	47Ω 5% 0.33W
3515	4822 050 11002	1kΩ 1% 0.4W
3516	3198 012 11570	0.15Ω 5% 1W
3517	2322 704 63004	300KΩ
3518	4822 051 30332	3.3Ω 5% 0.062W
3519	4822 116 52244	15kΩ 5% 0.5W
3520	3198 012 11570	0.15Ω 5% 1W
3521	4822 117 11817	1.2kΩ 1% 0.0625W
3522	4822 051 30563	56kΩ 5% 0.062W
3523▲	2122 663 00018	4.7Ω 20%
3524	4822 116 52269	3.3kΩ 5% 0.5W
3525	2312 915 13004	300kΩ
3526▲	2322 750 61501	150Ω 1206
3527	4822 117 12925	47kΩ 1% 0.063W 0603
3528	4822 051 30105	1MΩ 5% 0.062W
3529	4822 053 20155	1.5MΩ 5% 0.25W
3530	4822 051 30563	56kΩ 5% 0.062W
3531	4822 050 11002	1kΩ 1% 0.4W
3532	4822 051 20158	1.5Ω 5% 0.1W
3533	4822 051 20188	1.8Ω 5% 0.1W
3534	2322 734 63309	33Ω 1% 0.1W 0805
3535▲	4822 052 10478	4.7Ω 5% 0.33W
3536▲	4822 052 10221	220Ω 5% 0.33W
3540	4822 051 30683	68kΩ 5% 0.062W
3541	4822 117 12925	47kΩ 1% 0.063W 0603
3542	4822 051 30681	680Ω 5% 0.062W
3543	4822 051 30103	10kΩ 5% 0.062W
3544	2322 704 62202	2.2kΩ 1% 0603
3545	2322 704 62202	2.2kΩ 1% 0603
3546	4822 051 30683	68kΩ 5% 0.062W
3549	4822 117 12925	47kΩ 1% 0.063W 0603
3550	4822 116 52269	3.3kΩ 5% 0.5W
3551	4822 051 30223	22kΩ 5% 0.062W
3552	4822 051 30103	10kΩ 5% 0.062W
3553	4822 117 12925	47kΩ 1% 0.063W 0603
3554	4822 051 30103	10kΩ 5% 0.062W
3563	4822 116 83872	220Ω 5% 0.5W
3565	4822 051 30273	27kΩ 5% 0.062W
3567	4822 051 30332	3.3Ω 5% 0.062W
3568	4822 117 12925	47kΩ 1% 0.063W 0603
3571	4822 116 52228	680Ω 5% 0.5W
3573	4822 051 30153	15kΩ 5% 0.062W
3574	2322 702 60184	180kΩ 5% 0603
3575	4822 050 28203	82kΩ 1% 0.6W
3576	5322 117 13034	1.5kΩ 1% 0.063W 0603
3579	4822 116 52256	2.2kΩ 5% 0.5W
3580	4822 117 12891	220kΩ 1%
3581	4822 051 30223	22kΩ 5% 0.062W
3583	4822 051 30562	5.6kΩ 5% 0.063W 0603
3584	4822 051 30103	10kΩ 5% 0.062W
3585	4822 051 30563	56kΩ 5% 0.062W
3586	4822 051 30562	5.6kΩ 5% 0.063W 0603
3587	4822 116 52256	2.2kΩ 5% 0.5W
3588	4822 051 30334	330kΩ 5% 0.062W
3589	4822 051 30103	10kΩ 5% 0.062W
3590	4822 117 12864	82kΩ 5% 0.6W
3591	4822 051 30103	10kΩ 5% 0.062W
3593	4822 051 30103	10kΩ 5% 0.062W
3594	4822 051 30223	22kΩ 5% 0.062W
3595	4822 117 13632	100kΩ 1% 0603 0.62W
3596	4822 051 30103	10kΩ 5% 0.062W
3596	4822 051 30472	4.7Ω 5% 0.062W
3597	4822 117 12891	220kΩ 1%
3598	4822 053 20334	330kΩ 5% 0.25W
3625	3198 021 31080	1Ω 5% 0603
3626	3198 021 31080	1Ω 5% 0603
3627	4822 116 52175	100Ω 5% 0.5W
3628	4822 116 52175	100Ω 5% 0.5W
3670▲	4822 052 10688	6.8Ω 5% 0.33W
3677	4822 051 30103	10kΩ 5% 0.062W
3683	4822 050 11002	1kΩ 1% 0.4W
3685	4822 051 30102	1kΩ 5% 0.062W
3686	4822 116 52234	100kΩ 5% 0.5W
3686	4822 117 13632	100kΩ 1% 0603 0.62W
3687	4822 116 52175	100Ω 5% 0.5W
3688	4822 051 30103	10kΩ 5% 0.062W
3701	4822 116 83868	150Ω 5% 0.5W
3702	4822 051 30151	150Ω 5% 0.062W
3703	4822 116 83868	150Ω 5% 0.5W
3704	4822 051 30151	150Ω 5% 0.062W
3705	4822 051 30101	100Ω 5% 0.062W
3706	4822 051 30101	100Ω 5% 0.062W
3707	4822 051 30151	150Ω 5% 0.062W
3708	4822 051 30151	150Ω 5% 0.062W
3709	4822 051 30151	150Ω 5% 0.062W
3710	4822 051 30151	150Ω 5% 0.062W
3711	4822 051 30101	100Ω 5% 0.062W
3712	4822 051 30101	100Ω 5% 0.062W
3714	4822 116 83882	39kΩ 5% 0.5W
3716	4822 051 30103	10kΩ 5% 0.062W
3717	4822 116 52175	100Ω 5% 0.5W
3718	4822 051 30393	39kΩ 5% 0.062W
3719	4822 051 30103	10kΩ 5% 0.062W
3724	4822 116 52175	100Ω 5% 0.5W
3725	4822 116 52201	75Ω 5% 0.5W
3728	4822 116 52201	75Ω 5% 0.5W
3729	4822 116 52201	75Ω 5% 0.5W
3732	4822 051 30759	75Ω 5% 0.062W
3733	4822 051 30759	75Ω 5% 0.062W
3735	4822 051 30151	150Ω 5% 0.062W
3736	4822 051 30101	100Ω 5% 0.062W
3739	4822 051 30561	560Ω 5% 0.062W
3740	4822 051 30103	10kΩ 5% 0.062W
3742	4822 051 30151	150Ω 5% 0.062W
3743	4822 051 30333	33kΩ 5% 0.062W
3744	4822 051 30333	33kΩ 5% 0.062W
3745	4822 051 30333	33kΩ 5% 0.062W
3746	4822 051 30333	33kΩ 5% 0.062W
3747	4822 051 30561	560Ω 5% 0.062W
3748	4822 051 30101	100Ω 5% 0.062W
3749	4822 051 30103	10kΩ 5% 0.062W
3985	4822 051 30103	10kΩ 5% 0.062W
3988	4822 051 30123	12kΩ 5% 0.1W
3989	4822 051 30109	10Ω 5% 0.062W
3991	4822 051 30103	10kΩ 5% 0.062W
3992	4822 051 30123	12kΩ 5% 0.1W
3993	4822 051 30109	10Ω 5% 0.062W
4420	4822 051 20008	Jumper 0805
4501	4822 051 20008	Jumper 0805
4664	4822 051 30008	Jumper 0603
4694	4822 051 30008	Jumper 0603
4905	4822 051 20008	Jumper 0805
4974	4822 051 20008	Jumper 0805
9664	4822 051 30008	Jumper 0603

–~~–

5247	4822 157 11867	5.6µH 5%
5248	2422 549 43062	Bead 600Ω at 100MHz
5249	2422 549 43062	Bead 600Ω at 100MHz
5250	2422 549 43062	Bead 600Ω at 100MHz
5251	2422 549 43062	Bead 600Ω at 100MHz
5402	2422 531 00057	SD12404-02 Y
5406	2422 531 02435	C948-02
5408	2422 531 02357	Bridge coil W7132-004Y
5410	2422 536 00059	12µH 10%
5450▲	2422 531 00061	JF0101-27308B
5450	2422 531 00062	JF0101-27309B B
5450▲	2422 531 00079	UU 1372.7077D
5450▲	2422 531 00081	UU 1372.0130A
5450▲	2422 531 00085	UU 1372.0131A
5452	4822 157 51462	10µH 10%
5453	4822 157 11771	0.09µH 10%
5455▲	2422 531 00043	CD25405-00
5455▲	2422 531 00074	SD20417-02
5456	4822 526 10704	Bead 50 Ω at 100MHz
5500▲	4822 157 10476	DMF-2820H
5501▲	4822 157 11523	Line filter 5mH/2A
5502▲	2422 549 45296	Mains harm filter 38mH
5504▲	2422 531 00049	SS25336-03 B
5511	4822 526 10704	Bead 50 Ω at 100MHz
5512▲	2422 531 02632	SS42316-0
5532	4822 526 10704	Bead 50 Ω at 100MHz
5551	4822 526 10704	Bead 50 Ω at 100MHz
5552	4822 157 71401	27µH
5561	4822 526 10704	Bead 50 Ω at 100MHz
5562	4822 526 10704	Bead 50 Ω at 100MHz
5564	2422 535 94637	4.7µH 20% LHL08
5565	4822 157 11411	Bead 80Ω at 100MHz
5566	4822 157 11411	Bead 80Ω at 100MHz
5567	4822 157 11411	Bead 80Ω at 100MHz
5680	4822 526 10704	Bead 50 Ω at 100MHz
5681	4822 157 11411	Bead 80Ω at 100MHz
5682	4822 157 11411	Bead 80Ω at 100MHz
5683	4822 157 11867	5.6µH 5%
5684	4822 157 11867	5.6µH 5%
5685	2422 549 43062	Bead 600Ω at 100MHz
5686	2422 549 43062	Bead 600Ω at 100MHz
5687	2422 549 43062	Bead 600Ω at 100MHz
5688	2422 549 43062	Bead 600Ω at 100MHz
5701	2422 549 43062	Bead 600Ω at 100MHz
5702	2422 549 43062	Bead 600Ω at 100MHz
5703	2422 549 43062	Bead 600Ω at 100MHz

5704	4822 157 10977	4.7µH 10%
5705	4822 157 10977	4.7µH 10%
5706	2422 549 43062	Bead 600Ω at 100MHz
5708	2422 549 43062	Bead 600Ω at 100MHz

6234	9340 548 71115	PDZ33B
6238	4822 130 11397	BAS316
6403	9322 185 83668	SM ES1D
6404	8238 274 33830	DIODE DMV32
6404	9322 169 61687	DMV1500M
6424	4822 130 11416	PDZ6.8B
6425	4822 130 11397	BAS316
6426	4822 130 34173	BZX79-C5V6
6452	4822 130 31607	RGP10D
6453	9334 939 60673	RGP10G
6456	4822 130 10871	SBYV27-200
6457	4822 130 10871	SBYV27-200
6458	9340 548 69115	PDZ27B
6459	4822 130 11152	UDZ18B
6461	9322 128 65685	RS1G
6464	9340 548 69115	PDZ27B
6465	5322 130 34337	BAV99
6465	9340 260 20115	BAW56W
6466	9322 185 83668	SM ES1D
6467	3139 120 52021	BYV29X-500
6468	4822 130 11397	BAS316
6469	3139 120 52021	BYV29X-500
6471	4822 130 31607	RGP10D
6474	4822 130 34379	BZX79-B27
6476	5322 130 32296	BZV85-C10
6478	4822 130 10837	UDZS8.2B
6500	3198 010 10640	Bridge cell GBU4K
6509	4822 130 31607	RGP10D
6511	4822 130 31607	RGP10D
6512	4822 130 11397	BAS316
6514	4822 130 11397	BAS316
6532	9322 197 45703	BAV21WS
6533	9322 197 45703	BAV21WS
6535	9322 161 76682	SB340L-7024
6536	9322 212 98673	SB260
6538	4822 130 11397	BAS316
6539	9322 212 82685	UDZS13B
6540	4822 130 11152	UDZ18B
6541	9322 129 41685	BZM55-C12
6551	9337 443 80127	BYT28-500
6562	9322 161 78682	SB360L-7024
6563	9322 161 78682	SB360L-7024
6564	4822 130 11397	BAS316
6565	4822 130 10837	UDZS8.2B
6567	4822 130 11397	BAS316
6574	9340 260 20115	BAW56W
6575	4822 130 31878	1N4003G
6576	4822 130 11416	PDZ6.8B
6578	4822 130 11397	BAS316
6581	9322 197 45703	BAV21WS
6681	5322 130 34331	BAV70
6682	4822 130 10838	UDZ3.3B
6683	4822 130 11397	BAS316
6684	9322 163 91685	BZX384-C6V2
6701	4822 130 11416	PDZ6.8B
6702	4822 130 11416	PDZ6.8B
6703	4822 130 11416	PDZ6.8B
6704	9322 129 41685	BZM55-C12
6705	4822 130 11416	PDZ6.8B
6706	4822 130 11416	PDZ6.8B
6707	4822 130 11416	PDZ6.8B
6708	4822 130 11416	PDZ6.8B
6709	4822 130 11416	PDZ6.8B
6710	4822 130 11416	PDZ6.8B
6711	4822 130 11416	PDZ6.8B
6712	4822 130 11416	PDZ6.8B

7403	4822 130 44568	BC557B
7404	9340 547 13215	BSH103
7405	4822 130 63627	BU2527AF
7405	9340 263 10127	BU2527AX
7405	9340 591 84127	ON5277
7406	9322 160 34687	FQPF3N60
7406	9322 194 27687	STP3NK60ZFP
7407	4822 130 10255	MUN2213
7455	9352 637 54112	TDA4863J/V1
7456	4822 130 10255	MUN2213
7486	9340 547 00215	PDTC143ZT
7510	9352 720 43118	TEA1506T/N1
7511	9352 720 43118	TEA1506T/N1
7512	9322 174 27687	FQPF7N80
7513⚠	8238 274 02070	TCET1103G
7516⚠	8238 274 02070	TCET1103G
7517	5322 130 60159	BC846B
7525	9322 194 21687	STP5NK80ZFP
7532	4822 130 60373	BC856B
7541	4822 130 60373	BC856B
7542	3198 010 70510	TL431CZ
7542	4822 209 14933	TL431IZ
7545	9322 179 08685	SI2305DS
7547	4822 130 11155	PDTC114ET
7548	4822 130 11155	PDTC114ET
7549	4822 130 62343	IMX1
7561	3198 010 42310	BC847BW
7562	3198 010 42310	BC847BW
7567	5322 130 60159	BC846B
7571	3198 010 70510	TL431CZ
7571	4822 209 14933	TL431IZ
7573	4822 130 11155	PDTC114ET
7575	5322 130 60159	BC846B
7576	4822 130 62343	IMX1
7583	4822 130 62343	IMX1
7584	4822 130 11155	PDTC114ET
7673	9322 123 54687	LD1117V33
7674	9322 202 97682	KA78R08
7701	4822 130 62343	IMX1
7990	4822 209 32641	TDA2616Q
7991	4822 130 63732	MMUN2212

Small Signal Board [B]

Various

0601	3139 127 03603	SW see item 7790
1112	2422 549 44369	SAW 38.9MHz K9656L
1113	2422 549 44372	SAW 38.9MHz K3953L
1581	2422 543 01359	Xtal 13.5MHz 12pF

2002	2020 552 96507	10µF 10V
2003	2020 552 96507	10µF 10V
2005	2020 552 96618	1nF 10% 50V 0402
2006	2020 552 96618	1nF 10% 50V 0402
2008	2020 552 96618	1nF 10% 50V 0402
2012	3198 017 44740	470nF 10V 0603
2013	3198 035 04710	470pF 50V 0402
2014	3198 035 71040	100nF 10% 16V 0402
2015	3198 035 04710	470pF 50V 0402
2016	3198 017 44740	470nF 10V 0603
2018	3198 035 04710	470pF 50V 0402
2019	3198 017 44740	470nF 10V 0603
2021	3198 035 04710	470pF 50V 0402
2022	3198 017 44740	470nF 10V 0603
2024	3198 035 04710	470pF 50V 0402
2025	3198 017 44740	470nF 10V 0603
2027	3198 035 04710	470pF 50V 0402
2028	3198 017 44740	470nF 10V 0603
2030	2020 552 96618	1nF 10% 50V 0402
2031	2020 552 96618	1nF 10% 50V 0402
2032	2020 552 96618	1nF 10% 50V 0402
2033	2020 552 96618	1nF 10% 50V 0402
2037	2020 552 96507	10µF 10V
2038	2020 552 96507	10µF 10V
2039	2020 552 96507	10µF 10V
2040	2020 552 96507	10µF 10V
2046	5322 124 41945	22µF 20% 35V
2047	4822 124 23002	10µF 16V
2048	3198 035 71040	100nF 10% 16V 0402
2049	3198 035 71040	100nF 10% 16V 0402
2050	3198 035 71040	100nF 10% 16V 0402
2051	3198 035 71040	100nF 10% 16V 0402
2060	3198 035 71040	100nF 10% 16V 0402
2062	3198 035 71030	10nF 16V 0402
2063	3198 035 71030	10nF 16V 0402
2065	3198 035 71030	10nF 16V 0402
2066	3198 035 71040	100nF 10% 16V 0402
2067	3198 035 71030	10nF 16V 0402
2068	3198 035 71040	100nF 10% 16V 0402
2071	3198 035 71030	10nF 16V 0402
2072	3198 035 71030	10nF 16V 0402
2073	3198 035 71030	10nF 16V 0402
2078	3198 035 71040	100nF 10% 16V 0402
2079	3198 035 71040	100nF 10% 16V 0402
2081	3198 035 71040	100nF 10% 16V 0402
2082	4822 126 14491	2.2µF 10V 0805
2083	3198 035 71040	100nF 10% 16V 0402
2084	3198 035 71040	100nF 10% 16V 0402
2085	3198 035 71040	100nF 10% 16V 0402
2088	4822 126 14491	2.2µF 10V 0805
2101	3198 035 71030	10nF 16V 0402
2102	3198 035 71030	10nF 16V 0402
2119	3198 035 71030	10nF 16V 0402
2126	2238 869 15101	100pF 5% 50V 0402
2127	3198 035 71040	100nF 10% 16V 0402
2130	3198 035 71030	10nF 16V 0402
2134	3198 035 71040	100nF 10% 16V 0402
2135	4822 124 23002	10µF 16V
2136	4822 124 23002	10µF 16V
2137	4822 124 12095	100µF 20% 16V
2138	3198 035 71040	100nF 10% 16V 0402
2150	3198 035 71040	100nF 10% 16V 0402
2152	3198 035 71040	100nF 10% 16V 0402
2154	4822 124 23002	10µF 16V
2155	3198 035 71040	100nF 10% 16V 0402
2156	3198 035 71040	100nF 10% 16V 0402
2157	3198 035 71040	100nF 10% 16V 0402
2281	3198 035 71040	100nF 10% 16V 0402
2282	3198 035 71040	100nF 10% 16V 0402
2284	3198 035 71040	100nF 10% 16V 0402
2285	3198 035 71040	100nF 10% 16V 0402
2300	3198 035 71040	100nF 10% 16V 0402
2305	3198 017 41050	1µF 10V 0603
2307	2238 869 15101	100pF 5% 50V 0402
2308	2238 869 15101	100pF 5% 50V 0402
2310	4822 124 23002	10µF 16V
2311	3198 035 71030	10nF 16V 0402
2317	2238 869 15101	100pF 5% 50V 0402
2318	2238 869 15101	100pF 5% 50V 0402
2321	3198 035 71030	10nF 16V 0402
2324	2238 869 15101	100pF 5% 50V 0402
2325	2238 869 15829	82pF 5% 50V 0402
2327	2238 869 15101	100pF 5% 50V 0402
2328	2238 869 15101	100pF 5% 50V 0402
2331	3198 035 71030	10nF 16V 0402
2341	3198 035 71040	100nF 10% 16V 0402
2342	3198 035 71040	100nF 10% 16V 0402
2343	3198 035 71040	100nF 10% 16V 0402
2344	3198 035 71040	100nF 10% 16V 0402
2345	3198 035 71040	100nF 10% 16V 0402
2346	3198 035 71040	100nF 10% 16V 0402
2350	4822 124 12095	100µF 20% 16V
2351	2238 869 15109	10pF 5% 50V 0402
2352	2238 869 15109	10pF 5% 50V 0402
2358	2238 869 15101	100pF 5% 50V 0402
2359	3198 035 71040	100nF 10% 16V 0402
2360	2238 869 15101	100pF 5% 50V 0402
2361	4822 126 14491	2.2µF 10V 0805
2363	2238 869 15101	100pF 5% 50V 0402
2365	2238 869 15101	100pF 5% 50V 0402
2366	4822 126 14491	2.2µF 10V 0805
2371	2020 552 96618	1nF 10% 50V 0402
2372	2020 552 96618	1nF 10% 50V 0402
2377	2020 552 96623	2.2nF 10% 50V 0402
2379	2020 552 96623	2.2nF 10% 50V 0402
2380	3198 035 04710	470pF 50V 0402
2384	2020 552 96618	1nF 10% 50V 0402
2386	2238 869 15109	10pF 5% 50V 0402
2395	3198 035 71030	10nF 16V 0402
2397	3198 035 71040	100nF 10% 16V 0402
2432	2020 552 96793	4.7nF 10% 50V 0402
2433	2020 552 96793	4.7nF 10% 50V 0402
2438	3198 017 44740	470nF 10V 0603
2439	3198 017 44740	470nF 10V 0603
2440	2020 552 96618	1nF 10% 50V 0402
2441	2020 552 96618	1nF 10% 50V 0402
2442	2020 552 96618	1nF 10% 50V 0402
2443	2020 552 96618	1nF 10% 50V 0402
2444	2020 552 96618	1nF 10% 50V 0402
2445	2020 552 96618	1nF 10% 50V 0402
2447	4822 124 12095	100µF 20% 16V
2450	3198 035 71030	10nF 16V 0402
2452	3198 035 71030	10nF 16V 0402
2461	3198 017 44740	470nF 10V 0603
2462	3198 017 44740	470nF 10V 0603
2480	3198 017 44740	470nF 10V 0603
2481	3198 017 44740	470nF 10V 0603
2483	2020 552 96618	1nF 10% 50V 0402
2484	4822 124 23002	10µF 16V
2485	2020 552 96618	1nF 10% 50V 0402
2486	3198 035 71040	100nF 10% 16V 0402
2487	4822 124 23002	10µF 16V
2488	4822 124 12095	100µF 20% 16V
2489	4822 124 12095	100µF 20% 16V
2514	2238 869 15189	18pF 5% 50V 0402
2516	2238 869 15189	18pF 5% 50V 0402
2525	3198 035 71040	100nF 10% 16V 0402
2546	3198 035 71040	100nF 10% 16V 0402
2557	2238 869 15101	100pF 5% 50V 0402
2571	3198 035 71040	100nF 10% 16V 0402
2581	4822 126 14519	22pF 5% 50V 0402
2582	4822 126 14519	22pF 5% 50V 0402
2583	3198 035 71040	100nF 10% 16V 0402
2584	3198 035 71040	100nF 10% 16V 0402
2600	3198 035 71040	100nF 10% 16V 0402
2601	3198 035 71040	100nF 10% 16V 0402
2604	3198 035 71040	100nF 10% 16V 0402
2607	3198 035 71040	100nF 10% 16V 0402

2609	3198 035 71040	100nF 10% 16V 0402
2611	3198 035 71040	100nF 10% 16V 0402
2612	3198 035 71040	100nF 10% 16V 0402
2615	3198 035 71040	100nF 10% 16V 0402
2618	3198 035 71040	100nF 10% 16V 0402
2620	3198 035 71040	100nF 10% 16V 0402
2622	3198 035 71040	100nF 10% 16V 0402
2623	3198 035 71040	100nF 10% 16V 0402
2628	3198 035 71040	100nF 10% 16V 0402
2629	3198 035 71040	100nF 10% 16V 0402
2630	3198 035 71040	100nF 10% 16V 0402
2633	3198 035 71040	100nF 10% 16V 0402
2634	3198 035 71040	100nF 10% 16V 0402
2638	3198 035 71040	100nF 10% 16V 0402
2644	5322 124 41945	22µF 20% 35V
2645	4822 124 23002	10µF 16V
2651	2020 021 00126	100µ 6.3V
2652	2020 552 96507	10µF 10V
2654	2020 552 96507	10µF 10V
2655	2020 552 96507	10µF 10V
2656	3198 035 71040	100nF 10% 16V 0402
2657	2238 869 15101	100pF 5% 50V 0402
2659	3198 017 42240	220nF 16V Y5V 0603
2659	4822 126 13879	220nF +80-20% 16V
2730	3198 035 71040	100nF 10% 16V 0402
2731	3198 035 71040	100nF 10% 16V 0402
2732	3198 035 71040	100nF 10% 16V 0402
2733	3198 035 71040	100nF 10% 16V 0402
2734	3198 035 71040	100nF 10% 16V 0402
2792	3198 035 71040	100nF 10% 16V 0402
2793	3198 035 71040	100nF 10% 16V 0402
2918	2238 869 15101	100pF 5% 50V 0402
2919	2238 869 15101	100pF 5% 50V 0402
2920	2238 869 15829	82pF 5% 50V 0402
2932	2238 869 15101	100pF 5% 50V 0402
2933	2238 869 15101	100pF 5% 50V 0402
2935	2238 869 15101	100pF 5% 50V 0402
2936	2238 869 15101	100pF 5% 50V 0402
2938	2238 869 15101	100pF 5% 50V 0402
2948	2238 869 15189	18pF 5% 50V 0402
2949	2238 869 15189	18pF 5% 50V 0402
2950	2238 869 15101	100pF 5% 50V 0402
2951	2238 869 15101	100pF 5% 50V 0402
2962	2238 869 15101	100pF 5% 50V 0402
2967	2020 552 96618	1nF 10% 50V 0402
2968	2020 552 96618	1nF 10% 50V 0402
2975	2020 552 96793	4.7nF 10% 50V 0402
2976	2020 552 96793	4.7nF 10% 50V 0402
2977	2238 869 15101	100pF 5% 50V 0402
2978	2238 869 15101	100pF 5% 50V 0402
2979	3198 035 71040	100nF 10% 16V 0402

–WW–

3002	2238 869 15101	100pF 5% 50V 0402
3003	2238 869 15101	100pF 5% 50V 0402
3004	2238 869 15101	100pF 5% 50V 0402
3005	2238 869 15101	100pF 5% 50V 0402
3006	3198 031 04730	47Ω 5% 0402
3007	3198 031 04730	47Ω 5% 0402
3010	4822 117 13605	Jumper 0402
3011	4822 117 13605	Jumper 0402
3018	4822 117 11152	4.7Ω 5%
3019	5322 117 11726	10Ω 5%
3022	3198 031 04730	47Ω 5% 0402
3024	3198 031 04730	47Ω 5% 0402
3026	3198 031 04730	47Ω 5% 0402
3027	3198 031 04730	47Ω 5% 0402
3032	4822 117 13597	330Ω 5% 0.01W 0402
3033	4822 117 13597	330Ω 5% 0.01W 0402
3060	4822 117 13602	2.2kΩ 5% 0.01W 0402
3061	4822 117 13602	2.2kΩ 5% 0.01W 0402
3062	3198 031 01810	180Ω 5% 0402
3063	4822 117 13596	220Ω 5% 0.01W 0402
3066	4822 117 13602	2.2kΩ 5% 0.01W 0402
3067	4822 117 13548	1kΩ 5% 0402
3068	4822 117 13548	1kΩ 5% 0402
3076	4822 051 30759	75Ω 5% 0.062W
3077	4822 051 30759	75Ω 5% 0.062W
3078	4822 051 30759	75Ω 5% 0.062W
3079	4822 051 30759	75Ω 5% 0.062W
3080	4822 051 30759	75Ω 5% 0.062W
3081	4822 051 30759	75Ω 5% 0.062W
3082	4822 051 30759	75Ω 5% 0.062W
3101	4822 117 13602	2.2kΩ 5% 0.01W 0402
3103	3198 031 06820	6.8kΩ 5% 0.01W 0402
3104	4822 117 13602	2.2kΩ 5% 0.01W 0402
3106	3198 031 02730	27kΩ 5% 0402
3131	4822 117 13606	10kΩ 5% 0.01W 0402
3132	4822 117 13545	100Ω 1% 0402
3138	3198 031 03910	390Ω 1% 0402
3150	3198 031 01820	1.8kΩ 5% 0.01W 0402
3151	3198 031 01220	1.2kΩ 5% 0.01W 0402
3152	3198 031 01820	1.8kΩ 5% 0.01W 0402
3153	3198 031 01220	1.2kΩ 5% 0.01W 0402
3154	3198 031 04730	47Ω 5% 0402
3155	3198 031 08210	820Ω 5% 0.5W
3281	4822 117 13548	1kΩ 5% 0402
3282	4822 117 13548	1kΩ 5% 0402
3283	4822 117 13548	1kΩ 5% 0402
3284	4822 117 13548	1kΩ 5% 0402
3285	4822 051 30759	75Ω 5% 0.062W
3302	3198 031 01220	1.2kΩ 5% 0.01W 0402
3303	3198 031 06820	6.8kΩ 5% 0.01W 0402
3304	4822 117 13597	330Ω 5% 0.01W 0402
3305	4822 117 13548	1kΩ 5% 0402
3306	3198 031 03390	33Ω 1% 0402
3307	2322 705 70189	18Ω 0402
3309	4822 051 30331	330Ω 5% 0.062W
3310	3198 031 01220	1.2kΩ 5% 0.01W 0402
3311	3198 031 03390	33Ω 1% 0402
3312	3198 031 08210	820Ω 5% 0.5W
3313	4822 117 13596	220Ω 5% 0.01W 0402
3316	2322 705 70189	18Ω 0402
3318	3198 031 01220	1.2kΩ 5% 0.01W 0402
3319	4822 051 30331	330Ω 5% 0.062W
3320	3198 031 01220	1.2kΩ 5% 0.01W 0402
3321	3198 031 03390	33Ω 1% 0402
3322	3198 031 08210	820Ω 5% 0.5W
3323	4822 117 13596	220Ω 5% 0.01W 0402
3326	4822 117 13543	470Ω 5% 0402
3329	4822 051 30331	330Ω 5% 0.062W
3330	3198 031 01220	1.2kΩ 5% 0.01W 0402
3331	3198 031 03390	33Ω 1% 0402
3332	3198 031 08210	820Ω 5% 0.5W
3333	4822 117 13596	220Ω 5% 0.01W 0402
3334	3198 031 03390	33Ω 1% 0402
3335	3198 031 03390	33Ω 1% 0402
3336	3198 031 03390	33Ω 1% 0402
3337	3198 031 03390	33Ω 1% 0402
3338	2322 705 70189	18Ω 0402
3340	4822 117 13548	1kΩ 5% 0402
3343	4822 117 13606	10kΩ 5% 0.01W 0402
3345	3198 031 06820	6.8kΩ 5% 0.01W 0402
3346	4822 117 13548	1kΩ 5% 0402
3347	4822 117 13601	22kΩ 5% 0402
3348	4822 117 13601	22kΩ 5% 0402
3349	3198 031 04730	47Ω 5% 0402
3350	4822 117 13596	220Ω 5% 0.01W 0402
3351	4822 117 13548	1kΩ 5% 0402
3352	3198 031 04730	47Ω 5% 0402
3353	4822 117 13606	10kΩ 5% 0.01W 0402
3354	4822 117 13606	10kΩ 5% 0.01W 0402
3355	4822 117 13601	22kΩ 5% 0402
3356	3198 031 08210	820Ω 5% 0.5W
3357	4822 117 13601	22kΩ 5% 0402
3358	5322 117 11726	10Ω 5%
3361	4822 117 13605	Jumper 0402
3364	2322 705 70124	120kΩ 5% 0402
3365	4822 117 13605	Jumper 0402
3366	4822 117 13602	2.2kΩ 5% 0.01W 0402
3367	4822 117 13548	1kΩ 5% 0402
3368	3198 031 06830	68kΩ 5% 0.01W 0402
3371	4822 117 13548	1kΩ 5% 0402
3372	2322 705 70155	1.5MΩ 5% 0402
3373	4822 117 13606	10kΩ 5% 0.01W 0402
3374	3198 031 02720	2.7kΩ 5% 0.01W 0402
3375	3198 031 02720	2.7kΩ 5% 0.01W 0402
3376	4822 117 13606	10kΩ 5% 0.01W 0402
3377	2322 705 70125	1.2mΩ 0402
3378	3198 031 03340	330kΩ 5% 0402
3380	4822 117 13606	10kΩ 5% 0.01W 0402
3382	4822 117 13548	1kΩ 5% 0402
3384	4822 117 13606	10kΩ 5% 0.01W 0402
3385	3198 031 04730	47Ω 5% 0402
3386	3198 031 02730	27kΩ 5% 0402
3390	4822 117 13548	1kΩ 5% 0402
3391	3198 031 03930	39kΩ 5% 0402
3392	3198 031 04730	47Ω 5% 0402
3393	3198 031 03320	3.3kΩ 5% 0402
3395	4822 117 13606	10kΩ 5% 0.01W 0402
3396	4822 117 13543	470Ω 5% 0402
3397	4822 117 13543	470Ω 5% 0402
3398	4822 117 13545	100Ω 1% 0402
3480	3198 031 02720	2.7kΩ 5% 0.01W 0402
3481	3198 031 02720	2.7kΩ 5% 0.01W 0402
3482	3198 031 04720	4.7kΩ 5% 0402
3483	3198 031 08220	8.2kΩ 5% 0.5W
3484	3198 031 04720	4.7kΩ 5% 0402
3485	3198 031 08220	8.2kΩ 5% 0.5W
3501	4822 117 13606	10kΩ 5% 0.01W 0402
3502	4822 117 13606	10kΩ 5% 0.01W 0402
3503	4822 117 13606	10kΩ 5% 0.01W 0402
3504	4822 117 13606	10kΩ 5% 0.01W 0402
3507	4822 117 13606	10kΩ 5% 0.01W 0402
3508	3198 031 04720	4.7kΩ 5% 0402
3509	3198 031 02720	2.7kΩ 5% 0.01W 0402
3510	3198 031 02720	2.7kΩ 5% 0.01W 0402
3511	4822 117 13546	47Ω 5% 0402
3512	4822 117 13546	47Ω 5% 0402
3513	3198 031 02720	2.7kΩ 5% 0.01W 0402
3514	3198 031 01220	1.2kΩ 5% 0.01W 0402
3515	3198 031 02720	2.7kΩ 5% 0.01W 0402
3523	4822 117 13606	10kΩ 5% 0.01W 0402
3530	4822 117 11297	100kΩ 5% 0.1W
3547	3198 031 03390	33Ω 1% 0402
3550	3198 031 04720	4.7kΩ 5% 0402
3557	4822 117 13546	47Ω 5% 0402
3563	4822 117 13606	10kΩ 5% 0.01W 0402
3564	4822 117 13606	10kΩ 5% 0.01W 0402
3565	4822 117 13606	10kΩ 5% 0.01W 0402
3570	4822 117 13602	2.2kΩ 5% 0.01W 0402
3571	3198 031 02720	2.7kΩ 5% 0.01W 0402
3572	4822 117 13606	10kΩ 5% 0.01W 0402
3581	4822 117 13545	100Ω 1% 0402
3582	4822 117 13606	10kΩ 5% 0.01W 0402
3583	3198 031 01830	18kΩ 5% 0.01W 0402
3586	4822 117 13601	22kΩ 5% 0402
3590	4822 117 13548	1kΩ 5% 0402
3651	5322 117 13036	1.2kΩ 1% 0.063W 0603
3652	2322 704 62702	2.7kΩ 1%
3737	3198 031 03390	33Ω 1% 0402
3904	4822 117 13605	Jumper 0402
3909	4822 117 13545	100Ω 1% 0402
3911	4822 117 13545	100Ω 1% 0402
3918	4822 117 13545	100Ω 1% 0402
3919	4822 117 13545	100Ω 1% 0402
3928	4822 117 13545	100Ω 1% 0402
3929	4822 117 13545	100Ω 1% 0402
3936	4822 117 13545	100Ω 1% 0402
3938	4822 117 13545	100Ω 1% 0402
3950	4822 117 13545	100Ω 1% 0402
3951	4822 117 13545	100Ω 1% 0402
3962	4822 117 13545	100Ω 1% 0402
3963	4822 117 13545	100Ω 1% 0402
3964	4822 117 13545	100Ω 1% 0402
3975	4822 117 13545	100Ω 1% 0402
3976	4822 117 13545	100Ω 1% 0402
3977	4822 117 13545	100Ω 1% 0402
3978	4822 117 13545	100Ω 1% 0402
3979	4822 117 13545	100Ω 1% 0402
3980	4822 117 13545	100Ω 1% 0402
4101	4822 117 13605	Jumper 0402
4104	4822 117 13605	Jumper 0402
4107	4822 117 13605	Jumper 0402
4363	4822 117 13605	Jumper 0402
4430	4822 117 13605	Jumper 0402
4431	4822 117 13605	Jumper 0402
4570	4822 117 13605	Jumper 0402
4791	4822 117 13605	Jumper 0402
4792	4822 117 13605	Jumper 0402
4795	4822 117 13605	Jumper 0402

–~~–

5060	2422 549 44197	Bead 220Ω at 100MHz
5061	2422 549 44197	Bead 220Ω at 100MHz
5062	2422 549 44197	Bead 220Ω at 100MHz
5063	2422 549 44197	Bead 220Ω at 100MHz
5101	3198 018 34770	0.47µH 10% 0805
5102	2422 549 44197	Bead 220Ω at 100MHz
5112	2422 549 44197	Bead 220Ω at 100MHz
5134	2422 549 44197	Bead 220Ω at 100MHz
5135	2422 549 44197	Bead 220Ω at 100MHz
5150	2422 549 44197	Bead 220Ω at 100MHz
5151	2422 549 44197	Bead 220Ω at 100MHz
5152	2422 549 44197	Bead 220Ω at 100MHz
5281	2422 549 44197	Bead 220Ω at 100MHz
5282	2422 549 44197	Bead 220Ω at 100MHz
5283	2422 549 44197	Bead 220Ω at 100MHz
5285	2422 549 44197	Bead 220Ω at 100MHz
5300	2422 549 44197	Bead 220Ω at 100MHz
5307	4822 051 20008	Jumper 0805
5317	4822 051 20008	Jumper 0805
5327	4822 051 20008	Jumper 0805
5328	4822 051 20008	Jumper 0805
5342	2422 549 44197	Bead 220Ω at 100MHz
5343	2422 549 44197	Bead 220Ω at 100MHz
5344	2422 549 44197	Bead 220Ω at 100MHz
5345	2422 549 44197	Bead 220Ω at 100MHz
5450	2422 549 44197	Bead 220Ω at 100MHz
5452	2422 549 44197	Bead 220Ω at 100MHz
5480	2422 549 44197	Bead 220Ω at 100MHz
5570	2422 549 44197	Bead 220Ω at 100MHz
5583	2422 549 44197	Bead 220Ω at 100MHz
5600	4822 157 11716	Bead 30Ω at 100MHz
5601	2422 549 44197	Bead 220Ω at 100MHz
5651	2422 535 94134	10µH 20% 0805
5654	2422 536 00734	1µH 1210
5659	4822 157 71334	0.68µH 5% 1008

5730	2422 549 44197	Bead 220Ω at 100MHz
5731	2422 549 44197	Bead 220Ω at 100MHz
5792	2422 549 44197	Bead 220Ω at 100MHz

6030	4822 130 11397	BAS316
6101	4822 130 11525	1SS356
6301	4822 130 11397	BAS316
6327	9322 102 64685	UDZ2.7B
6341	4822 130 11397	BAS316
6353	5322 130 34337	BAV99
6365	5322 130 34337	BAV99
6367	9340 548 67115	PDZ22B
6368	4822 130 11397	BAS316
6381	5322 130 34337	BAV99
6382	9322 150 18685	BZX384-C47
6384	9340 548 67115	PDZ22B
6385	4822 130 11397	BAS316
6397	9340 548 69115	PDZ27B
6398	4822 130 11397	BAS316
6480	9322 129 41685	BZM55-C12
6481	9322 129 41685	BZM55-C12
6651	9322 128 70685	SMSS14

Software (See Product Survey)

0601	3139 127 03603	

7031	9340 425 20115	BC847BS
7060	9340 425 30115	BC847BPN
7062	4822 130 60373	BC856B
7063	4822 130 60373	BC856B
7100	9352 767 55557	PNX3000HL/N3
7101	3198 010 42310	BC847BW
7150	9340 425 20115	BC847BS
7300	9352 774 07557	PNX3002E/N404
7300	9352 774 14557	PNX3008E/N404
7300	9352 779 27557	PNX3002E/N302/G
7301	4822 130 60373	BC856B
7302	4822 130 60373	BC856B
7303	4822 130 60373	BC856B
7304	3198 010 42310	BC847BW
7310	9340 425 30115	BC847BPN
7320	9340 425 30115	BC847BPN
7330	9340 425 30115	BC847BPN
7346	4822 130 60373	BC856B
7356	4822 130 60373	BC856B
7365	5322 130 60159	BC846B
7382	4822 130 60373	BC856B
7383	9340 425 30115	BC847BPN
7393	3198 010 42310	BC847BW
7480	4822 209 33165	TDA1308T/N1
7525	9322 130 41668	M24C64-WMN6
7581	9322 212 24685	PST596C
7650	9322 170 61668	CS51033YDR8
7651	9322 170 87668	STS5PF30L
7730	9322 166 67668	MT48LC4M16A2TG-7E
7730	9322 207 15668	K4S641632H-TC75
7790		SW see “Software”

Side I/O Panel [D]

Various

0240	2422 025 12485	Connector 11p m
0240	2422 025 17309	Connector 11p m
0241	4822 267 10734	Connector 5p
0242	4822 267 10734	Connector 5p
0306	3139 124 31651	Side I/O bracket
1254	2422 026 05703	Socket Cinch 1p f
1254	4822 267 31014	Soc. headphone
1255	4822 265 11606	Connector 3p
1256	2422 026 04926	Soc. Mini-DIN 4p f
1326	4822 267 10975	Soc. Cinch f YeWhRd
1327	2422 026 05703	Socket Cinch 1p f
1328	2422 026 05494	7P Female
1936	2422 025 17309	Connector 11p m
8620	3139 131 06241	Cable 11p/560/11p Bk

2286	4822 122 33642	150pF 5% 50V
2288	4822 122 33642	150pF 5% 50V
2292	5322 122 32311	470pF 10% 100V
2294	5322 122 32311	470pF 10% 100V
2296	2238 780 55652	150nF 16V
2296	4822 121 41854	150nF 5% 63V
2297	2238 780 55652	150nF 16V
2297	4822 121 41854	150nF 5% 63V
2804	5322 122 32531	100pF 5% 50V
2805	5322 122 32531	100pF 5% 50V
2832	2238 780 55652	150nF 16V
2834	2238 780 55652	150nF 16V

3285	4822 116 52201	75Ω 5% 0.5W
3286	4822 116 52176	10Ω 5% 0.5W
3287	4822 116 52201	75Ω 5% 0.5W
3288	4822 116 52176	10Ω 5% 0.5W
3289	4822 116 52249	1.8Ω 5% 0.5W
3291	4822 050 11002	1kΩ 1% 0.4W
3292	4822 117 10834	47kΩ 1% 0.1W
3293	4822 050 11002	1kΩ 1% 0.4W
3294	4822 117 10834	47kΩ 1% 0.1W
3295	4822 116 52276	3.9Ω 5% 0.5W
3296	4822 117 10833	10kΩ 1% 0.1W
3297	4822 117 10833	10kΩ 1% 0.1W
3801	4822 117 11927	75Ω 1% 0.1W
3802	4822 116 52201	75Ω 5% 0.5W
3805	4822 117 10834	47kΩ 1% 0.1W
3806	4822 117 10834	47kΩ 1% 0.1W
3808	4822 051 20008	Jumper 0805
3809	4822 117 11373	100Ω 1% 0805
3816	4822 117 11373	100Ω 1% 0805
3830	4822 050 21003	10kΩ 1% 0.6W
3835	4822 116 52276	3.9Ω 5% 0.5W
3842	4822 050 21003	10kΩ 1% 0.6W
3850	4822 116 52249	1.8Ω 5% 0.5W
4241	4822 051 20008	Jumper 0805
4243	4822 051 20008	Jumper 0805
4800	4822 051 20008	Jumper 0805
4801	4822 051 20008	Jumper 0805
4802	4822 051 20008	Jumper 0805
4803	4822 051 20008	Jumper 0805
4805	4822 051 20008	Jumper 0805
4808	4822 051 20008	Jumper 0805
4813	4822 051 20008	Jumper 0805

5291	2422 549 43062	Bead 600Ω at 100MHz
5292	2422 549 43062	Bead 600Ω at 100MHz
5801	2422 549 43062	Bead 600Ω at 100MHz
5802	2422 549 43062	Bead 600Ω at 100MHz

6291	9322 129 41685	BZM55-C12
6292	9322 129 41685	BZM55-C12
6293	9322 129 41685	BZM55-C12
6294	9322 129 41685	BZM55-C12
6296	9322 129 41685	BZM55-C12
6297	9322 129 41685	BZM55-C12
6801	4822 130 11416	PDZ6.8B
6802	4822 130 11416	PDZ6.8B
6803	4822 130 11551	UDZS10B
6804	4822 130 11551	UDZS10B
6805	4822 130 11551	UDZS10B
6806	4822 130 11551	UDZS10B
6807	4822 130 11416	PDZ6.8B
6808	4822 130 11416	PDZ6.8B

Control Panel [E]

Various

0158	3104 311 02021	Cable 3p/1000/3pp
0215	2422 025 16601	Connector 3p m
0215	4822 267 10748	Connector 3p
0345	4822 267 10748	Connector 3p
1091	4822 276 13775	Switch 1p 0.1A 12V
1092	4822 276 13775	Switch 1p 0.1A 12V
1093	4822 276 13775	Switch 1p 0.1A 12V
1094	4822 276 13775	Switch 1p 0.1A 12V
1095	4822 276 13775	Switch 1p 0.1A 12V
1701	4822 276 13775	Switch 1p 0.1A 12V
1702	4822 276 13775	Switch 1p 0.1A 12V
1703	4822 276 13775	Switch 1p 0.1A 12V
1704	4822 276 13775	Switch 1p 0.1A 12V
1705	4822 276 13775	Switch 1p 0.1A 12V
8345	3104 311 01101	Cable 3p/1000/3p
8945	3104 311 04671	Cable 3p/1200/3p
8945	3104 311 05951	Cable 3p/680/3p

2010	5322 126 11583	10nF 10% 50V 0603

3008	2322 730 61911	910Ω 0805
3010	4822 117 11139	1.5kΩ 1% 0.1W
3011	2322 730 81202	2kΩ 0805
3013	4822 051 20332	2.3kΩ 5% 0.1W
3014	4822 051 20512	5K10 5% 0,1W
3091	4822 051 30561	560Ω 5% 0.062W
3092	4822 051 30391	390Ω 5% 0.062W
3093	4822 051 30561	560Ω 5% 0.062W
3094	4822 051 30271	270Ω 5% 0.062W
3095	4822 051 30332	3.3Ω 5% 0.062W
3096	4822 051 30152	1.5Ω 5% 0.062W
3099	4822 051 30102	1kΩ 5% 0.062W
9000	4822 051 20008	Jumper 0805
9001	4822 051 20008	Jumper 0805
9002	4822 051 20008	Jumper 0805

6092	4822 130 80622	BAT54

CRT Panel [F]

Various

1317	3139 121 27391	Double Comp Clip
1335	3104 301 08281	Connector 1p
1340	4822 265 30735	Connector 5p
1351	4822 265 41113	Connector 7p
1354	2422 500 00004	Soc. CRT 10p 15-19kV
1354	2422 500 80087	Socket CRT 9p
1361	4822 267 10735	Connector 3p
1382	4822 267 10735	Connector 3p

2313	4822 124 12373	47µF 20% 250V
2317	5322 121 44356	4.7nF 5% 2kV
2319	4822 122 30043	10nF 80% 63V
2332	4822 126 13193	4.7nF 10% 63V
2333	3198 016 36810	680pF 25V 0603
2336	3198 017 33330	33nF 20% 16V 0603
2338	2022 318 00109	100nF 250V
2339	2022 318 00109	100nF 250V
2340	2022 318 00109	100nF 250V
2343	3198 016 36810	680pF 25V 0603
2344	4822 126 13193	4.7nF 10% 63V
2346	3198 017 33330	33nF 20% 16V 0603
2347	4822 124 80791	470µF 20% 16V
2352	4822 126 13193	4.7nF 10% 63V
2353	3198 016 36810	680pF 25V 0603
2356	3198 017 33330	33nF 20% 16V 0603
2357	5322 126 11583	10nF 10% 50V 0603
2361	2238 586 59812	100nF 20% 50V 0603
2363	4822 124 40764	22µF 100V
2365	4822 126 13193	4.7nF 10% 63V
2367	2238 586 59812	100nF 20% 50V 0603
2368	4822 124 40764	22µF 100V
2369	4822 126 14241	330pF 0603 50V
2370	2238 586 59812	100nF 20% 50V 0603
2371	3198 016 35680	5.6pF 0.5pF 50V 0603
2371	4822 122 33741	10pF 10% 50V
2372	3198 016 35680	5.6pF 0.5pF 50V 0603
2372	4822 122 33741	10pF 10% 50V
2373	3198 016 35680	5.6pF 0.5pF 50V 0603
2373	4822 122 33741	10pF 10% 50V
2374	4822 126 12102	330nF 10% 16V 0805
2375	3198 017 34730	47nF 16V 0603
2381	4822 124 40433	47µF 20% 25V
2382	4822 126 13193	4.7nF 10% 63V
2383	2238 930 11541	220pF 5% 200V
2384	2238 586 59812	100nF 20% 50V 0603
2385	2238 586 59812	100nF 20% 50V 0603
2386	2020 552 94427	100pF 5% 50V
2386	3198 017 34730	47nF 16V 0603
2387	4822 126 14507	18pF 5% 50V 0603
2388	4822 126 13193	4.7nF 10% 63V
2389	2238 586 59812	100nF 20% 50V 0603
2390	4822 124 11947	10µF 20% 16V

3305▲	4822 052 10108	1Ω 5% 0.33W
3306	4822 052 10478	4.7Ω 5% 0.33W

3306▲	4822 052 10568	5.6Ω 5% 0.33W
3306▲	4822 052 11338	3.3Ω 5% 0,5W
3306	4822 052 11688	6Ω8 5% 0.5W
3307	4822 052 10478	4.7Ω 5% 0.33W
3307▲	4822 052 10568	5.6Ω 5% 0.33W
3307▲	4822 052 11338	3.3Ω 5% 0,5W
3317	4822 050 11002	1kΩ 1% 0.4W
3318▲	4822 052 10109	10Ω 5% 0.33W
3319	4822 051 30154	150kΩ 5% 0.062W
3320	4822 051 30223	22kΩ 5% 0.062W
3321	4822 051 30154	150kΩ 5% 0.062W
3321	4822 051 30684	680kΩ 5% 0.062W
3322	4822 051 30154	150kΩ 5% 0.062W
3325	3198 021 31820	1.8kΩ 5% 0.062W 0603
3331	4822 116 52175	100Ω 5% 0.5W
3332	3198 013 04710	470Ω 20% 0.5W
3333	4822 116 52175	100Ω 5% 0.5W
3334	3198 013 04710	470Ω 20% 0.5W
3335	4822 116 52175	100Ω 5% 0.5W
3336	3198 013 04710	470Ω 20% 0.5W
3337▲	2322 242 13104	100kΩ 20W
3337	4822 050 21004	100kΩ 1% 0.6W
3338	4822 051 30222	2.2kΩ 5% 0.062W
3339	4822 051 30272	2.7kΩ 5% 0.062W
3340	4822 051 30102	1kΩ 5% 0.062W
3341▲	2322 242 13104	100kΩ 20W
3341	4822 050 21004	100kΩ 1% 0.6W
3342	4822 051 30272	2.7kΩ 5% 0.062W
3343	4822 051 30222	2.2kΩ 5% 0.062W
3344	4822 050 11002	1kΩ 1% 0.4W
3345	4822 050 23309	33Ω 1% 0,6W
3347	3198 013 01520	1.5kΩ 20% 0.5W
3348	4822 050 11002	1kΩ 1% 0.4W
3350	4822 050 21003	10kΩ 1% 0.6W
3351▲	2306 207 03151	150Ω 5% 0.5W
3352▲	2322 242 13104	100kΩ 20W
3352	4822 050 21004	100kΩ 1% 0.6W
3353	4822 051 30222	2.2kΩ 5% 0.062W
3354	4822 051 30272	2.7kΩ 5% 0.062W
3355	4822 051 30102	1kΩ 5% 0.062W
3357▲	2122 552 00004	1mA 18V 0603
3358	4822 051 30472	4.7Ω 5% 0.062W
3359	4822 051 30682	6.8Ω 5% 0.062W
3360	4822 051 30221	220Ω 5% 0.062W
3361	4822 050 24701	470Ω 1% 0.6W
3361	4822 116 83883	470Ω 5% 0.5W
3362▲	2120 108 94133	R Fuse 10Ω
3363	4822 051 30561	560Ω 5% 0.062W
3364	4822 051 20108	1Ω 5% 0.1W
3364	4822 051 20228	2.2Ω 5% 0.1W
3365	4822 051 30472	4.7Ω 5% 0.062W
3366	4822 051 30683	68kΩ 5% 0.062W
3367	4822 116 52297	68kΩ 5% 0.5W
3368	4822 051 30561	560Ω 5% 0.062W
3370	4822 051 20108	1Ω 5% 0.1W
3370	4822 051 20228	2.2Ω 5% 0.1W
3371	2312 915 11002	1kΩ 1% 0.5W
3371	4822 116 52226	560Ω 5% 0.5W
3372	2312 915 11002	1kΩ 1% 0.5W
3375	4822 051 30681	680Ω 5% 0.062W
3377	4822 051 30121	120Ω 5% 0.062W
3377	4822 051 30272	2.7kΩ 5% 0.062W
3378	4822 051 30221	220Ω 5% 0.062W
3378	4822 117 12971	15Ω 5% 0603 0.62W
3379	2322 702 60511	510Ω 5% 0603
3380	4822 051 30222	2.2kΩ 5% 0.062W
3381	4822 051 30222	2.2kΩ 5% 0.062W
3385	4822 051 30681	680Ω 5% 0.062W
3385	4822 051 30682	6.8Ω 5% 0.062W
3389▲	2120 108 94132	1Ω 1206
3392	4822 051 30271	270Ω 5% 0.062W
3393	4822 051 30109	10Ω 5% 0.062W
3393	4822 051 30569	56Ω 5% 0.062W
3394	4822 051 30472	4.7Ω 5% 0.062W
3395	4822 116 52219	330Ω 5% 0.5W
3396	3198 021 31820	1.8kΩ 5% 0.062W 0603
3998	4822 117 11817	1.2kΩ 1% 0.0625W
3999	4822 117 11817	1.2kΩ 1% 0.0625W
4310	4822 051 20008	Jumper 0805
4322	4822 051 20008	Jumper 0805

5303	4822 157 11867	5.6µH 5%
5304	4822 526 10704	Bead 50 Ω at 100MHz
5308	4822 157 11867	5.6µH 5%
5339	4822 526 10704	Bead 50 Ω at 100MHz
5346	4822 526 10704	Bead 50 Ω at 100MHz
5347	4822 157 11139	6.8µH 5%
5348	4822 157 11139	6.8µH 5%
5349	4822 157 11139	6.8µH 5%
5361	4822 157 11411	Bead 80Ω at 100MHz

6307	4822 130 11416	PDZ6.8B
6325	4822 130 10838	UDZ3.3B
6331	9322 197 45703	BAV21WS
6332	9322 197 45703	BAV21WS
6333	9322 197 45703	BAV21WS
6334	4822 130 10838	UDZ3.3B
6335	5322 130 34337	BAV99
6336	5322 130 34337	BAV99
6361	4822 130 11397	BAS316
6389	9340 548 52115	PDZ5.1B

7330	4822 209 33365	TDA6111Q/N4
7331	4822 130 60373	BC856B
7332	4822 130 41246	BC327-25
7333	4822 130 40981	BC337-25
7340	4822 209 33365	TDA6111Q/N4
7350	4822 209 33365	TDA6111Q/N4
7361	4822 130 60887	BF840
7361	5322 130 60159	BC846B
7362	4822 130 60373	BC856B
7362	4822 130 60383	BF824
7363	9322 195 05687	KTB631KY
7364	9322 195 14687	KTD600KY
7365	4822 130 60887	BF840
7366	9352 628 51112	TDA8941p/N1

Front Interface Panel [M] + [Q]

Various

0201	2422 025 16268	Connector 2p m
0201▲	2422 025 16374	Connector 2p m
0202	2422 025 16268	Connector 2p m
0203	2422 025 06353	Connector 5p m
0242	2422 025 06353	Connector 5p m
0247	4822 267 10734	Connector 5p
1002	4822 276 13775	Switch 1p 0.1A 12V
1003	4822 276 13775	Switch 1p 0.1A 12V
1004	4822 276 13775	Switch 1p 0.1A 12V
1005	4822 276 13775	Switch 1p 0.1A 12V
1010	9322 206 78667	TSOP34836UH1B
1031▲	2422 128 02972	Switch power 2p 8/128A
1040	9322 155 82667	TSOP2236
1040	9322 206 78667	TSOP34836UH1B
1050	2422 025 06353	Connector 5p m
1051	2422 128 02972	Switch power 2p 8/128A
1060	3139 188 89901	Front Int SL5 ESP Salsa
1910	9322 206 78667	TSOP34836UH1B
1951	2422 128 02972	Switch power 2p 8/128A
8202	3104 311 03011	Cable 2p/340/2p Bk
8302▲	4822 320 12513	Wiring VH 2p 480
8341▲	3104 311 02471	Cable 5p/680/5p INS
8624	3104 311 10181	Cable 5p/820/5p

2001	4822 124 41584	100µF 20% 10V
2003	4822 122 30043	10nF 80% 63V
2030	4822 124 41584	100µF 20% 10V
2040	4822 124 40248	10µF 20% 63V
2930	4822 124 41584	100µF 20% 10V

3002	4822 051 30681	680Ω 5% 0.062W
3006	4822 051 30331	330Ω 5% 0.062W
3007	4822 116 52175	100Ω 5% 0.5W
3011	4822 116 52226	560Ω 5% 0.5W
3013	4822 116 83881	390Ω 5% 0.5W
3015	4822 116 52226	560Ω 5% 0.5W
3017	4822 116 83876	270Ω 5% 0.5W
3018	4822 116 52243	1.5kΩ 5% 0.5W
3019	4822 116 52269	3.3kΩ 5% 0.5W
3031▲	4822 053 21335	3.3MΩ 5% 0.5W
3032▲	4822 053 21335	3.3MΩ 5% 0.5W
3040	4822 117 11503	220Ω 1% 0.1W
3052	4822 051 30681	680Ω 5% 0.062W
3057	4822 053 21335	3.3MΩ 5% 0.5W
3066	4822 053 21335	3.3MΩ 5% 0.5W
3078	4822 051 30101	100Ω 5% 0.062W
3081	4822 051 30681	680Ω 5% 0.062W
3082	4822 117 13577	330Ω 1% 1.25W 0805
3957	4822 053 21335	3.3MΩ 5% 0.5W
3966	4822 053 21335	3.3MΩ 5% 0.5W
3981	4822 051 30681	680Ω 5% 0.062W
3982	4822 116 52219	330Ω 5% 0.5W
9002	3198 036 90010	Wire 0.58mm
9003	3198 036 90010	Wire 0.58mm
9044	3198 036 90010	Wire 0.58mm

6001	9322 050 99682	LTL-10224WHCR
6001	9322 110 34682	TLDR5400
6003	4822 130 31983	BAT85
6004	9322 206 78667	TSOP34836UH1B
6050	9322 110 34682	TLDR5400
6901	9322 050 99682	LTL-10224WHCR

11. Revision List

Manual xxxx xxx xxxx.0

- First release.

Manual xxxx xxx xxxx.1

- Chapter 10: Spare parts list updated